



# Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for SIEMENS GIGASET S150/ DUO. You'll find the answers to all your questions on the SIEMENS GIGASET S150/ DUO in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

## User manual SIEMENS GIGASET S150/ DUO User guide SIEMENS GIGASET S150/ DUO Operating instructions SIEMENS GIGASET S150/ DUO Instructions for use SIEMENS GIGASET S150/ DUO Instruction manual SIEMENS GIGASET S150/ DUO

### Gigaset

**EN** Dear Customer,  
Gigaset Communications GmbH is the legal successor to Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), which in turn continues the Gigaset business of Siemens AG. Any statements made by Siemens AG or SHC that are found in the user guides should therefore be understood as statements of Gigaset Communications GmbH.  
We hope you enjoy your Gigaset.

**DE** Sehr geehrte Kunden, sehr geehrter Kunde,  
die Gigaset Communications GmbH ist Rechtsnachfolgerin der Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), die ihrerseits das Gigaset Geschäft der Siemens AG fortführt. Ewige Erklärungen der Siemens AG oder der SHC über Bedienungsanleitungen sind daher als Erklärungen der Gigaset Communications GmbH zu verstehen.  
Wir wünschen Ihnen viel Freude mit Ihrem Gigaset.

**FR** Chère Cliente, Cher Client,  
la société Gigaset Communications GmbH succède en droit à Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) qui poursuit elle-même les activités Gigaset de Siemens AG. Donc, les éventuelles explications de Siemens AG ou de SHC, figurant dans les modes d'emploi doivent être comprises comme des explications de Gigaset Communications GmbH.  
Nous vous souhaitons beaucoup d'agrement avec votre Gigaset.

**IT** Gentile cliente,  
la Gigaset Communications GmbH è successore della Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) che a sua volta ha proseguito l'attività della Siemens AG. Eventuali dichiarazioni della Siemens AG o della SHC nei manuali d'istruzione, vanno pertanto intese come dichiarazioni della Gigaset Communications GmbH. Le auguriamo tanta soddisfazione con il vostro Gigaset.

**NL** Geachte klant,  
Gigaset Communications GmbH is de rechtsopvolger van Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), de onderneming die de Gigaset-activiteiten van Siemens AG heeft voortgezet. Eventuele uitspraken of mededelingen van Siemens AG of SHC in de gebruiksaanwijzingen dienen daarom als mededelingen van Gigaset Communications GmbH te worden gezien.  
Wij wensen u veel plezier met uw Gigaset.

**ES** Estimado cliente,  
la Gigaset Communications GmbH es derechohabiente de la Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) que por su parte continuó el negocio Gigaset de la Siemens AG. Las posibles declaraciones de la Siemens AG o de la SHC en las instrucciones de uso se deben entender por lo tanto como declaraciones de la Gigaset Communications GmbH.  
Le deseamos que disfrute con su Gigaset.

**PT** Scații clienți,  
Gigaset Communications GmbH é a sucessora legal da Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), que, por sua vez, deu continuidade ao sector de negócios Gigaset, da Siemens AG. Quaisquer declarações por parte da Siemens AG ou da SHC encontradas nos manuais de utilização deverão, portanto, ser consideradas como declarações da Gigaset Communications GmbH. Desejamos que tenham bons momentos com o seu Gigaset.

Issued by  
Gigaset Communications GmbH  
Schillerstrasse 66, D-45999 Bocholt  
Gigaset Communications GmbH is a trademark  
licensee of Siemens AG

**DA** Kære Kunde,  
Gigaset Communications GmbH er retlig arvtager af Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som fra deres side videregiver Siemens AGs Gigaset-forretninger. Siemens AG eller SHCs eventuelle forklaringer i betjeningsvejledningen skal derfor forstås som Gigaset Communications GmbHs forklaringer. Vi håber, du får meget glæde af din Gigaset.

**FI** Arvoisa asiakkaamme,  
Gigaset Communications GmbH on Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) yrityksen oikeudenomistaja, joka jatkaa puolestaan Siemens AG:n Gigaset liiketoimintaa. Käyttöoppaissa mahdollisesti esitetyt Siemens AG:n tai SHC:n selosteet on tämän vuoksi ymmärrettävä Gigaset Communications GmbH:n selosteina.  
Toivottamme teille paljon iloa Gigaset-laitteestanne.

**SV** Kära kund,  
Gigaset Communications GmbH övertar rättigheterna från Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som bedriv Gigaset-verksamheten efter Siemens AG. Alla förklaringar från Siemens AG eller SHC i användarhandboken gäller därför som förklaringar från Gigaset Communications GmbH.  
Vi önskar dig mycket njota med din Gigaset.

**NO** Kjære kunde,  
Gigaset Communications GmbH er rettslig etterfølger etter Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som i sin tur videreførte Gigaset-geopningen i Siemens AG. Eventuelle meddelelser fra Siemens AG eller SHC i brukerveiledningene er derfor å forstå som meddelelser fra Gigaset Communications GmbH.  
Vi håper du får stor glede av din Gigaset-enhet.

**EL** Αγαπητέ πελάτη,  
η Gigaset Communications GmbH είναι η νομική διάδοχος της Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), η οποία έχει αναλάβει την εταιρική διαχείριση της Gigaset της Siemens AG. Οι δηλώσεις της Siemens AG ή της SHC που υπάρχουν στα εγχειρίδια χρήσης, θεωρούνται δηλώσεις της Gigaset Communications GmbH.  
Σας ευχόμαστε καλή διασκέδαση με τη συσκευή σας Gigaset.

**HR** Poštovani korisniče,  
Gigaset Communications GmbH pravni je sljednik tvrtke Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), koji je nastavio Gigaset poslovanje tvrtke Siemens AG. Zato sve izjave tvrtke Siemens AG ili SHC koje se nalaze u uputama za upotrebu treba tumačiti kao izjave tvrtke Gigaset Communications GmbH.  
Nadamo se da će zadovoljstvom koristiti svoj Gigaset uređaj.

**SL** Spoštovani kupci!  
Podjetje Gigaset Communications GmbH je pravni naslednik podjetja Siemens Home and Office Communication Devices GmbH & Co. KG (SHC). Al naslednje dejavnosti znamko Gigaset podjetja Siemens AG. Vse izjave podjetja Siemens AG ali SHC v priročnikih za uporabo nitej veljajo kot izjave podjetja Gigaset Communications GmbH.  
Želimo vam veliko užitek ob uporabi naprave Gigaset.

© Gigaset Communications GmbH 2008  
All rights reserved.  
Subject to availability. Rights of modifications reserved.  
www.gigaset.com



[You're reading an excerpt. Click here to read official SIEMENS GIGASET S150/ DUO user guide](http://yourpdfguides.com/dref/4569525)  
<http://yourpdfguides.com/dref/4569525>

**Manual abstract:**

*@@@We hope you enjoy your Gigaset. @@@@Etwaige Erklärungen der Siemens AG oder der SHC in den Bedienungsanleitungen sind daher als Erklärungen der Gigaset Communications GmbH zu verstehen. Wir wünschen Ihnen viel Freude mit Ihrem Gigaset. Chre Cliente, Cher Client, la socit Gigaset Communications GmbH succde en droit Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) qui poursuivait elle-mme les activits Gigaset de Siemens AG. Donc les ventuelles explications de Siemens AG ou de SHC figurant dans les modes d'emploi doivent tre comprises comme des explications de Gigaset Communications GmbH. Nous vous souhaitons beaucoup d'agrment avec votre Gigaset. Gentile cliente, la Gigaset Communications GmbH successore della Siemens Home and Office Communication Devices GmbH & Co. @@@@Le auguriamo tanta soddisfazione con il vostro Gigaset. @@@@Eventuele uitspraken of mededelingen van Siemens AG of SHC in de gebruiksaanwijzingen dienen daarom als mededelingen van Gigaset Communications GmbH te worden gezien.*

*Wij wensen u veel plezier met uw Gigaset. Estimado cliente, la Gigaset Communications GmbH es derechohabiente de la Siemens Home and Office Communication Devices GmbH & Co. KG (SHC) que por su parte continu el negocio Gigaset de la Siemens AG. Las posibles declaraciones de la Siemens AG o de la SHC en las instrucciones de uso se deben entender por lo tanto como declaraciones de la Gigaset Communications GmbH. Le deseamos que disfrute con su Gigaset.*

*SCaros clientes, Gigaset Communications GmbH a sucessora legal da Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), que, por sua vez, deu continuidade ao sector de negcios Gigaset, da Siemens AG. Quaisquer declaraes por parte da Siemens AG ou da SHC encontradas nos manuais de utilizao devero, portanto, ser consideradas como declaraes da Gigaset Communications GmbH. Desejamos que tenham bons momentos com o seu Gigaset.*

*DA Kre Kunde, Gigaset Communications GmbH er retlig efterflger til Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som fra deres side videreftrte Siemens AGs Gigaset-forretninger. Siemens AGs eller SHCs eventuelle forklaringer i betjeningsvejledningerne skal derfor forst som Gigaset Communications GmbHs forklaringer. Vi hber, du fr meget glde af din Gigaset. Arvoisa asiakkaamme, Gigaset Communications GmbH on Siemens Home and Office Communication Devices GmbH & Co. KG (SHC)-yrityksen oikeudenomistaja, joka jatko puolestaan Siemens AG:n Gigaset-liiketoimintaa. Kyttoppaissa mahdollisesti esiintyvt Siemens AG:n tai SHC:n selosteet on tmn vuoksi ymmrrttv Gigaset Communications GmbH:n selosteina. Toivotamme Teille paljon iloa Gigaset-laitteestanne. Kra kund, Gigaset Communications GmbH vertar rtigheterna frn Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som bedrev Gigaset-verksamheten efter Siemens AG. Alla frklaringar frn Siemens AG eller SHC i anvandarhandboken gller drfr som frklaringar frn Gigaset Communications GmbH.*

*Vi nskar dig mycket nje med din Gigaset. Kjre kunde, Gigaset Communications GmbH er rettslig etterflger etter Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), som i sin tur videreftrte Gigaset-geskjeften i Siemens AG. Eventuelle meddelelser fra Siemens AG eller SHC i bruksanvisningene er derfor forst som meddelelser fra Gigaset Communications GmbH. Vi hper du fr stor glede av din Gigaset-enhet. , Gigaset Communications GmbH Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), Gigaset Siemens AG. Siemens AG SHC Gigaset Communications GmbH. Gigaset. Postovani korisnici, Gigaset Communications GmbH pravni je sljednik tvrtke Siemens Home and Office Communication Devices GmbH & Co.*

*KG (SHC), koji je nastavio Gigaset poslovanje tvrtke Siemens AG. Zato sve izjave tvrtke Siemens AG ili SHC koje se nalaze u uputama za upotrebu treba tumaciti kao izjave tvrtke Gigaset Communications GmbH. Nadamo se da sa zadovoljstvom koristite svoj Gigaset ureaj. Spostovani kupec! Podjetje Gigaset Communications GmbH je pravni naslednik podjetja Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), ki nadaljuje dejavnost znamke Gigaset podjetja Siemens AG.*

*Vse izjave podjetja Siemens AG ali SHC v prirocnikih za uporabnike torej veljajo kot izjave podjetja Gigaset Communications GmbH. Zelimo vam veliko koristov ob uporabi naprave Gigaset. FI DE FR SV NO IT EL NL HR ES SL PT Issued by Gigaset Communications GmbH Schlavenhorst 66, D-46395 Bocholt Gigaset Communications GmbH is a trademark licensee of Siemens AG Gigaset Communications GmbH 2008 All rights reserved. Subject to availability. Rights of modifications reserved.*

*www.gigaset.com CS Vzen zkaznci, spolecnost Gigaset Communications GmbH je prvnm nstupcem spolecnosti Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), kter dle pejala segment produkt Gigaset spolecnosti Siemens AG. Jakkoli prohlsen spolecnosti Siemens AG nebo SHC, kter naleznete v uzivatelskch pruckch, je teba povazovat za prohlsen spolecnosti Gigaset Communications GmbH. Doufme, ze jste s produkty Gigaset spokojeni. Vzen zkaznk, Spolocnos Gigaset Communications GmbH je prvny nstupcom spolocnosti Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), ktor zasa pokracovala v cinnosti divzie Gigaset spolocnosti Siemens AG. Z tohto dvodu je potrebn vsetky vyhlshenia spolocnosti Siemens AG alebo SHC, ktor sa nachdzaj v pouzvatelskch pruckch, chpa ako vyhlshenia spolocnosti Gigaset Communications GmbH. Verme, ze budete so zariadenm Gigaset spokojn.*

*Stimate client, Gigaset Communications GmbH este succesorul legal al companiei Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), care, la rndul su, a continuat activitatea companiei Gigaset a Siemens AG. Orice afirmatii efectuate de Siemens AG sau SHC i incluse n ghidurile de utilizare vor fi, prin urmare, considerate a aparine Gigaset Communications GmbH. Sperem ca produsele Gigaset s fie la nlinea dorinelor dvs. Postovani potrosacu, Gigaset Communications GmbH je pravni naslednik kompanije Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), kroz koju je nastavljeno poslovanje kompanije Gigaset kao dela Siemens AG. Stoga sve izjave od strane Siemens AG ili SHC koje se mogu nai u korisnickim uputstvima treba tumaciti kao izjave kompanije Gigaset Communications GmbH. Nadamo se da ete uzivati u korisenju svog Gigaset ureaja. , Gigaset Communications GmbH Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), Siemens AG.*

*, Siemens AG SHC, , Gigaset Communications GmbH. Gigaset. Tisztelt Vsr! A Siemens Home and Communication Devices GmbH & Co. KG (SHC) trvnyes jogutdja a Gigaset Communications GmbH, amely a Siemens AG Gigaset zletgnak utdja. Ebb! kvetkezen a Siemens AG vagy az SHC felhasznli kziknyveiben tallhat brmely kijelentst a Gigaset Communications GmbH kijelentsnek kell tekinteni.*



**[You're reading an excerpt. Click here to read official SIEMENS GIGASET S150/ DUO user guide](http://yourpdfguides.com/dref/4569525)**  
<http://yourpdfguides.com/dref/4569525>

Remljk, megelgedssel hasznlja Gigaset kszlkt. PL SK Szanowny Kliencie, Firma Gigaset Communications GmbH jest spadkobierc prawnym firmy Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), ktra z kolei przejl segment produktw Gigaset od firmy Siemens AG. Wszelkie owiadczenia firm Siemens AG i SHC, ktre mona znale w instrukcjach obslugi, naley traktowa jako owiadczenia firmy Gigaset Communications GmbH. yczymy wiele przyjemnoci z korzystania z produktw Gigaset.

Sayin Mterimiz, Gigaset Communications GmbH, Siemens AG'nin Gigaset iletmesini yrten Siemens Home and Office Communication Devices GmbH & Co. KG (SHC)'nin yasal halefidir. Kullanma kilavuzlarında bulunan ve Siemens AG veya SHC tarafından yapılan bildiriler Gigaset Communications GmbH tarafından yapilmi bildiriler olarak algılanmalıdır. Gigaset'ten memnun kalmanızı mit ediyoruz. ! Gigaset Communications GmbH Siemens Home and Office Communication Devices GmbH & Co. KG (SHC), , Gigaset Siemens AG. , Siemens AG SHC , Gigaset Communications GmbH. , Gigaset . TR RO RU SR BG HU Issued by Gigaset Communications GmbH Schlavenhorst 66, D-46395 Bocholt Gigaset Communications GmbH is a trademark licensee of Siemens AG Gigaset Communications GmbH 2008 All rights reserved. Subject to availability.

Rights of modifications reserved. www.gigaset.com Telephone with answering machine Operating instructions and warranty Brief overview of the handset Brief overview of the handset Reception strength Talk key Accept a call Dial number Switch from handsfree Display (display field) Charging status flat full flashes: Battery almost flat or battery being charged Current functions and display keys The display keys give you access to the functions displayed. End call key and On/Off key End call Cancel function One menu level back (press briefly) Return to idle state (press for about 1 second) Handset on/off (press for about 2 seconds) Message key Access to the lists of to "handset" Control key Opens the menu, directory, Navigation in entry field Handsfree key Switch from "handset" to handsfree talking Illuminated: Handsfree talking is activated Flashes: incoming call, automatic redial Open directory Key 1 Select answering machine/network mailbox Star key Ringer tones on/off (press for about 2 seconds) Switch between uppercase, lowercase and number mode R key Enter pause (hold key down) INT 1 20.05.04 09:45 SMS SMS messages, network mailbox, caller/ answering machine Flashes: new SMS, message, calls Microphone Hash key Keypad protection on/off (press for about 1 second) Speed dial key Open speed dial list (press briefly) 1 Contents Contents Brief overview of the handset .

...

.....

.....

... 1 Safety precautions .....

.....

.....

... 6 Preparing the telephone .

.....

.....

. 7 Installing the base station .....

.....

.....

.....

.....

.....

..... 7 Connecting the base station ..

.....

.....

.....

... 8 Operating the handset ..

.....

.....

.....

.....

.....

... 9 Attaching the belt clip .....

.....

.....

.....

.....

.....

.....

.. 11 Activating/deactivating the handset .....

.....

.....

.....  
.....

*11 Activating/deactivating keypad protection .....*

.....  
.....  
.....

*... 11 Using the telephone and menus .....*

*.. 12 Keys ..*

.....  
.....  
.....  
.....

*Correcting entries .....*

.....  
.....  
.....  
.....

*... Idle state ..*

.....  
.....  
.....  
.....

*... Graphic main menu ..*

.....  
.....  
.....  
.....

*.... Example for menu operation: "Set volume for handsfree talking" .....*

*.... 12 13 14 14 14 Date and time functions .*

.....  
.....  
.....  
.....

*15 Setting the date and the time .....*

.....  
.....  
.....  
.....

*... Setting the alarm clock .....*

.....  
.....  
.....  
.....

.....  
. *Setting appointments . . . .*

.....  
.....  
.....  
.....  
.....

*Displayingck messages . . . . .*

.....  
.....  
.....  
.....

*. . . Recording infotexts . .*

.....  
.....  
.....  
.....

*. . . . . Operating the answering machine by voice command .*

.....  
.....  
.....

*. . Operating the answering machine away from home (remote operation) . . . . .*

*. 64 65 70 72 74 75 Setting the base station answering machine . . . 77 Ring delay and charge saving ff the base station .*

.....  
.....

*. . . . . 103 Changing the base station ringer tones . . . .*

.....  
.....  
.....

*104 Activating/deactivating the base station key beep . . . . .*

.....  
.....

*. . . . . 104 Changing the base station name . . . .*

.....  
.....  
.....

*. 105 Repeater support . . . .*

.....  
.....  
.....  
.....

*. . . . . 105 Resetting the base station to the factory setting . .*

.....  
.....  
.....

*. . . . . 105 Connecting the base station to a PABX . . . .*



.....

.....  
... *Technical data* .

.....

.....

.....

.....

..... *Answering machine remote operation* . .

.....

.....

.....

.....  
... *Character map* . .

.....

.....

.....

.....

.....

..... *Predictive text entry* . . .

.....

.....

.....

.....

.....

..... *110 110 110 111 113 114 114 116 Menu table* . . . . .

.....

.....

.....

..... *117 Main menu* . . . . .

.....

.....

.....

.....

.....

.....

.. *117 Directory key and speed dialling list key* . . . . .

.....

.....

.....

..... *119 Caller list/message list* . . . . .

.....

.....

.....

.....

..... *119 Index* .

.....

.....

.....  
.....

. . . . 120 5 Safety precautions Safety precautions \$ ! Only use the power supply unit supplied, as indicated on the underside of the base station. Only use approved rechargeable batteries (page 113) of the same type! I. e. no other type of rechargeable batteries or non-rechargeable batteries because otherwise health risks and personal injuries cannot be excluded. < OE Insert rechargeable batteries in accordance with the polarity symbols and use the battery type recommended in these operating instructions (the symbols can be found on the handset battery compartment). Medical equipment can be affected by the use of the telephone. Observe the conditions of your environment (e. g. doctor's practice). The handset can cause an unpleasant humming sound in hearing aids.



[You're reading an excerpt. Click here to read official SIEMENS GIGASET S150/ DUO user guide](http://yourpdfguides.com/dref/4569525)  
<http://yourpdfguides.com/dref/4569525>



Do not install the base station in bathrooms or showers (page 110).

The handsets and base station are not splashproof. Do not use the telephone while driving (Walk and Talk function). Telephones must be switched off at all times while in an aircraft (Walk and Talk function). Prevent accidental activation. Do not use the telephone in environments where there is a risk of explosions (e. g. paint shops). Ensure that the operating instructions are included when passing on your base station and handset to a third party. Dispose of batteries and telephone in an environmentally friendly manner. i 6 Not all functions described in these operating instructions are available in all countries.

Preparing the telephone Preparing the telephone The package contains the following: one base station, one handset, one power supply unit and cable, one telephone cord, one belt clip for the handset, two batteries, one set of operating instructions. Installing the base station Notes on installation The base station is designed for operation in dry rooms with a temperature range of +5 C to +45 C. Install the base station in a central location in the home, e. g. in the hall.

W Never expose the telephone to the following: heat sources, direct sunlight, other electrical equipment. Protect your base station and handset against moisture, dust, corrosive liquids and vapours. Range and reception strength The base station range is approx. 300 m outdoors and up to 50 m indoors. The receive strength display shows the quality of the radio contact between the base station and the handset: \ receive strength 100% receive strength 50% no reception (flashes) i receive strength 75% low receive strength 7 Preparing the telephone Connecting the base station Telephone socket Cable duct Underneath of base station (magnified) 1.

Telephone plug with telephone cable Insert the small plug on the telephone cable into the jack (clicks into place), place cable in the cable duct, insert telephone jack into the telephone socket. 1. Socket Cable duct Underneath of base station (magnified) 2. Power supply unit (230V) with mains cable Insert the small plug on the mains cable into the jack, place cable in the cable duct, insert power supply unit into mains socket. Telephone jack assignment: 3 2 1 4 5 6 1 2 3 4 5 6 free free a b free free 2. i 8 The power supply unit must be plugged in at all times for the telephone to work. If you buy another telephone cable, ensure that the telephone leads have 3-4 assignment. Preparing the telephone Operating the handset Remove the protective plastic film The display is protected by a plastic film. Remove the protective plastic film! Insert the batteries Insert the batteries ensuring correct polarity see figure on left. Place the cover about 3 mm down lower and then push upwards until it clicks into place, To open, press the grooved area on the cover and slide back.

W Only use the chargeable batteries recommended on page 113! Never use ordinary (non-rechargeable) batteries or a different type of rechargeable batteries because this may lead to serious health risks or personal injuries. For example the battery casing may be destroyed (dangerous). The telephone itself may not work properly or be damaged. 9 Preparing the telephone Placing the handset into the base station and charging the batteries If you place the handset on the base station, it automatically registers. This can be done as follows: 1. Place the handset in the base station with the display facing upward. 2. Wait until the handset has automatically registered with the base station (page 81): This takes about a minute. During registration the display shows Regstr.Procedure and it flashes Base 1.

After registration you will see "INT 1" in the display, which means that the handset has been assigned the first internal number. You can change the handset name "INT 1" (page 84). 3. Leave the handset in the base station to charge the batteries, because they are not charged at the factory. The charging is indicated in the upper right of the display where the charging status flashes: Batteries flat 1 Batteries /3 charged Batt.

fully charged Batt. 2/3 charged If automatic registration is interrupted, you can register the handset manually as described from page 81. There is a table of the most important questions and answers to help you (page 110). i W If you want to register further handsets, please turn to page 81. For initial charging we recommend a continuous, uninterrupted charging period of seven hours, whatever charge level is indicated! The battery charge capacity decreases after a few years for technical reasons.

The battery charging status is correctly displayed only after uninterrupted charging/discharging. Therefore you should not remove the batteries unnecessarily or terminate the charging process early. Once the initial charging operation is completed you can replace your i Note: handset in the base station after each call. Charging is controlled electronically. This ensures optimum charging. The batteries heat up during charging. This is normal and not dangerous. Your telephone is now ready for operation. The answering machine with the prerecorded announcement has also been switched on. All you have to do is set the date and time, so the time of incoming calls and messages can be noted correctly (page 15).

10 Preparing the telephone Attaching the belt clip Push the belt clip onto the back of the handset until the side protrusions click into place.

Activating/deactivating the handset To activate the handset hold down the end call key a. You will hear a confirmation beep (rising tone sequence). To deactivate the handset while in the idle state hold down the end call key a again (confirmation beep). i Placing the handset in the base station or charging unit automatically activates it. Activating/deactivating keypad protection You can disable the handset keys, e. g. when carrying it in your pocket or bag. This protects the keypad against inadvertent activation. Hold down the hash key (confirmation beep).

The display shows the icon . To deactivate hold down the hash key R again (confirmation beep). The keypad protection is automatically deactivated when you receive i a call. After the call it is automatically activated again. Emergency numbers cannot be dialled if the keypad protection has been activated.

The keypad protection is still indicated if you have loaded a logo as display graphic (page 61). 11 Using the telephone and menus Using the telephone and menus Keys Control key The control key with four direction arrows and associated icons is the central operating element. Pressing the various icons (up, down, right or left) opens a different function. The side you have to press is shown by a black triangle in the operating instructions, e.



[You're reading an excerpt. Click here to read official SIEMENS GIGASET S150/ DUO user guide](http://yourpdfguides.com/dref/4569525)  
<http://yourpdfguides.com/dref/4569525>

: v key for right = open menu. Navigating in the graphic main menu (see page 14) is always displayed with the down key s. Example: Control key Functions of the control key. t In idle state Open directory Open graphic main menu In lists and menus Scroll up Scroll down In an entry field Move the cursor one line up Move the cursor one line down Move the cursor to the right s v Confirm selected entry (as OK ) Open handset list Scroll one menu level back Move the cursor to the left u (cancel) Use the control key to navigate through the icons that appear in the graphic main menu (page 14). i You can often use the control key to carry out functions assigned to the right display key. 12 Using the telephone and menus Display keys The display keys are the horizontal buttons directly below the display. Their functions depend on the operating situation. The current function is shown directly above the button in the display. Example: SMS Display keys The various displays have the following meaning: Display icon C OK If you press the key Redial key: Opens the list of the last 10 telephone numbers. OK key: Confirm menu function or entry.

Menu key: In idle state opens the main menu. While telephoning, opens context sensitive menu. Delete key: Deletes input character by character from right to left. Escape key: One menu level back (cancel). Open email directory. Correcting entries After a correct entry you will hear a confirmation beep (rising tone sequence), after an incorrect entry an error beep (falling tone sequence). You can repeat the entry. If you have entered the wrong character in a text, you can correct it as follows: Delete characters to the left of the cursor with fC To correct a telephone number or text, move the cursor to the right of the incorrect character or number with the control key. Then press the display key fC . This deletes the character.

Now enter the correct character. Inserting characters to the left of the cursor If you have left out a character, use the control key to move the cursor to where you want to insert the character and then enter it. Overwriting characters to the right of the cursor When entering Cost per Unit: the number of digits is fixed and there is a default entry in the field. Use the control key to move the cursor to the left of the wrong digit and then overwrite it. 13 Using the telephone and menus Idle state Display in idle state (example) 20.

05.04 INT 1 09:45 The date and time have already been set SMS Returning to the idle state from anywhere in the menu: Hold down the end call key a for about 1 second or do not press any key: After about 2 minutes the display automatically returns to the idle state. Changes you have not confirmed or saved by pressing OK , Yes, Save, Send or with Save Entry OK will be discarded. Graphic main menu SMS t OK x The display shows all the menu options from the main menu as coloured icons. Use the control key to select the required icon - this is now highlighted by a border.

The name of the selected menu appears at the top of the screen. To open the menu, press the display key OK . If the main menu has three lines, then either the top two or the bottom two lines will be displayed. 1 The icons actually displayed will depend on your base. Example for menu operation: "Set volume for handsfree talking" 1. v 2. s Press the right side of the control key. This opens the menu. Navigate with the control key (up, down, right or left) until the icon is framed in the display. Confirm with the display key.

Confirm the first display entry, Handset Volume, with the right side of the control key or with the display key. Press the left or right side of the control key to set the volume you want (15). Press the display key to save the setting. Hold the end call key down to return to the idle state. 3. OK 4. v or OK 5. r 6.

[RRRRRRRRRRRRRRRRRRRRRRRR] Save 7. a 14 Date and time functions Date and time functions Setting the date and the time You need to set the date and time so that they can be displayed correctly when calls / messages are received.

You can set the clock mode to either 12 hour (factory setting) or 24 hour (am = 1st part of the day; pm = 2nd part of the day).

[ \_\_\_\_\_ ] OK [ \_\_\_\_\_ ] OK Date/Time Open the menu.

Select the menu item and confirm. Select the menu item and confirm. Enter the date: In the Date: line, enter day/month/year.

Enter the time: Scroll to the Time: line and enter the hours/minutes. Select the display mode: Scroll to the Time Mode: line if you want to choose between 12 hour and 24 hour mode. [RRRRRRRRRRRRRRRRRRRRRRRR] Save Press the display key to save the entry. With 12-hour mode you can scroll to Time: and then use the display key am/pm to switch between am and pm. Setting the alarm clock You can use your handset as an alarm clock.

Prerequisite: You have set the date and time (page 15). 15 Date and time functions Activating and setting the alarm clock If you want to use your handset as an alarm clock, you have to set the alarm time, choose a melody and activate the alarm clock. Open the menu. Select the menu item and confirm. Select the menu item and confirm. The current setting is displayed. Switching the alarm clock on: In the Room M.: line select On. Enter the time for alarm call: Scroll to the Time: line and enter the hours/minutes, e.g.

QM15 for "7.15 am". [RRRRRRRRRRRRRRRRRRRRRRRR] am/pm [RRRRRRRRRRRRRRRRRRRRRRRR] Save

[ \_\_\_\_\_ ] OK [ \_\_\_\_\_ ] OK Alarm Clock When in 12 hour mode, press the display key if you want to switch between am and pm. Press the display key to save the entry. Hold down (return to idle). You will see the icon . The alarm clock will ring only if the handset is in the idle state. The i alarm clock will not ring if the room monitor function is activated, a call is being made or during automatic redialling. How to change the volume and melody is explained on page 96. Switching the alarm clock off The alarm clock is set to a particular time, but you do not want it to ring.

[ \_\_\_\_\_ ] OK [ \_\_\_\_\_ ] OK Alarm Clock

[RRRRRRRRRRRRRRRRRRRRRRRR] Save Open the menu. Select the menu item and confirm. Select the menu item and confirm. In the Room M.: line select Off. Press the display key to save the setting. Hold down (return to idle). Deactivating the alarm call An alarm call with deactivated ringer melody is signalled on the handset and the display shows Alarm Clock. Press the display key Silence or any key to turn off the alarm call. The alarm call will ring for 30 seconds if it is not answered sooner.

16 Date and time functions Setting appointments You can have your handset remind you of up to five appointments.



[You're reading an excerpt. Click here to read official SIEMENS](http://yourpdfguides.com/dref/4569525)

[GIGASET S150/ DUO user guide](http://yourpdfguides.com/dref/4569525)

<http://yourpdfguides.com/dref/4569525>









