



Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for ZYXEL NSA221. You'll find the answers to all your questions on the ZYXEL NSA221 in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

User manual ZYXEL NSA221
User guide ZYXEL NSA221
Operating instructions ZYXEL NSA221
Instructions for use ZYXEL NSA221
Instruction manual ZYXEL NSA221

NSA221

2-Bay Digital Media Server

User's Guide

Default Login Details

Web Address	nsa221
User Name	admin
Password	1234

Firmware Version 4.00
Edition 1, 4/2010

www.zyxel.com



ZyXEL

Copyright © 2010
ZyXEL Communications Corporation



[You're reading an excerpt. Click here to read official ZYXEL NSA221 user guide](http://yourpdfguides.com/dref/3685280)
<http://yourpdfguides.com/dref/3685280>

Manual abstract:

This can help you quickly pinpoint the information you require. You can also enter text directly into the toolbar in Reader. · To quickly move around within a page, press the [SPACE] bar. This turns your cursor into a "hand" with which you can grab the page and move it around freely on your screen. · Embedded hyperlinks are actually cross-references to related text. Click them to jump to the corresponding section of the User's Guide PDF. Related Documentation · Quick Start Guide The Quick Start Guide is designed to help you get your NSA up and running right away. @@@@ Knowledge Base If you have a specific question about your product, the answer may be here. This is a collection of answers to previously asked questions about ZyXEL products. · Forum

This contains discussions on ZyXEL products.

Learn from others who use ZyXEL products and share your experiences as well. 4 NSA221 User's Guide About This User's Guide Customer Support Should problems arise that cannot be solved by the methods listed above, you should contact your vendor. If you cannot contact your vendor, then contact a ZyXEL office for the region in which you bought the device. See http://www.zyxel.com/web/contact_us.php for contact information. Please have the following information ready when you contact an office. · Product model and serial number.

· Warranty Information.

· Date that you received your device. Brief description of the problem and the steps you took to solve it. NSA221 User's Guide 5 Document Conventions Document Conventions Warnings and Notes These are how warnings and notes are shown in this User's Guide. Warnings tell you about things that could harm you or your device. Note: Notes tell you other important information (for example, other things you may need to configure or helpful tips) or recommendations. Syntax Conventions · The NSA may be referred to as the "NSA", the "device" or the "system" in this User's Guide. · Product labels, screen names, field labels and field choices are all in bold font. · A key stroke is denoted by square brackets and uppercase text, for example, [ENTER] means the "enter" or "return" key on your keyboard. · "Enter" means for you to type one or more characters and then press the [ENTER] key. "Select" or "choose" means for you to use one of the predefined choices.

· A right angle bracket (>) within a screen name denotes a mouse click. For example, Maintenance > Log > Log Setting means you first click Maintenance in the navigation panel, then the Log sub menu and finally the Log Setting tab to get to that screen. · Units of measurement may denote the "metric" value or the "scientific" value. For example, "k" for kilo may denote "1000" or "1024", "M" for mega may denote "1000000" or "1048576" and so on. · "e.g.," is a shorthand for "for instance", and "i.e.," means "that is" or "in other words". 6 NSA221 User's Guide Document Conventions Icons Used in Figures Figures in this User's Guide may use the following generic icons.

The NSA icon is not an exact representation of your device. Graphics in this book may differ slightly from the product due to differences in operating systems, operating system versions, or if you installed updated firmware/software for your device. Every effort has been made to ensure that the information in this manual is accurate. NSA Computer Notebook computer Server Television Firewall Router Switch Internet NSA221 User's Guide 7 Safety Warnings Safety Warnings · Do NOT use this product near water, for example, in a wet basement or near a swimming pool. · Do NOT expose your device to dampness, dust or corrosive liquids.

· Do NOT store things on the device. · Do NOT install, use, or service this device during a thunderstorm. There is a remote risk of electric shock from lightning. · Connect ONLY suitable accessories to the device. · Do NOT open the device or unit.

Opening or removing covers can expose you to dangerous high voltage points or other risks. ONLY qualified service personnel should service or disassemble this device. Please contact your vendor for further information. · ONLY qualified service personnel should service or disassemble this device. · Make sure to connect the cables to the correct ports. · Place connecting cables carefully so that no one will step on them or stumble over them. · Always disconnect all cables from this device before servicing or disassembling. · Use ONLY an appropriate power adaptor or cord for your device. · Connect the power adaptor or cord to the right supply voltage (for example, 110V AC in North America or 230V AC in Europe). · Do NOT allow anything to rest on the power adaptor or cord and do NOT place the product where anyone can walk on the power adaptor or cord.

· Do NOT use the device if the power adaptor or cord is damaged as it might cause electrocution. · If the power adaptor or cord is damaged, remove it from the power outlet. · Do NOT attempt to repair the power adaptor or cord. Contact your local vendor to order a new one. · Do not use the device outside, and make sure all the connections are indoors. There is a remote risk of electric shock from lightning. · CAUTION: RISK OF EXPLOSION IF BATTERY (on the motherboard) IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS. Dispose them at the applicable collection point for the recycling of electrical and electronic equipment. For detailed information about recycling of this product, please contact your local city office, your household waste disposal service or the store where you purchased the product.

· Do NOT obstruct the device ventilation slots, as insufficient airflow may harm your device. Your product is marked with this symbol, which is known as the WEEE mark. WEEE stands for Waste Electrical and Electrical Equipment. It means that used electrical and electronic products should not be mixed with general waste. Used electrical and electronic equipment should be treated separately.

8 NSA221 User's Guide Contents Overview Contents Overview User's Guide

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....
.....
... 19 Getting to Know Your NSA ..
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 21 NAS Starter Utility

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

27 Web Configurator Basics

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.. 47 Tutorials ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
141 Storage

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 147 Network

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 161 Applications ...

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....

.....
.. 173 Package Management ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 219 Auto Upload

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 273 Users

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 289 Groups

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 295 Shares .

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.. 299 Maintenance Screens

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.. 309 Protecting Your Data ...

.....

.....

.....

.....

.....

.....

.....
.....
.....
.....

.....
.....
.....
.....

... 333 Troubleshooting

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 339 Product Specifications

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 359 NSA221 User's Guide 9 Contents Overview 10 NSA221 User's Guide Table of Contents Table of Contents About This User's Guide .



[You're reading an excerpt. Click here to read official ZYXEL](#)

[NSA221 user guide](#)

<http://yourpdfguides.com/dref/3685280>

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *3 Document Conventions.*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *6 Safety Warnings...*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *8 Contents Overview*

.....

.....

.....

.....

.....

.....

.....

.....

.....
.....
.....
.....

. 9 Table of Contents.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 11 Part I: User's Guide...

.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 19 Chapter 1 Getting to Know Your NSA...

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

... 21 1.1 Overview .

.....

.....
.....
.....
.....

.....
.....

.....
.....

.....
.....
.....
.....

.....
.....
.....

..... *21 1.2 Hard Disks*

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... *22 1.*

3 LEDs

.....
.....
.....

.....
.....
.....

..... *63 3.*

5.1 Global Administration Icons

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. *63 3.5.2 Navigation Panel* .

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.. 64 3.5.3 Main Window

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

... 65 3.5.4 Status Messages

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 65 3.5.

5 Common Screen Icons

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 66 3.

5.6 Session Example (Windows)

.....

.....
.....
.....
.....

.....

.....
.....
.....

. 67 Chapter 4 Tutorials

.....
.....

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.. 69 4.1 Overview

.....
.....
.....
.....

.....
.....
.....

.....Backup Files .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.... 132 Part II: Technical Reference

.....
.....
.....
.....

.....
.....
.....

..... 135 Chapter 5 Status Screen ..

.....
.....
.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 137 5.1 Overview .

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

... 137 5.2 The Status Screen

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.. 137 Chapter 6 System Setting

.....

.....

.....

.....

.....

.....

.....

.....
.....
.....
.....

.....
.....
.....
141 6.1 Overview

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 141 6.2 What You Can Do

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

. 141 6.3 What You Need to Know ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 141 6.4 The Server Name Screen ..

.....
.....

.....
.....
.....
.....

..... 147 7.1.1 What You Need to Know About Storage ...

.....
.....
.....

.....
.....
.....
.....

.....
... 147 7.2 The Storage Screen .

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 148 7.2.1 Disk Replacement Restrictions

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

... 148 7.2.2 Storage Screen

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

3 Creating an Internal Volume

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 151 7.

3.1 Volume Status

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 152 7.4 Editing a Volume

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 153 7.5 Creating an External Volume

.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 154 7.

5.1 External Disks

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 155 7.6 Storage Technical Reference ..

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

. 156 7.6.1 Volumes and RAID

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 156 NSA221 User's Guide 13 Table of Contents 7.6.2 Choosing a Storage Method for a Volume

.....
.....
.....

.....
.....
.....
.....

..... 157 7.6.3 Storage Methods .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 157 Chapter 8 Network

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

161 8.1 Overview

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 161 8.2 What You Can Do

.....
.....
.....

.....
.....
.....
.....

.....
.....

.....
.....

..... 161 8.3 What You Need to Know ...

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 161 8.4 The TCP/IP Screen ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 163 8.5 UPnP Port Mapping Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

166 8.5.1 UPnP and the NSA's IP Address

.....
.....
.....

.....
.....
.....

.....
.....
.....
.....
167 8.5.2 UPnP and Security

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

. 167 8.5.3 The NSA's Services and UPnP

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

... 167 8.5.4 Configuring UPnP Port Mapping

.....
.....
.....
.....
.....
.....
.....
.....

... 168 8.6 The PPPoE Screen .

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

170 Chapter 9 Applications

.....
.....
.....
.....
.....

..... 174 9.
4 FTP Server

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
176 9.5 The Media Server Screen

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.. 178 9.6 The Download Service Screen ..

.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

..... 179 9.6.
1 Adding a Download Task

.....
.....
.....
.....

.....
.....
.....
.....

183 9.6.2 Configuring General Settings

.....
.....
.....
.....

.....
.....
.....
.....

185 9.6.3 Configuring the BitTorrent Settings ...

.....
.....
.....
.....

.....
.....
.....
.....

. 188 9.6.4 Edit IP Filter

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 189 9.6.5 Displaying the Task Information

.....
.....
.....
.....

.....
.....
.....
.....

.. 191 9.7 The Web Publishing Screen ..

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.. 192 9.8 The Broadcatching Screen ..

.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 194 9.8.1 Adding a Broadcatching Channel

.....
.....
.....

.....
.....
.....

.....
.....

*... 196 9.8.
2 Editing a Broadcatching Channel*

.....

.....
.....
.....

.....
.....
.....

. 200 9.9 The Print Server Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 202 9.9.1 Print Server Rename ..

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

... 203 9.10 The Copy/Sync Button Screen .

.....

.....
.....
.....

.....
.....
.....

.....
.....

.. 204 9.11 Technical Reference ..

.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 205 9.11.1 Sharing Media Files on Your Network

.....
.....

.....
.....
.....

.....

.. 205 9.11.2 Download Service .

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 207 9.11.3 Link Capture Browser Plugin

.....
.....
.....
.....
.....
.....
.....

. 207 9.11.4 Download Service Notification ..

.....
.....
.....
.....
.....
.....
.....

..... 208 9.11.

5 BitTorrent Security

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

... 209 9.11.

6 Web Publishing Example

.....
.....
.....

.....
.....
.....
.....
.....

.....
.....
.....211 14 NSA221 User's Guide Table of Contents 9.
11.7 Web Publishing

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

... 213 9.11.8 Channel Guides for Broadcatching

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 214 9.11.9 Printer Sharing .

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 215 9.11.10 Copying Files

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
.....

... 216 9.11.

11 Synchronizing Files

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 217 Chapter 10 Package Management

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 219 10.1 Overview ...

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 219 10.

2 What You Can Do

.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

... 219 10.3 What You Need to Know

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 219 10.4 Package Management Screen ..

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

220 10.4.1 Displaying the Package Information ...

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 223 10.5 eMule Screens

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
.....

.....
... 224 10.5.
1 eMule Server Screen

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 224 10.5.2 Add Server .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 225 10.5.3 Edit Server .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 226 10.5.4 My Info .

.....
.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

... 227 10.5.5 eMule Task Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

228 10.5.6 Add Task

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 230 10.5.7 Preferences

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 232 10.5.8 Edit IP Filter .

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

. 235 10.5.9 Share Browsing

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

*.... 236 10.
5.10 Task Info*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 237 10.5.11 eMule Search Screen ..

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 239 10.6 DyDNS Screen ..

.....
.....

.....
.....

.....
.....

.....
.....

..... 240 10.7 NFS Screen .

.....
.....

.....
.....

.....
.....

.....
.....

.... 241 10.7.1 Add/Edit NFS Share

.....
.....

.....
.....

.....
.....

243 10.7.2 NFS Session

.....
.....

.....
.....

.....
.....

.....
.....
.....
.....
.. 244 10.8 SMART Screen ..

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 245 10.8.
1 SMART Brief Summary

.....
.....
.....
.....
.....
.....
.....

..... 246 10.
8.2 SMART Full Summary

.....
.....
.....
.....
.....
.....
.....
.....

.....
..... 247 10.9 Protect Screens ...

.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
.....

. 249 10.10 Backup Screens

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

..... 249 10.

10.1 Backup: Step 1

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 251 10.10.2 Backup: Step 2

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 253 10.10.

3 Backup: Step 3

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 256 10.10.4 Backup: Step 4 ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 257 10.10.5 Edit Job Screen .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

..... 258 10.
10.6 Edit Job: Step 1

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

259 10.10.7 Edit Job: Step 2

.....
.....
.....

.....
.....
.....

.....

.....

.....

.....

.....

. 261 10.10.8 Restore Archive Screen ..

.....

.....

.....

.....

.....

.....

.....

.....

.....

262 10.10.9 Restore Archive: Step 1 ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 262 NSA221 User's Guide 15 Table of Contents 10.10.10 Restore Archive: Step 2 ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

. 263 10.10.11 Restore Archive: Step 3

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 264 10.11 Restore Screen .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

... 265 10.11.
1 Restore: Step 1

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

265 10.11.2 Restore: Step 2

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 266 10.11.3 Restore: Step 3 .

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.....
.....
.....
.....

273 11.1 Overview

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 273 11.2 What You Can Do

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.. 273 11.3 What You Need to Know

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 273 11.4 The Flickr/YouTube Screen

.....
.....
.....
.....

.....
.....
.....
.....
.....

.. 287 Chapter 12 Users

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

. 289 12.1 Overview ...

.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

... 289 12.

2 What You Can Do

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

. 293 12.4 Displaying User Info

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

. 294 Chapter 13 Groups

.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 295 13.1 Overview ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

295 13.2 What You Can Do

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.... 295 13.
3 The Groups Screen

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 295 13.3.1 *Adding or Editing a Group*

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 297 13.3.2 *Group Names*

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.... 298 *Chapter 14 Shares* .

.....
.....

.....
.....
.....
.....

..... 300 14.

3.1 Adding or Editing Share

.....
.....

.....
.....
.....

.....
.....
.....

..... 302 14.

3.2 Configuring Advanced Share Access

.....
.....

.....
.....
.....

.....
.....

..... 303 14.

3.3 Public and ANONYMOUS Share Access Rights

.....
.....
.....

.....

.. 304 14.4 The Recycle Bin Configuration Screen ..

.....
.....

.....
.....
.....

.....
.....

..... 305 14.4.

1 Recycle Bins

.....
.....
.....

.....
.....
.....

.....
.....

..... 309 15.1 Overview

.....
.....
.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 309 15.2 What You Can Do .

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 309 15.3 The Power Screen ..

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 310 15.

3.1 Editing the Power Control Schedule Screen

.....
.....
.....
.....

.....
... 312 15.4 The Log Screen .

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 314 15.4.1 Report Config Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 315 15.
4.2 Email Setting

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 315 15.4.3 Report Setting ..

.....
.....
.....

.....
.....
.....

.....

.....
.....
.....

.....
. 316 15.4.4 Syslog Server Setting ..

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
317 15.5 The Configuration Screen

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

. 318 15.6 SSL Certification

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
. 319 15.6.1 Modifying or Creating a Certificate ..

.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 321 15.7 The Firmware Upgrade Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 322 15.8 The Shutdown Screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 323 15.9 Technical Reference

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.... 323 15.

9.1 Log Classes

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 324 15.9.
2 Log Severity Levels

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

. 324 15.9.3 Log Messages ..

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 324 Chapter 16 Protecting Your Data.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

. 333 16.1 Overview

.....
.....
.....

.....
.....
.....

.....
.....

.....
.....
.....
.....

.. 337 Chapter 17 Troubleshooting.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 339 NSA221 User's Guide 17 Table of Contents 17.1 Troubleshooting Overview .

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 339 17.2 Power, Hardware, Connections, and LEDs

.....
.....
.....

.....
.....
.....

.....

.... 339 17.

3 NAS Starter Utility

.....

.....
.....
.....

.....
.....
.....

.....

.....
.....
.....

... 342 17.4 NSA Login and Access

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....

.... 343 17.

4.1 Reset the NSA

.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 344 17.

4.2 Enabling Scripting of Safe ActiveX Controls

.....
.....
.....

.....
.....
.....

..... 345 17.

5 I Cannot Access The NSA

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 347 17.6 Users Cannot Access the NSA

.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

.... 347 17.7 External USB Drives

.....
.....
.....
.....
.....
.....
.....
.....
.....

.... 349 17.
8 Firmware

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 349 17.9 File Transfer

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
349 17.10 Networking

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 350 17.11 Some Features' Screens Do Not Display .

.....
.....
.....
.....

.....
.....
.....
.....

..... 351 17.

12 Media Server Functions

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 352 17.13 Download Service and Broadcatching Functions ..

.....
.....
.....
.....

.....
.....
.....
.....

..... 354 17.14 Web Publishing ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.....
.....
.....

.....
.....
.....

..... 355 17.15 Auto Upload ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 356 17.16 Package Management

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 357 17.17 Backups

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 358 Chapter 18 Product Specifications

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

359 18.1 Physical Features

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 359 18.

2 Firmware Features

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 360 18.3 Specification Tables ...

.....
.....
.....

.....
.....
.....

.....

...

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 395 Appendix D Importing Certificates..

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 399 Appendix E

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 431 Appendix E Open Source Licences..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 431 Appendix F Legal Information

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 569 Index..

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

... 573 18 NSA221 User's Guide PART 1 User's Guide 19 20 CHAPTER 1.1 Overview This chapter covers the main features and applications of the NSA. Use the NSA to do the following. · Share files between computers on your network. · Back up files from your computers to the NSA. 1 Getting to Know Your NSA · Use the COPY/SYNC button to copy or synchronize files between the NSA and USB devices like card readers, MP3 players, mass storage devices, and digital cameras without using a computer. · Have the NSA handle large file downloads. · Automatically download files from website feeds for convenient viewing. · Play the NSA's video, music and photo files on your computers using the included media client software. · Play the NSA's video, music and photo files on hardware-based media clients like the DMA-2500. · Use the NSA's website to share files with remote users. · Use iTunes on your computer to play video and music files stored on the NSA. · Share printers. · Automatically upload photo and video files to your FTP server, Flickr and YouTube accounts. NSA221 User's Guide 21 Chapter 1 Getting to Know Your NSA Figure 1 Example of the NSA in a Home Network NSA Above is the NSA in a home network. Users back up and share data on the NSA. The DMA-2500 plays the NSA's media files on the TV.

A USB hard drive provides extra storage space and files are copied directly from the USB mass storage device to the NSA. Place the NSA behind a firewall and/or IDP (Intrusion Detection and Prevention) device to protect it from attacks from the Internet. Note: See Chapter 18 on page 359 for a more detailed list of NSA features. Refer to the Quick Start Guide for hardware connections and how to install and remove hard drives from the disk trays. Note: Turn off and disconnect the NSA before you install or remove the internal hard disk. 1.2 Hard Disks Your NSA has two internal hard disk bays. Install one or two SATA (Serial Advanced Technology Attachment) hard disks. Note that both SATA hard disks are treated as internal or SATA volumes in the Storage > Volume screen (Section 7.4 on page 153).

Any hard disk connected to the USB port(s) is considered an external or USB volume. 22 NSA221 User's Guide Chapter 1 Getting to Know Your NSA 1.3 LEDs The NSA LEDs (lights) tell you important information. Figure 2 NSA Front Panel This table describes the NSA's LEDs. Table 1 LEDs LED POWER SYSTEM COLOR Blue Green Red STATUS On Off On Blinking On On Blinking DESCRIPTION The NSA is turned on and receiving power. The NSA is turned off. The NSA has fully started and is operating normally. The NSA is starting up or upgrading the firmware. The NSA has failed. The hard disk drive is connected properly to the NSA.

The NSA is saving data to the hard disk drive. The NSA detected an error on the hard disk drive (like a bad sector for example). The NSA automatically tries to recover a bad sector, but the LED stays red until the NSA restarts. The NSA cannot detect a hard disk in the disk bay. The USB device is connected properly to the NSA. The NSA is saving data to the USB device. The USB device has failed and the NSA can no longer detect it. No USB device connected to the USB port. HDD1/ HDD2 Green Red On Off USB Green Red On Blinking On Off NSA221 User's Guide 23 Chapter 1 Getting to Know Your NSA Table 1 LEDs (continued) LED LAN COLOR Green STATUS On Blinking Off DESCRIPTION The NSA has a successful 10/100 Mbps Ethernet connection. The 100M LAN is sending or receiving packets.

The NSA does not have a 10/100 Mbps Ethernet connection. The NSA has a successful 1000 Mbps Ethernet connection. The 1000 M LAN is sending or receiving packets. The NSA does not have a 1000 Mbps Ethernet connection. A USB device is connected to the NSA. The NSA is copying or synchronizing files to or from the USB device. Copying or synchronizing files to or from the USB device failed. No USB device is connected. Amber On Blinking Off COPY/

SYNC Green On Blinking Red On Off 1.3.

1 COPY/SYNC Button Use the COPY/SYNC button on the front panel to copy or synchronize files between a connected USB device and the NSA. See Section 9.10 on page 204 for more details on how to configure the copy/sync settings. 1.3.

2 RESET Button Use the RESET button on the rear panel to restore the NSA's default settings. Figure 3 The RESET Button Press 1 Beep 2 Beeps 5 more seconds Release to Reset IP Address Password Release to Clear All Settings · Press the RESET button until you hear one beep (after about two seconds), then release it. You will hear one more beep after you release the button. This resets the NSA's IP address and password to the default values. 24 NSA221 User's Guide Chapter 1 Getting to Know Your NSA · Press the RESET button until you hear two beeps.

After the second beep, continue pressing the button for five more seconds, then release it. You will hear three quick beeps after you release the button. This resets the NSA to the factory default configuration. All settings you have configured on the NSA, including IP address, password, user accounts, groups, and so on will be reset to the factory defaults. The reset process does NOT affect the volume settings, nor data stored on the NSA. You should periodically back up your configuration file to your computer (see Section 15.5 on page 318 for details about managing the NSA's configuration file). You could then restore your configuration in the event that you or someone else reset the NSA to the factory defaults. Note: You should keep the NSA in a secure location in order to prevent unauthorized reset of the device. NSA221 User's Guide 25 Chapter 1 Getting to Know Your NSA 26 NSA221 User's Guide CHAPTER 2.

1 Overview 2 NAS Starter Utility This chapter describes the NAS Starter Utility. Use the NAS Starter Utility to find, set up, and manage the NSA as well as copy files to it and access the files on it. Make sure you have a backup of any existing data in the hard disk before installing it in the NSA. Using the initialization wizard formats the hard disk and deletes all data in the process. There is a NAS Starter Utility available for Windows XP, Windows Vista, or Windows 7. Click Help to open a web help page about the NAS Starter Utility screens. NAS Starter Utility screens are shown here as they display with the Windows platform. Note: Refer to the Quick Start Guide for your NSA's hardware connections and the steps for installing the NAS Starter Utility. 2.2 Starting the NAS Starter Utility · The NAS Starter Utility broadcasts a request packet when you first run it.

Each NSA has an NAS Starter Utility Agent that always listens and responds to requests from the NAS Starter Utility.



[You're reading an excerpt. Click here to read official ZYXEL
NSA221 user guide
http://yourpdfguides.com/dref/3685280](http://yourpdfguides.com/dref/3685280)

The NAS Starter Utility receives the response packet that contains information, such as host name, IP, and so on. If you plan to use more than one NSA in your network, configure them with unique server names. This enables you to identify each NSA in the NAS Starter Utility screens. 2.

3 NAS Discovery Screen Use this screen to view the NSAs in your network. The NSA's Server Name (default is 'nsa221'). See Section 2.9 on page 44 for how to change it to a more recognizable one in your network. NSA221 User's Guide 27 Chapter 2 NAS Starter Utility Start the NAS Starter Utility (click the icon in your Desktop or in Start > Programs > ZyXEL > NAS Starter Utility).

The first time you open the NAS Starter Utility the discovery screen appears as follows. Figure 4 NAS Discovery The following table describes the labels in this screen. Table 2 NAS Discovery LABEL Refresh Hostname DESCRIPTION Click this to refresh the screen. The NAS Starter Utility does not automatically refresh. This is the server name you configured for the NSA. If you have more than one NSA in your network, it is recommended that you give each one a unique name for identification purposes. If you have several NSAs connected to your computer/network, hover your mouse over the host name to view the details of each device. A box pops up containing details about the NSA. Hostname shows the NSA's configured server name. IP shows the NSA's current IP address.

Model ID shows the NSA's model name. Firmware Version shows the version of firmware the NSA is currently using. Status shows whether the NSA is Online, Unreachable, Configuring, or Config Failed. 28 NSA221 User's Guide Chapter 2 NAS Starter Utility 2.4 Main NAS Starter Utility Screen The main NAS Starter Utility screen displays after you select a NSA in the NSA Discovery screen. Figure 5 NAS Starter Utility Main Screen The following table describes the labels in this screen. Table 3 NAS Starter Utility Main Screen LABEL Discovery bar Name DESCRIPTION Click this to use the NSA Discovery screen (Section 2.3 on page 27) to find and select the NSA on your network to which you want to connect. The bar shows the NSA's in-use and remaining storage capacity. This is the server name you configured for the NSA.

If you have more than one NSA in your network, it is recommended that you give each one a unique name for identification purposes. This shows the version of firmware the NSA is currently using. This is the current IP address of the NSA. This shows whether the NSA is Online, Unreachable, Configuring, or Config Failed. Click this to use the NSA Discovery screen (Section 2.

3 on page 27) to find and select the NSA on your network to which you want to connect. Click this to launch zPilot to drag and drop files onto the NSA. Firmware IP address Status NAS Discovery Import files or folders with zPilot Add a network drive to My Computer Manage the device Click this to add the NSA as a network drive in your computer's Windows Explorer. Click this to log into the advanced administration screens. See Section 3.

5 on page 63 for details on the administration screens. NSA221 User's Guide 29 Chapter 2 NAS Starter Utility Table 3 NAS Starter Utility Main Screen LABEL Play Media Files from Home Screen Show the directory of the NSA Run the Initialization Wizard Configure network setting DESCRIPTION Click this to enjoy your media files through your web browser. See Section 3.4 on page 50 for details on the Home screen. Click this to open the NSA's file directory in Windows Explorer. See Section 2.5.3 on page 40 for details. Click this to set up the NSA for the first time. See Section 2.

5 on page 30 for details. Click this to change the NSA network settings such as the NSA's name, IP address, subnet mask, default gateway, DNS, or PPPoE. See Section 2.9 on page 44 for details. 2.5 Initialization Wizard Use these screens to set up the NSA for the first time Click Run the Initialization Wizard in the main utility screen to display the following screen. You must log in using an admin account. The default administrator username is 'admin' and the default password is '1234' and click Next. Figure 6 Initialization Wizard Welcome 30 NSA221 User's Guide Chapter 2 NAS Starter Utility Choose Default Configuration (recommended) or manual configuration. Use the manual option if you need to name the NSA to configure specific network settings. Click Next. Figure 7 Initialization Wizard: Wizard Type 2.5.1 Default Configuration 1 The NAS Starter Utility checks the Internet connection. Figure 8 Check Network Connection NSA221 User's Guide 31 Chapter 2 NAS Starter Utility Type a new administrator password (and retype it to confirm).

If you do not want to change the administrator password, you can leave the fields blank and just click Next. 2 Figure 9 Change Admin Password 3 Specify usernames and passwords for the individuals you want to be able to access the NSA. Figure 10 Create User Accounts 32 NSA221 User's Guide Chapter 2 NAS Starter Utility Check your settings. If they are OK, click Next. Otherwise click Back.

If you want to change anything other than the user accounts, keep clicking Back until you can change the wizard type to manual. 4 Figure 11 Confirm Settings 5 Wait while the NAS Starter Utility configures the NSA. Figure 12 Setting the NAS After the NAS Starter Utility finishes configuring the NSA, you can click Show the directory of the NAS to see the NSA's shares (see Section 2.5.3 on page 40) or NSA221 User's Guide 33 Chapter 2 NAS Starter Utility click Finish to return to the main NAS Starter Utility screen (see Section 2.4 on page 29). Figure 13 Setting the NAS 2.5.2 Manual Configuration 1 Set up the NSA's basic network configuration first. Figure 14 Setup Network 34 NSA221 User's Guide Chapter 2 NAS Starter Utility The following table describes the labels in this screen.

Table 4 NAS Starter Utility > Config LABEL Get IP automatically from DHCP server Assign IP Manually DESCRIPTION Select this if the NSA is automatically assigned an IP address from the ISP or a DHCP server in your network. Select this if you want to assign the NSA a fixed IP address, subnet mask and default gateway. Note: Do not configure an IP address that is already in use in your network. This results to a network IP address conflict and makes the NSA inaccessible. Use DNS server from DHCP server Assign DNS server manually Domain Name System (DNS) is for mapping a domain name to its corresponding IP address and vice versa. Select this if the NSA is automatically given DNS information from the ISP or a DHCP server in your network. If you were given specific IP address(es) of the DNS server(s), select this and enter the primary and secondary DNS in the corresponding fields. 2 If your Internet connection requires you to enter a user name and password to connect to the Internet, enter them here and click Next.



[You're reading an excerpt. Click here to read official ZYXEL](http://yourpdfguides.com/dref/3685280)

[NSA221 user guide](http://yourpdfguides.com/dref/3685280)

<http://yourpdfguides.com/dref/3685280>

If you do not need to enter a user name and password to connect to the Internet, click Skip. Figure 15 PPPoE NSA221 User's Guide 35 Chapter 2 NAS Starter Utility The NAS Starter Utility checks the Internet connection.

3 Figure 16 Check Network Connection 4 Type a new administrator password (and retype it to confirm) and click Next. If you do not want to change the administrator password, you can leave the fields blank and just click Next. Figure 17 Change Admin Password 36 NSA221 User's Guide Chapter 2 NAS Starter Utility Specify a name to uniquely identify the NSA on your network. Choose the time zone of your location. This sets the time difference between your time zone and Greenwich Mean Time (GMT).

5 Figure 18 Create User Accounts 6 Select how to configure the hard disks. Figure 19 Create User Accounts With only one hard disk installed, just click Next. If you have two hard disks installed choose one of the following: · RAID 1: Use this to mirror all data on one disk to the other disk to protect against data loss. · Individual Disks: Use this if you want maximum storage capacity and/or you have other means of protecting your data. This creates two JBOD volumes (with one disk in each), a failure of one disk (volume) should not affect the other volume (disk). · JBOD: Use this if you want maximum storage capacity and/or you have other means of protecting your data. This combines the two physical disks into a single virtual one, so they appear as a single large disk. NSA221 User's Guide 37 Chapter 2 NAS Starter Utility · RAID 0: Use this if you want maximum speed for your disks, and/or you have other means of protecting your data. RAID 0 has the fastest read and write performance but if one disk fails you lose all your data from both disks. 7 This screen lists the shares the NAS Starter Utility creates on the NSA by default. Select the ones you want to use as network drives in Windows Explorer. Figure 20 Connect Network Drives 8 Specify usernames and passwords for the individuals you want to be able to access the NSA and click Next. Figure 21 Create User Accounts 38 NSA221 User's Guide Chapter 2 NAS Starter Utility If the settings are OK, click Next. Otherwise click Back. If you want to change anything other than the user accounts, keep clicking Back until you can change the wizard type to manual.

9 Figure 22 Confirm Settings 10 Wait while the NAS Starter Utility configures the NSA. Figure 23 Setting the NAS After the NAS Starter Utility finishes configuring the NSA, you can click Show the directory of the NAS to see the NSA's shares (see Section 2.5.3 on page 40) or NSA221 User's Guide 39 Chapter 2 NAS Starter Utility click Finish to return to the main NAS Starter Utility screen (see Section 2.4 on page 29). Figure 24 Setting the NAS 2.5.3 Directory of the NAS Enter the administrator user name and password and click Login. Figure 25 Login The utility opens the NSA's directory in Windows Explorer. Figure 26 Directory 40 NSA221 User's Guide Chapter 2 NAS Starter Utility 2.

6 Import Files or Folders with zPilot In the main NAS Starter Utility screen click Import files or folders with zPilot to be able to drag and drop files from your computer to the NSA. Enter the administrator user name and password and click Login. Figure 27 Login The zPilot icon displays. Figure 28 zPilot Drag files onto the zPilot icon to move them to the NSA. zPilot automatically sorts music, photo, and video files into the Music, Photo, and Video folders. zPilot can automatically sort the types of media files listed in Table 121 on page 366 (except for the subtitles). Other types of files go to the Public folder. For folders of files you are prompted to choose the target destination. The zPilot icon shows the transfer rate. Figure 29 zPilot Showing Transfer Rate NSA221 User's Guide 41 Chapter 2 NAS Starter Utility Double-click the zPilot icon to display the NAS Starter Utility screen with status details about the file transfers. Click the "x" button next to a file entry to stop transferring the file. Click Clean Up to clear completed transfers from the list. Figure 30 zPilot Showing Transfer Rate 2.7 Add a Network Drive to My Computer In the main NAS Starter Utility screen click Add a network drive to My Computer to add the NSA as a network drive in your computer's Windows Explorer. Enter the administrator user name and password and click Login. Figure 31 Login Select a share on the NSA and the drive letter on your computer to which you want to map it. The table displays the NSA shares that are already mapped to drive letters on your computer. After you click OK you can see the new drive in 42 NSA221 User's Guide Chapter 2 NAS Starter Utility Windows Explorer (My Computer) where you can access and use it like your computer's other drives. Figure 32 Network Drive Mapping Select a share on the NSA and the drive letter on your computer to which you want to map it. The table displays the NSA shares that are already mapped to drive letters on your computer.

After you click OK you can see the new drive in Windows Explorer (My Computer) where you can access and use it like your computer's other drives. 2.8 Manage the Device In the main NAS Starter Utility screen click Manage the Device to log into the NSA's administration screens where you can manage the NSA. Enter the administrator user name and password and click Login. Figure 33 Login See Section 3.5 on page 63 for more on the administration screens. NSA221 User's Guide 43 Chapter 2 NAS Starter Utility 2.9 Configure Network Setting Use these screens to change the NSA network settings such as the NSA's name, IP address, subnet mask, default gateway, DNS, or PPPoE. Click Configure network setting in the main utility screen to display the following screen. Figure 34 NAS Starter Utility > Configure network setting The following table describes the labels in this screen.

Table 5 NAS Starter Utility > Config LABEL NAS Name DESCRIPTION Specify a name to uniquely identify the NSA on your network. You can enter up to 15 alphanumeric characters with minus signs allowed but not as the last character. The name must begin with an alphabetic character (a-z) and is NOT case sensitive. Select this if the NSA is automatically assigned an IP address from the ISP or a DHCP server in your network. Get IP automatically from DHCP server Assign IP Manually Select this if you want to assign the NSA a fixed IP address, subnet mask and default gateway.

Note: Do not configure an IP address that is already in use in your network. This results to a network IP address conflict and makes the NSA inaccessible. Use DNS server from DHCP server Domain Name System (DNS) is for mapping a domain name to its corresponding IP address and vice versa.



[You're reading an excerpt. Click here to read official ZYXEL](http://yourpdfguides.com/dref/3685280)

[NSA221 user guide](http://yourpdfguides.com/dref/3685280)

<http://yourpdfguides.com/dref/3685280>

Select this if the NSA is automatically given DNS information from the ISP or a DHCP server in your network. 44 NSA221 User's Guide Chapter 2 NAS Starter Utility Table 5 NAS Starter Utility > Config LABEL Assign DNS server manually PPPoE DESCRIPTION If you were given specific IP address(es) of the DNS server(s), select this and enter the primary and secondary DNS in the corresponding fields.

Click this if your Internet connection requires you to enter a user name and password to connect to the Internet. If your Internet connection requires you to enter a user name and password to connect to the Internet, select Enable PPPoE Connection and enter your user name and password. Figure 35 PPPoE NSA221 User's Guide 45 Chapter 2 NAS Starter Utility 46 NSA221 User's Guide CHAPTER 3.1 Overview 3 Web Configurator Basics This chapter describes how to access the NSA web configurator and provides an overview of its screens. The web configurator is an HTML-based management interface that allows easy NSA setup and management using an Internet browser. Use Internet Explorer 6.0 or Mozilla Firefox 2.00, or later versions of these browsers. The recommended screen resolution is 1024 by 768 pixels or higher. In order to use the web configurator you need to allow: · Web browser pop-up windows from your device.

Web pop-up blocking is enabled by default in Windows XP SP (Service Pack) 2. · JavaScript (enabled by default). 3.2 Accessing the NSA Web Configurator Make sure your NSA is properly connected and that your computer is in the same subnet as the NSA (refer to the Quick Start Guide or the appendices). 3.2.1 Access the NSA Via NAS Starter Utility If you don't know the IP address of the NSA, then use the NAS Starter Utility's Play Media Files from Home Screen link to find it. Refer to the Quick Start NSA221 User's Guide 47 Chapter 3 Web Configurator Basics Guide for how to install and run the NAS Starter Utility.

See Chapter 2 on page 27 for more information on the NAS Starter Utility. Figure 36 NAS Starter Utility Main Screen 3.

2.2 Web Browser Access Configure the server name of your NSA using the Network Configuration screen (Section 2.9 on page 44) of the NAS Starter Utility.

Open your browser and type in the server name of the NSA ("nsa221" by default). Figure 37 NSA URL 3.

3 Login The default username and password are 'admin' and '1234' respectively. Enter your username and password. If you use the option to stay logged in for two weeks (assuming you do not log out), make sure you keep your computer secure. 48 NSA221 User's Guide Chapter 3 Web Configurator Basics Then click Login. See Chapter 12 on page 289 for how to create other user accounts.

Figure 38 NSA Login Screen If you have not done so yet, you should see a screen asking you to change your password (highly recommended) as shown next. Type a new password (and retype it to confirm) and click Apply or click Ignore. Figure 39 Change Password Screen NSA221 User's Guide 49 Chapter 3 Web Configurator Basics 3.4 Home Screens All users (including the administrator) first see the Home screen after logging in. Figure 40 Home Note: If you did not select the option to stay logged in for two weeks when you logged in, the web configurator management session automatically times out if it is left idle for 15 minutes. Simply log back into the NSA if this happens to you. The main Home screen displays icons for the various features you can access. Table 6 Main Home Screen Icons ICON DESCRIPTION Use Music, Photo, and Video to play and organize your music, picture, and video files. Use Favorite to create and edit playlists. Use File Browser to see your files in a tree-folder structure.

50 NSA221 User's Guide Chapter 3 Web Configurator Basics Table 6 Main Home Screen Icons (continued) ICON DESCRIPTION Administrators can use Application Zone to install, access, and manage the NSA's applications. Use System to edit general system settings or log into the administrator advanced configuration screens. Note: Your browser may need Windows Media Player and VLC plugins installed to play music and video files. To get the VLC plugins, you have to download and install VLC (use the .exe file). To install a VLC plugin for FireFox, when you install VLC, you have to select the Mozilla plugin option. To display your photos as a 3-D wall for quick browsing, install the CoolIris plugin. The icons at the top-right of the screen are visible from most screens. Use them to navigate between the screens and menus. The following table describes the icons.

Table 7 Global Home Labels and Icons LABEL/ICON Home Help Logout DESCRIPTION Click this to return to the Home screen. Click this to open a web help page specific to the screen you are currently configuring. Click this at any time to exit the web configurator. NSA221 User's Guide 51 Chapter 3 Web Configurator Basics 3.4.

1 Home Screens Here are some Home screen descriptions. A music screen is shown here as an example. Other screens work in a similar way. Figure 41 Music Screen B A C D This table describes common labels in the Home media screens. Not every item displays in every screen.

Table 8 Home Media Screens LABEL A B C DESCRIPTION Click a letter to go to the first item starting with that letter. View files. Double-click an item to play it. Shows which page is displaying and the total number of pages of entries. Click an arrow or type a number to go to another page of entries. 52 NSA221 User's Guide Chapter 3 Web Configurator Basics Table 8 Home Media Screens LABEL D DESCRIPTION Select the sorting criteria: Artist - Sort music by artist. All - All of the menu's files display here. Genre - Sort music by category. Folder - List the folders containing music files. Album - List the identified music albums.

Current Playlist - Show the playing and queued songs. The NSA categorizes files into genres and albums according to the information stored in your files. Files may not appear in the proper folders if they have missing, incorrect or incomplete information. Thumbnail List Play Delete Rename Click this to view the files as thumbnails. Click this to view the files as a list. Click this to play the currently selected file. You can also double-click a file to play it. Select an item and click Delete to remove it. Select an item and click Rename to change its name. Note: When you change a file name, make sure you keep the file extension unchanged.

Add to Current Playlist Add to Playlist Search Refresh Now Playing Click this to add the selected music file to the currently playing playlist. Click this to add the selected music file to a playlist. Click this to look for a file or folder by name. Click this to update the display in the screen. This link is available when a song is playing.



[You're reading an excerpt. Click here to read official ZYXEL NSA221 user guide](http://yourpdfguides.com/dref/3685280)
<http://yourpdfguides.com/dref/3685280>

Click it to see details about the song that is currently playing. 3.4.1.1 Now Playing (Music) A Now Playing link displays when a song is playing. Click it to display a panel like the following. This screen displays the name of the current song and its play progress and lets you control the playback. Figure 42 Now Playing NSA221 User's Guide 53 Chapter 3 Web Configurator Basics 3.4.1.2 Slideshow and CoolIris (Photos) In a Photo menu click the SlideShow button to display the menu's files as a slideshow. Move your cursor over the slideshow's screen to display full screen, previous, pause, and next buttons for controlling the slideshow. Figure 43 Slideshow When the CoolIris plugin is installed in your browser, click the Launch CoolIris button to display your photos as a 3-D wall for quick browsing. 3.4.

2 Favorite Use the Favorite menu to manage your playlists. 3.4.2.1 Shared Playlist Use Favorite > Shared Playlist to view and play playlists that you created externally (in iTunes, Windows Media Player, VLC media player, or Winamp for example) and saved to the NSA. When using zPilot to move files to the NSA, playlists are automatically put into the music share. 54 NSA221 User's Guide Chapter 3 Web Configurator Basics 3.4.2.2 My Favorite Use Favorite > My Favorite to create, edit, and play playlists.

These playlists are specific to the NSA and cannot be used in external music players. Figure 44 Favorite > My Favorite This table describes labels in this menu. Table 9 Favorite > My Favorite LABEL New Edit Delete All DESCRIPTION Click this to create a new playlist. Double-click a playlist or select it and click Edit to go to a screen where you can remove songs from the playlist. Within a playlist click Delete All to remove all of the playlist's songs.

3.4.3 File Browser Click File Browser to open the following screen. Use the file browsing screens to play, open, upload, and download files. A share is a set of user access permissions for a specific folder on a volume (gives someone access to a folder).

It is equivalent to the Windows concept of a shared folder, but the access rights are independent of the folder (you configure the share and the folder separately). You NSA221 User's Guide 55 Chapter 3 Web Configurator Basics can map a share to a network drive for easy and familiar file transfer for Windows users. · A folder icon with a hand indicates a share. · The administrator owns and manages the public shares. · Double-click a media file to open it.

Double-click other types of files to be able to save them. · Click to the right of a file or folder name to select it. · Use the [SHIFT] key to select a range of entries. Hold down the [CTRL] key to select multiple individual entries. · Drag and drop files to open a screen that lets you choose whether to copy or move them.

· You can upload files of up to 2 GB in size. · You can download individual files of up to 4 GB in size with Mozilla Firefox and Internet Explorer 7 and later or up to 2 GB in size with Internet Explorer 6. Figure 45 File Browser 56 NSA221 User's Guide Chapter 3 Web Configurator Basics The following table describes the labels in this screen. Table 10 File Browser LABEL Up Name DESCRIPTION Click this to go to the next higher layer in the share's folder tree. This column identifies the names of folders and files in the share. Click a file's file name to open the file or save it to your computer. Click a folder's name to display the folder's contents. This column displays a file's size in bytes. This column displays the last time the file or folder was changed (in year-month-day hour:minute:second format). Click this to open the following screen where you can create a new folder within the share.

Size Last Modified Create New Folder Specify a name to identify the folder. See Section 3.4.4 on page 59 for more information on folder names. Click Apply to create a folder or click Close to exit this screen.

Configure Share Upload Select a share and click this link to open a screen where you can see and configure share management details. Click this to open the following screen where you can add files to the share. Use the Browse button to locate your file/s and click Apply to upload the file. Click Cancel to close this screen. Note: Do not refresh the screen while an upload is going on.

Download Select a file and click this to save the file to your computer. Note: Do not refresh the screen while a download is going on. Restore When you are in a recycle bin folder, select a folder or file and click this to restore it. NSA221 User's Guide 57 Chapter 3 Web Configurator Basics 3.4.3.1 Configure Share Screen In the File Browser screen, select a share and click Configure Share to open the following screen where you can see and configure share management details. Figure 46 File Browser > Configure Share The following table describes the labels in the this screen. Table 11 File Browser > Configure Share LABEL Share Name DESCRIPTION Configure a name to identify this share. Type a share name from 1 to 239 single-byte (no Chinese characters allowed for example) ASCII characters.

The name cannot be the same as another existing local share. See Section 3.4.4 on page 59 for more information on share names. This is not configurable for the NSA's default admin, music, photo, public, and video shares. This shows the volume the share is on. It is read-only. Select the administrator or user account that is to own (manage) this share. The share owner controls access rights to the share. This is not configurable for the NSA's default admin, music, photo, public, and video shares.

Select this option to allow users to access this share. When this option is not selected, you cannot see and access this share. Select this option to keep deleted items in a recycle bin. When you delete an item, a recycle folder is created within the share, and the deleted item is stored in the recycle bin. Later if you want to retrieve a deleted item, you can select the item from the recycle folder and move/copy the item to another share.

Select this option to make the share's files available to media clients. Volume Make this share owned by Enable This Share Enable Recycle Bin Publish this share to Media Server Publish this share to Web Select this option to let people use a web browser to access this share's files without logging into the Home screens. 58 NSA221 User's Guide Chapter 3 Web Configurator Basics Table 11 File Browser > Configure Share (continued) LABEL Share Access DESCRIPTION Select who can access the files in the share and how much access they are to be given. If you publish the share to the media server or the web, all users will have at least read-only access to the share, regardless of what you configure here.



[You're reading an excerpt. Click here to read official ZYXEL](http://yourpdfguides.com/dref/3685280)

[NSA221 user guide](http://yourpdfguides.com/dref/3685280)

<http://yourpdfguides.com/dref/3685280>

This is not configurable for the NSA's default admin, music, photo, public, and video shares.

Select Keep it private to owner to allow only the share owner to read files in the share, delete files in the share and save files to the share. Select Make it public to allow anyone (with or without a user account on the NSA) to read files in the share, delete files in the share and save files to the share. Select Advanced to select which individual users can read the share's files, which users can delete the share's files, and which users are blocked from doing either. Apply Cancel Click this to save your changes. Click this to return to the previous screen without saving. 3.4.4 Share and Folder Names The name can only contain the following characters: · Alphanumeric (A-z, 0-9) and Unicode. The NSA allows FTP access to shares, folders or files with names encoded in the UTF-8 (8-bit UCS/Unicode Transformation Format) format. So your FTP client must support UTF-8 in order to access shares, folders or files on the NSA with Unicode names.

· Spaces · _ [underscores] · . [periods] · - [dashes] Other limitations include: · All leading and trailing spaces are removed automatically. @@ · Share names must be unique (they cannot be the same as other share names). · The NSA creates automatic volume names for external (USB) disk volumes. These are a type of share, so the share name you configure cannot conflict with the external (USB) disk volume names. "ExtVol1" or "ExtVol2" are examples of external (USB) disk volume names. · Folder names must be unique (they cannot be the same as other folder names). · The minimum character length of a name is one character, that is a name cannot be blank. NSA221 User's Guide 59 Chapter 3 Web Configurator Basics · The maximum character length of share name is 239 characters. · Unicode is supported for share names, although your FTP client must support UTF-8.

Full support should be available in all Windows versions after Windows 2000. 3.4.5 Application Zone Administrators can click Application Zone to go to a screen where you can enable or disable various applications for file sharing and downloading. Figure 47 Application Zone The following table describes the labels in the this screen.

Table 12 Application Zone LABEL Name Description Management Page Enable Disable DESCRIPTION This is the name of the application. This is a brief description of the application. See Chapter 9 on page 173 for more information. Click this link to go the application's management page where you can configure settings for it. See Chapter 9 on page 173 for more information.

Select a disabled application and click this to turn on the application. Some applications are always enabled and cannot be disabled. Select an enabled application and click this to turn off the application. Select the Flickr or Youtube Uploadr entry and click this to cancel all uploading. Some applications are always enabled and cannot be disabled. 60 NSA221 User's Guide Chapter 3 Web Configurator Basics Table 12 Application Zone (continued) LABEL Pause Resume DESCRIPTION Select the Flickr or Youtube Uploadr entry and click this to pause current uploading. Resume will resume current uploading. Select the Flickr or Youtube Uploadr entry and click this to resume current uploading. 3.4.

6 System Settings Click System > Settings to open the following screen. Use this screen to change general settings and an account password. Figure 48 System > Settings NSA221 User's Guide 61 Chapter 3 Web Configurator Basics The following table describes the labels in this screen. Table 13 System > Settings LABEL Double Click Behavior Setting DESCRIPTION Select Replace current playlist and start to play to have double clicking a song cause the NSA to immediately stop any currently playing song and start playing the double-clicked song. Select Append to current playlist to have double clicking a song add a song to the end of the current playlist. Ken Burns Select Yes to have the NSA automatically pan and zoom photos in slideshows. Select No to display photos in slideshows normally. Select how long to display each image in a slideshow before changing to the next. Type the user name of the account for which you want to change the password. Type the user's current password.

Create a new password for the user. You can type from one to 14 single-byte (no Chinese characters allowed for example) ASCII characters. You must type the exact same password that you just typed in the above field. Select the web configurator language from the drop-down list box. This link appears when you are logged in as the administrator.

Click it to open the advanced administration screens. See Section 3.5 on page 63 for more on the advanced administration screens. Click this to save your changes. Click this to refresh the screen.

Click this to exit the screen without saving your changes. Slide Interval Account Name Old Password New Password Password (Confirm) Language Go to system administration page Apply Reset Cancel 62 NSA221 User's Guide Chapter 3 Web Configurator Basics 3.5 Administration Screens The System > Administration link displays when you log in as the administrator. Click System > Administration in the Home screen to open the advanced administration screens. The Status screen is the first advanced administration screen that displays. Figure 49 Status 1 2 3 4 3.5.1 Global Administration Icons The icons and language label at the top-right of the screen (1) are visible from most of the administration screens. The following table describes the 'global' icons and labels. Table 14 Global Labels and Icons LABEL/ ICON Language Help About Home Logout DESCRIPTION Select the web configurator language from the drop-down list box.

Click this to open web help specific to the screen you are in. Click this to view the model name, firmware version and copyright. Click this to return to the Home screens. Click this at any time to exit the web configurator. This is the same as clicking the Logout link at the bottom of the navigation panel. NSA221 User's Guide 63 Chapter 3 Web Configurator Basics 3.5.2 Navigation Panel The navigation panel on the left of the screen (2) contains screen links. Click a link to display sub-links. There are no sub-links for the Status screen.

Certain screens also contain hyper links that allow you to jump to another screen. The following table describes the navigation panel screens. Table 15 Screens Summary LINK Status System Setting Storage Server Name Date & Time Volume SCREEN FUNCTION This screen shows system information, the status of the volumes, and the users who are currently using the NSA. Specify the NSA's server name and workgroup name. Chose a time zone and/or allow the NSA to synchronize with a time server.



[You're reading an excerpt. Click here to read official ZYXEL NSA221 user guide](http://yourpdfguides.com/dref/3685280)
<http://yourpdfguides.com/dref/3685280>

View volume and disk information and create and edit volumes. A volume is a storage area that can span one or more internal disks or a single external (USB) disk. Assign the NSA a dynamic or static IP address and DNS information. Configure your Internet gateway to allow access from the WAN (Internet) to services on the NSA. Configure PPPoE settings for a direct Internet connection.

Enable FTP file transfer to/from the NSA, set the number of FTP connections allowed, an FTP idle timeout, and the character set. Enable or disable the sharing of media files and select which shares to share. Have the NSA handle large file downloads. Let people use a web browser to access files in shares without logging into the Home screens. Subscribe the NSA to feeds to download frequently updated digital content like TV programs, radio talk shows, Podcasts (audio files), YouTube videos, or even BitTorrents. View and manage the NSA's list of printers and print jobs. Copy or synchronize files between a USB device and the NSA. Set up more useful applications in your NSA. The NSA can download multiple packages/files at once and automatically goes through all the installation steps. Upload files in selected shares to your Flickr and/or YouTube accounts.

Upload files in selected shares to FTP servers. Network TCP/IP UPnP Port Mapping PPPoE Applications FTP Server Media Server Download Service Web Publishing Broadcatching Print Server Copy/Sync Button Package Auto Upload Flickr/YouTube Auto Upload FTP Uploadr 64 NSA221 User's Guide Chapter 3 Web Configurator Basics Table 15 Screens Summary (continued) LINK Sharing SCREEN Users Groups FUNCTION View, create and edit administrator and user accounts to let people use the NSA. View, create and edit groups. Groups allow you to organize users into specific groups. You can create shares accessible only by the group members. View, create and edit shares. Shares are shared folders to which you can allow specific users read/write access rights. Configure power saving settings for the NSA and have the NSA turn itself off and on or reboot according to the schedules you configure. View the NSA's logs and configure how you want to receive the log reports. Back up and/or restore the NSA configuration file.

Configure HTTPS and the NSA's SSL certificate. Upload/upgrade new firmware to your NSA. Restart the NSA or shut it down. Click this to exit the web configurator. This is recommended to prevent unauthorized administrator access to the NSA.

Shares Maintenance Power Log Configuration SSL FW Upgrade Shutdown Logout 3.5.3 Main Window The main window (3) shows the screen you select in the navigation panel. It is discussed in the rest of this document. The Status screen is the first administration screen to display.

See Chapter 5 on page 137 for more information about the Status screen. 3.5.4 Status Messages The message text box at the bottom of the screen as you configure the NSA. (4) displays status messages NSA221 User's Guide 65 Chapter 3 Web Configurator Basics 3.5.5 Common Screen Icons The following table explains some icons that appear in several configuration screens. Table 16 Common Configuration Screen Icons ICON DESCRIPTION Edit Click this to go to a screen where you can change the configuration settings of an entry. Delete Click this to delete an entry from the list. Edit Click this to jump to related item's configuration screen.

Refresh Click this to refresh the data for the field or value with which it is associated. User See the chapter on user accounts for detailed information on variants of this icon. Share See the chapter on shares for detailed information on variants of this icon. Healthy This represents a healthy volume. Degraded This represents a degraded RAID 1 volume. Replace the faulty disk. If the replacement disk does not contain any partition, the NSA automatically restores the volume. If the replacement disk already contains a volume, you need to delete the volume and then click the Repair icon to fix the degraded RAID volume.

Down This represents a down volume. Scan Disk Click this to scan a hard disk for file system errors.

Eject Click this before you remove an external hard drive so that you do not lose data that is being transferred to or from that hard drive. Locate Click this to cause the LED on the external storage device to blink. Repair If you replace a faulty disk with a disk that contains a volume, you need to delete the volume and then click this to fix the degraded RAID volume. 66 NSA221 User's Guide Chapter 3 Web Configurator Basics 3.5.

6 Session Example (Windows) Open Windows Explorer and type two back slashes followed by the NSA name or IP address. Initially you can only read and write to the Public, Video, Music, and Photo folders until you create other shares on the NSA. This session is then displayed as shown in the following figure. Session Example (Windows) NSA221 User's Guide 67 Chapter 3 Web Configurator Basics 68 NSA221 User's Guide CHAPTER 4.1 Overview This chapter provides tutorials that show how to use the NSA.

· Creating a Volume, see page 69 · Deleting a Volume, see page 72 · File Sharing Tutorials, see page 73 · Download Service Tutorial, see page 83 · Broadcatching Tutorial, see page 99 · Copy and Flickr Auto Upload Tutorial, see page 104 · FTP Uploadr Tutorial, see page 105 · Web Configurator's Security Sessions, see page 110 · Using FTPES to Connect to the NSA, see page 122 · How to Use the BackupPlanner, see page 123 4 Tutorials 4.2 Creating a Volume This section shows you how to create a volume on your NSA. Creating a volume deletes all existing data in the hard disk. Make sure you have a backup of your existing data before following the steps in this section. Your NSA has two bays for SATA (Serial Advanced Technology Attachment) hard disks. The JBOD storage method is used if you are using a single hard disk for your NSA. NSA221 User's Guide 69 Chapter 4 Tutorials This JBOD volume shows up in the Storage > Volume screen (Section 7.4 on page 153) as follows. 4.2.

1 Creating a RAID 1 Volume This storage method allows recovery of data if your hard disk fails. To create a RAID 1 volume, you must install two SATA hard disks in your NSA. There are two ways to create a RAID 1 volume: · Click the Migrate button - If you already have a SATA hard disk with a volume and you later install a second SATA hard disk in your NSA, use the Migrate button to convert the existing JBOD volume to a RAID 1 volume. · Click the Create a SATA volume button - Use this if there are no existing volumes in your NSA. 4.2.2 Migrate Button Do the following steps to create a RAID 1 volume. 1 Once you install a second SATA hard disk in the NSA, the Storage > Volume screen shows the Migrate button. 2 Click the Migrate button and you can see the following progress bar.



[You're reading an excerpt. Click here to read official ZYXEL](http://yourpdfguides.com/dref/3685280)

[NSA221 user guide](http://yourpdfguides.com/dref/3685280)

<http://yourpdfguides.com/dref/3685280>