




Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for COMPAQ P1000. You'll find the answers to all your questions on the COMPAQ P1000 in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

User manual COMPAQ P1000
User guide COMPAQ P1000
Operating instructions COMPAQ P1000
Instructions for use COMPAQ P1000
Instruction manual COMPAQ P1000

HP LaserJet P1000 and P1500 Series
Software Technical Reference



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>

Manual abstract:

@@@HP shall not be liable for technical or editorial errors or omissions contained herein. Edition 1, 11/2007 Trademark Credits Microsoft®, Windows®, and Windows NT® are U.S. registered trademarks of Microsoft Corporation. PostScript® is a registered trademark of Adobe Systems Incorporated. Table of contents 1 Purpose and scope Introduction

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.... 1 Product configurations

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 2 Product features

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.....
..... 3 Identify product parts ...

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
..... 4 HP LaserJet P1000 Series

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
..... 4 HP LaserJet P1500 Series .

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 5 Printing-system software ...

.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

..... 7 In-box printing-system software

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 7 HP LaserJet P1000 and P1500 Series software CD, Windows partition

..... 7 Supported operating systems ..

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 7 Software for Windows ...

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 8 Windows printer drivers ..

.....
.....
.....
.....

.....
.....

.....
.....
.....
.....
.....
.....
..... 8 Printer preferences (driver)

.....
.....
.....
.....
.....
.....
.....
.....
.....
8 Printer properties online Help

.....
.....
.....
.....
.....
.....
.....
.....
. 8 Print-setting priorities

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
8 Additional Windows driver types (HP LaserJet P1500 network models)

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
8 Install the Windows printer software

.....
.....
.....
.....
.....
.....
. 9 Change printer-driver settings for Windows

.....
.....
.....
9 Embedded Web server (HP LaserJet P1500 network models only)

..... 9 Software for Macintosh .

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 9 Macintosh printer drivers

.....
.....
.....

.....
.....
.....

.....
.....

... 9 Install the Macintosh printer driver ..

.....
.....
.....
.....

.. 9 Configure the Macintosh print driver ...

.....
.....

.....
.....
.....

. 10 CD language groupings

.....
.....
.....

.....
.....
.....

.....

.....
.....
.....

.....
.. 10 Ordering software ...

.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 12 Documentation availability and localization

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

13 2 Software description Introduction

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 17 Windows printing-system software ...

.....

.....
.....
.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *18 HP Easy Printer Care ..*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *19 HP Embedded Web Server (network-ready models only) .*

.....

.....

.....

.....

.....

.....

.....

.....

..... *20 Information tab*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

20 Device Status page

.....

.....

.....

.....
.....
.....
.....

. 21 Device Configuration page

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

. 21 Supplies Status page

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.... 22 Network Summary page .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

... 23 ENWW iii Settings tab ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.....
... 24 Networking tab ..

.....
.....

.....
.....

.....
.....

.....
.....

.....
.....

.....
.....

..... 24 IPv4 Configuration page ..

.....
.....

.....
.....

.....
.....

.....
.....

.....
.....

.. 25 IPv6 Configuration page

.....
.....

.....
.....

.....
.....

.....
.....

.....
.....

..... 25 Advanced page

.....
.....

.....
.....

.....
.....

.....
.....

.....
.....

... 26 Bonjour page

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 26 Password page .

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

. 27 SNMP settings

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 27 Network Summary page .

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 28 HP Web Jetadmin

.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 29 *HP Extended Capabilities* .

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 30 *Internal Fonts*

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 31 3 *Install Windows printing-system components Installation overview ...*

.....
.....
.....

.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

..... 34 Windows installation instructions .

.....
.....
.....
.....
.....
.....
.....
.....
.....

... 35 Installing the software before the printer is connected to the computer

.....
.....
.....

. 35 Installing the software when the printer is already connected to a computer

. 52 Installation options

.....
.....
.....
.....
.....
.....
.....
.....
.....

.. 62 Windows installation for direct connections ...

.....
.....
.....
.....

.....
.....

.....
65 Printer-driver installation for Windows 2000 or Windows XP

.....
.....

..... *65 Plug-n-Play ..*

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... *66 Add Printer Wizard ..*

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... *66 Uninstall ...*

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 76 Properties tab set

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

..... 76 Printing Preferences tab set

.....
.....
.....

.....
.....
.....

.....
.....

..... 76 Print Task Quick Sets .

.....
.....
.....

.....
.....
.....

.....
.....

..... 76 Document preview image ...

.....
.....
.....

.....
.....
.....

.....
.....
.... 77 Driver tabs .

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 78 Printing Preferences tab set ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 78 iv ENWW Advanced tab features

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 78 Paper/Output ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....
.....

. 79 Printer Features

.....
.....
.....

.....
.....
.....

.....
.....
.....

. 79 Paper/Quality tab features

.....
.....
.....

.....
.....
.....

. 80 Paper Options

.....
.....

.....
.....
.....

.....
.....
.....

.... 81 Use Different Papers/Covers

.....
.....
.....

.....
.....
.....

.... 84 Print Quality

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
..... 92 Orientation .

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 96 Services tab features ...

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 97 Internet Services

.....
.....
.....

.....
.....
.....

..... 97 Print Information Pages .

.....
.....

.....
.....
.....

.....
.....
.....

.. 98 Device Services

.....
.....
.....

.....
.....
.....

.....
.....
.. 98 Properties tab set ...

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 98 Device Settings tab features

.....
.....
.....

.....
.....
.....

.....
.....
.....

99 Jam Recovery

.....
.....
.....

.....
.....

.. 116 Troubleshooting the printer setup ...

.....

.....
.....
.....

..... 117 Uninstall the Macintosh printing system ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 118 HP Embedded Web Server (EWS, network-ready models only)

.....
.....
.....
.....

118 Access to the HP EWS

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 119 Information

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 120 Device Status

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.. 120 Device Configuration

.....
.....
.....

.....
.....

.....
.....
.....
.....
.....
.....
..... 121 Supplies Status .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 121 Network Summary

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 122 Settings

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 123 Networking .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

..... *123 IPv4 Configuration ..*

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... *124 IPv6 Configuration .*

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

124 Advanced

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.... *125 Bonjour*

.....
.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.. 125 Password ...

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 126 SNMP

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

. 126 Network Summary

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.. 127 6 Engineering details Introduction ...

.....
.....

.....
.....
.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.. *129 Firmware updates*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... *130 Media attributes ...*

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

131 Media sizes

.....

.....

.....

.....

.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.. 131 Media type and tray loading ...
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
133 Index
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... *135 vi ENWW List of tables Table 1-1 Table 1-2 Table 4-1 Table 4-2 Table 5-1 Table 6-1 Table 6-2 Table 6-3 CD language groupings for Windows installation*

.....
.....
.....
.....

.....
.....
.....
.....

.....

.. 11 User documentation availability and localization ...

.....
.....

.....
.....
.....

.....
.....
.....

..... 13 Standard paper types and engine speed .

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 83 Page orientation ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 93 CD language groupings for Macintosh installation

.....
.....
.....

.....
.....
.....

.....
.....

... 106 Supported media sizes ..

.....
.....
.....

.....
.....
.....
.....
.....
.....
.....
.....

... 131 Tray 1 media information ..

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

.... 133 Tray 2 media information

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 134 ENWW vii viii ENWW List of figures Figure 1-1 Figure 1-2 Figure 1-3 Figure 1-4 Figure 2-1 Figure 2-2 Figure 2-3 Figure 2-4 Figure 2-5 Figure 2-6 Figure 2-7 Figure 2-8 Figure 2-9 Figure 2-10 Figure 2-11 Figure 2-12 Figure 2-13 Figure 3-1 Figure 3-2 Figure 3-3 Figure 3-4 Figure 3-5 Figure 3-6 Figure 3-7 Figure 3-8 Figure 3-9 Figure 3-10 Figure 3-11 Figure 3-12 Figure 3-13 Figure 3-14 Figure 3-15 Figure 3-16 Figure 3-17 Figure 3-18 Figure 3-19 Figure 3-20 Figure 3-21 Figure 3-22 HP LaserJet P1000 Series, front view

.....
.....
.....
.....
.....
.....
.....

..... 4 HP LaserJet P1000 Series, back view .

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

... 4 HP LaserJet P1500 Series, front view

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 5 HP LaserJet P1500 Series, back view ...

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

. 5 Getting Started Guide -- Welcome screen

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 18 HP EWS Device Status page

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 21 HP EWS Device Configuration page ..

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 22 HP EWS Supplies Status page .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 22 HP EWS Network Summary page .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 23 HP EWS Settings tab

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 24 HP EWS IPv4 Configuration page .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.... 25 HP EWS IPv6 Configuration page

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 25 HP EWS Advanced page .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 26 HP EWS Bonjour page ..

.....
.....
.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

... 26 HP EWS Password page ..

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 27 HP EWS SNMP page

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... 27 HP EWS Network Summary page ...

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

28 Driver Installation -- Getting Started Guide -- Welcome screen

.....
.....
.....

.....
.....
.....

. 35 Driver Installation -- Select Your Connection screen

.....
.....
.....
.....

.....
.....
.....
.....

36 Driver Installation -- Begin Setup screen

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 36 Driver Installation -- Software Wizard -- Welcome screen ...

.....
.....
.....
.....

.....
.....
.....

..... 37 Driver Installation -- End User License Agreement screen ...

.....
.....
.....
.....

.....
.....
.....

..... 38 Driver Installation -- Select the Printer screen ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

. 38 Driver Installation -- Printer Connections screen

.....
.....
.....
.....
.....
.....
.....
.....

. 39 Driver Installation -- Identify Printer screen

.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 40 Driver Installation -- Firewall Detected

.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 41 Driver Installation -- Printer Not Found screen

.....
.....
.....
.....
.....
.....
.....

.. 42 Driver Installation -- Printer Found screen ...

.....
.....
.....
.....
.....
.....
.....

..... 43 Driver Installation -- Specify Printer screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 44 Driver Installation -- Check Printer Connection screen

.....
.....
.....

.....
.....
.....

45 Driver Installation -- Confirm Network Settings screen

.....
.....
.....

.....
.....
.....

.... 46 Driver Installation -- Confirm Change Settings screen

.....
.....
.....

.....
.....
.....

..... 47 Driver Installation -- Change TCP/IP Settings screen ..

.....
.....
.....

.....
.....
.....

.....
.....
.....

... 48 Driver Installation -- Setup Settings screen ..

.....
.....
.....

.....
.....
.....

.....

.....
.....
.....

.... 49 Driver Installation -- Exit Setup screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 49 Driver Installation -- HP Extended Capabilities screen

.....
.....
.....

.....
.....
.....

..... 50 Driver Installation -- Setup Complete screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

..... 51 Driver Installation -- Setup Complete screen 2

.....
.....
.....

.....
.....
.....

. 51 Driver Installation -- Reboot screen

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....

.....

.... 52 ENWW ix Figure 3-23 Figure 3-24 Figure 3-25 Figure 3-26 Figure 3-27 Figure 3-28 Figure 3-29 Figure 3-30 Figure 3-31 Figure 3-32 Figure 3-33
Figure 3-34 Figure 3-35 Figure 3-36 Figure 3-37 Figure 3-38 Figure 3-39 Figure 3-40 Figure 4-1 Figure 4-2 Figure 4-3 Figure 4-4 Figure 4-5 Figure 4-6
Figure 4-7 Figure 4-8 Figure 4-9 Figure 4-10 Figure 4-11 Figure 4-12 Figure 4-13 Figure 4-14 Figure 4-15 Figure 5-1 Figure 5-2 Figure 5-3 Figure 5-4
Figure 5-5 Figure 5-6 Figure 5-7 Figure 5-8 Figure 5-9 Figure 5-10 Figure 5-11 Figure 5-12 Figure 5-13 Figure 5-14 Figure 5-15 Figure 5-16 Figure 5-17
Add Printer Wizard -- Welcome Screen .



[You're reading an excerpt. Click here to read official COMPAQ](http://yourpdfguides.com/dref/3235268)

[P1000 user guide](http://yourpdfguides.com/dref/3235268)

<http://yourpdfguides.com/dref/3235268>

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
. 53 Add Printer Wizard -- Local or Network Printer screen

.....
.....

.....
.....
.....

.....
.....

54 Add Printer Wizard -- Select the Printer Port screen

.....

.....
.....
.....

.....
.....
.....

.. 55 Add Printer Wizard -- Manufacturer and model screen

.....
.....
.....

.....
.....
.....

..... 56 Add Printer Wizard -- Install from Disk

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 56 Add Printer Wizard -- Locate File

.....
.....
.....

.....
.....
.....
.....
.....
.....
.....

. 57 Add Printer Wizard -- Install From Disk, screen 2

.....
.....
.....
.....
.....
.....

... 57 Add Printer Wizard -- Manufacturer and Model screen 2 ..

.....
.....
.....
.....
.....

... 58 Add Printer Wizard -- Name Your Printer screen ..

.....
.....
.....
.....
.....

..... 58 Add Printer Wizard -- Printer Sharing screen

.....
.....
.....
.....
.....

.... 59 Add Printer Wizard -- Print Test Page screen .

.....
.....
.....
.....
.....

.....
.....
.....

.. 60 Add Printer Wizard -- Completing the Add Printer Wizard screen

.....
.....
.....

.....
.....

.... 61 Windows Control Panel screen .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

68 Windows Change or Remove Programs screen

.....
.....
.....

.....
.....
.....
.....

.....
.....

68 Welcome to the LaserJet P1000 / P1500 series Uninstall Wizard dialog box

.....

.....
.....

69 HP LaserJet P1000 / P1500 series Driver Uninstall Information dialog box

.....

.....
.....

... 70 HP LaserJet P1000 / P1500 series Driver Uninstall Information dialog box, screen 2 ..

.....

..... 71 Uninstall Complete dialog box

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.. 72 Paper Type Warning message ...
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

75 Advanced tab

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

78 Paper/Quality tab

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... 80 Paper Options group box .

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.... *81 Custom Paper Size dialog box*

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.... *82 Use Different Paper/Covers options* .

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....

... *84 Effects tab*

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....

.....
.....

..... 86 Preview images - Legal on Letter; Scale to Fit off (left) and on (right)

.....
.....
.....

.....
.....

.. 87 Watermark Details dialog box ..

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 89 Finishing tab

.....
.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 92 Print on Both Sides Instructions ...

.....
.....

.....
.....
.....

.....
.....
.....

.....
.....
.....

.. 93 Page-order preview images

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

..... 95 Services tab ...

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.. 97 Device Settings tab ...

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

. 99 About tab

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 100 HP LaserJet P1000/P1500 CD-ROM icon .

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

... 110 HP LaserJet P1000/P1500 screen

.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 110 Welcome to the HP LaserJet P1000/P1500 Series Installer dialog ..

.....
.....
.....
.....

.....
.....

.... 111 Software License Agreement dialog .

.....
.....

.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 111 Select a Destination dialog ...

.....
.....
.....
.....

115 Print & Fax screen

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

115 Printer List screen

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

... 116 Printer List screen .

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....

..... 122 HP EWS Settings tab

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

. 123 x ENWW Figure 5-18 Figure 5-19 Figure 5-20 Figure 5-21 Figure 5-22 Figure 5-23 Figure 5-24 HP EWS IPv4 Configuration page

.....
.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

.. 124 HP EWS IPv6 Configuration page ...

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....

... 124 HP EWS Advanced page ..

.....
.....

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

..... 127 ENWW xi xii ENWW 1 Purpose and scope Introduction Product configurations Product features Identify product parts Printing-system software Documentation availability and localization This software technical reference (STR) provides information about and troubleshooting tips for the printing-system software for the product. This STR is prepared in an electronic format to serve as a quick-reference tool for Customer Care Center (CCC) agents, support engineers, system administrators, management information systems (MIS) personnel, and end users, as appropriate. NOTE: This STR describes drivers that are shipped on the printing-system software CD that comes with the product.

This STR does not describe drivers that will become available on the Web. The following information is included in this STR: Descriptions of drivers, operating systems, and system environments Procedures for installing and uninstalling the printing-system software components For information about the location of information within chapters, see the table of contents. An index is also provided in this STR. ENWW Introduction 1 Product configurations HP LaserJet P1000 Series HP LaserJet P1500 Series First Page Out: < 8.5 seconds Speed: 16 A4 pages per minute (ppm), 17 Letter-size ppm. Tray: 150 sheet universal tray. Connectivity: Hi-Speed USB 2.0 port. First Page Out: < 6.5 seconds Speed: 22 A4 pages per minute (ppm), 24 Letter-size ppm. Trays: 10 sheet priority feed slot and a 250 sheet universal tray Connectivity: Hi-Speed USB 2.0 port. On-board networking (not available on all models). 2 Chapter 1 Purpose and scope ENWW Product features Benefit Excellent print quality Supporting features Ease of use Flexible paper handling HP print cartridges. 600 by 600 dots per inch (dpi) text and graphics.

Adjustable settings to optimize print quality. The print cartridge is easy to install. Convenient access to the print cartridge and to the paper path through the cartridge door. Adjust paper tray with one hand. Main tray for letterhead, envelopes, labels, transparencies, custom-sized media, postcards, and heavy paper. Priority feed slot for letterhead, envelopes, labels, transparencies, custom-sized media, postcards, and heavy paper. A 125-sheet top output bin. Print on Both Sides (manually). Hi-Speed 2.0 USB port. Built-in internal print server for connecting to a 10/100BaseT network. (not available on all models) The device automatically conserves electricity by substantially reducing power consumption when it is not printing. N-up printing (printing more than one page on a sheet) features saves paper. When printing pages that are to be stored long-term, this option sets the device to a mode that reduces toner smearing and dusting. Select Archive as the paper type.

A Supplies Status page with print cartridge gauges that estimate remaining supply level. No-shake cartridge design. Authentication for original HP print cartridges. Easy ordering for replacement supplies. Online user guide compatible with text screen-readers. All doors and covers can be opened with one hand. Kensington lock receptacle on back of device. Interface connections Energy savings Economical printing Archive printing Supplies Accessibility Security ENWW Product features 3 Identify product parts HP LaserJet P1000 Series Figure 1-1 HP LaserJet P1000 Series, front view 1 2 3 4 5 6 7 8 Output bin Foldable Output Tray Extension Priority feed slot (not available on some models) Foldable Main Input tray Short Media Extender (not available on some models) Power button Cartridge door lift-tab Control panel Figure 1-2 HP LaserJet P1000 Series, back view 1 USB Port 4 Chapter 1 Purpose and scope ENWW 2 3 Power receptacle Serial number HP LaserJet P1500 Series Figure 1-3 HP LaserJet P1500 Series, front view 1 2 3 4 5 6 7 Output bin Foldable Output Tray Extension Priority feed slot Input tray Power button Cartridge door lift-tab Control panel Figure 1-4 HP LaserJet P1500 Series, back view 1 USB Port ENWW Identify product parts 5 2 3 4 HP internal network port (not available on some models) Power receptacle Serial Number 6 Chapter 1 Purpose and scope ENWW Printing-system software The software CD for the HP LaserJet P1000 and P1500 Series contain a variety of files for installing the printing-system software on your computer. This section describes the files that are available on the software CD, as well as additional support and fulfillment information. In-box printing-system software The HP LaserJet P1000 and P1500 Series printing-system software consist of two partitions: one for installation on Windows® operating systems and the other for Macintosh operating systems.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>

The files in each partition include both documentation files and files that are required to install and uninstall the systems. HP LaserJet P1000 and P1500 Series software CD, Windows partition The HP LaserJet P1000 and P1500 Series printing-system software is delivered on a CD that is included with the product. The CD include the following files: Installation files Uninstall files Printer driver Online Help Order Reminder .CHM version of the HP LaserJet P1000 and P1500 Series User Guide .PDF version of the HP LaserJet P1000 and P1500 Series User Guide Registration link Readme Status-message files To view the directories and support files, insert the HP LaserJet P1000 and P1500 Series printingsystem software CD into the CD-ROM drive on your computer, right-click Start, click Explore, and then select the CD-ROM drive.

Supported operating systems The device comes with software for the following operating systems: Windows 2000 Windows Server 2003 (32-bit and 64-bit) For more information about upgrading from Windows 2000 Server to Windows Server 2003; using Windows Server 2003 Point and Print; or using Windows Server 2003 Terminal Services and Printing, go to www.microsoft.com. Windows® XP (32-bit and 64-bit) ENWW Printing-system software 7 Windows Vista (32-bit and 64-bit) Macintosh OS X v10.3.

9, and above Software for Windows Windows printer drivers A printer driver is the software that provides access to printer features and provides the means for the computer to communicate with the device. Printer preferences (driver) Printer preferences control the device. You can change the default settings, such as media size and type, printing multiple pages on a single sheet of media (N-up printing), resolution, and watermarks. You can access the printer preferences in the following ways: Through the software application that you are using to print. This only changes the settings for the current software application. Through the Windows operating system. This changes the default settings for all future print jobs. NOTE: Because many software applications use a different method of accessing the printer properties, the following section describes the most common methods used in Windows 2000 and Windows XP. Printer properties online Help The printer properties online Help, also called the driver Help, includes specific information about the functions in the printer properties. This online Help guides you through the process of changing your printer default settings.

For some drivers, online Help provides context-sensitive help that describes the options for the driver feature you are currently using. To access the printer properties online Help 1. 2. From the software application, click File, and then click Print. Click Properties, and then click Help. Print-setting priorities There are two ways to change print settings for this device: in the software application or in the printer driver. Changes made in the software application override settings changed in the printer driver. Within a software application, changes made in the Page Setup dialog box override changes made in the Print dialog box. If more than one method is available to change a particular print setting, use the method that has the highest priority. Additional Windows driver types (HP LaserJet P1500 network models) The HP LaserJet P1500 network models also feature an available PCL 5e printer driver.

Use the Add Printer feature to install the driver. 8 Chapter 1 Purpose and scope ENWW Install the Windows printer software To install printer software for Windows Server 2003 See the operating system documentation for instructions on installing a printer driver. To install printer software for Windows 2000 and XP Insert the software CD that came with the device into the computer CD-ROM drive. Follow the onscreen installation instructions to install the printer software. NOTE: If the Welcome screen does not open, click Start on the Windows taskbar, click Run, type Z:\setup (where Z is your CD drive letter), and click OK.

Change printer-driver settings for Windows To change the settings for all print jobs until the software program is closed 1. On the File menu in the software program, click Print. Select the driver, and then click Properties or Preferences. To change the default settings for all print jobs To change the device configuration settings 1. 2.

The steps can vary; this procedure is most common. Click Start, click Settings, and then click Printers (Windows 2000) or Printers and Faxes (Windows XP Professional and Server 2003) or Printers and Other Hardware Devices (Windows XP Home). For Windows Vista, click Start, click Control Panel, and then click Printer. 1. Click Start, click Settings, and then click Printers (Windows 2000) or Printers and Faxes (Windows XP Professional and Server 2003) or Printers and Other Hardware Devices (Windows XP Home). For Windows Vista, click Start, click Control Panel, and then click Printer. 2. Right-click the driver icon, and then select Printing Preferences. 2. Right-click the driver icon, and then select Properties.

Click the Device Settings tab. 3. Embedded Web server (HP LaserJet P1500 network models only) You can use the embedded Web server to configure the device, view status information, and obtain problem-solving information. See HP Embedded Web Server (network-ready models only) on page 20 for more information. Software for Macintosh Macintosh printer drivers A printer driver is the software component that provides access to printer features and provides the means for the computer to communicate with the device. Install the Macintosh printer driver This section explains how to install the printing system software for Macintosh OS X v10.3.9, and above. 1. 2.

Insert the software CD into the CD-ROM drive and run the installer. Double-click the CD icon on the desktop ENWW Printing-system software 9 3. 4. 5. Double-click the Installer icon.

Follow the instructions on the computer screen. Print a test page or a page from any software program to make sure that the software is correctly installed. If installation fails, reinstall the software. If this fails, see the Known Issues and Workarounds section of the Install Notes. The Install Notes are located on the software CD or at the support Web site (www.

hp.com/support/ljP1000 or www.hp.com/support/ljP1500). Configure the Macintosh print driver Use one of the following methods to open the Macintosh printer driver from your computer: Operating System To change the settings for all print jobs until the software program is closed To change the print job default To change the configuration settings (for example, turn on settings (for example, add a Print on Both Sides by default) tray or enable/disable manual two-sided printing) 1. On the File menu, click Print. Change the settings that you want on the various pop-up menus. On the Presets pop-up menu, click Save as and type a name for the preset.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)

<http://yourpdfguides.com/dref/3235268>

1. Open Printer Setup Utility by selecting the hard drive, clicking Applications, clicking Utilities, then double-clicking Printer Setup Utility. Click the print queue. On the Printers menu, click Show Info. Macintosh OS X v10.3.9 1. On the File menu, click Print. Change the settings that you want on the various pop-up menus. 2.

2. 3. These settings are saved in the Presets menu. To use the new settings, you must select the saved preset option every time you open a program and print. Macintosh OS X v10.

4.3 and above 1. On the File menu, click Print. Change the settings that you want on the various pop-up menus. 1.

On the File menu, click Print. Change the settings that you want on the various pop-up menus. On the Presets pop-up menu, click Save as and type a name for the preset. These settings are saved in the Presets menu. To use the new settings, you must select the saved preset option every time you open a program and print. 2. 3. 1. Open Printer Setup Utility by selecting the hard drive, clicking Applications, clicking Utilities, then double-clicking Printer Setup Utility. Click the print queue.

On the Printers menu, click Show Info. 2. 2. 3. 4. CD language groupings The following table presents the Windows language groups that are included on the software CD for the product. 10 Chapter 1 Purpose and scope ENWW Table 1-1 CD language groupings for Windows installation CD Rest of World CD Languages Asia CD Arabic Bulgarian Catalan Croatian Czech Danish Dutch English Estonian Finnish French German Greek Hebrew Hungarian Italian Kazakh Latvian Lithuanian Norwegian Polish Portuguese, Brazilian Romanian Russian Serbian Slovak Slovenian Spanish Swedish Turkish Ukrainian English Korean ENWW Printing-system software 11 Table 1-1 CD language groupings for Windows installation (continued) CD Languages Simplified Chinese Thai Traditional Chinese Vietnamese Ordering software If you need a replacement CD or a newer version of the product software, go to the following Web site: www.hp.com/support/ljP1000 or www.hp.com.

Click CD Order Page to order, or click Download drivers and software to get the software update. To request the software CD by phone, see the following Web site for the correct contact number for your country/region: www.hp.com/country/us/en/wwcontact.html

12 Chapter 1 Purpose and scope ENWW Documentation availability and localization The documentation in the following table is available for the product. Table 1-2 User documentation availability and localization Document name HP LaserJet P1000 and P1500 Series User Guide Languages Arabic Bahasa Bulgarian Catalan Croatian Czech Danish Dutch English Estonian Finnish French German Greek Hebrew Hungarian Italian Kazakh Korean Latvian Lithuanian Norwegian Polish Portuguese, Brazilian Romanian Russian Simplified Chinese Slovak Slovenian Spanish Location The HP LaserJet P1000 and P1500 Series User Guide is available in electronic format on the HP LaserJet P1000 and P1500 Series software CD. This guide is also available by clicking Manuals at the following Web sites: www.hp.com/support/ljP1000 or www.hp.com.

hp.com/support/ljP1500 ENWW Documentation availability and localization 13 Table 1-2 User documentation availability and localization (continued) HP LaserJet P1000 and P1500 Series Welcome Mat Swedish Thai Traditional Chinese Ukrainian Arabic Bahasa Bulgarian Catalan Croatian Czech Danish Dutch English Estonian Finnish French German Greek Hebrew Hungarian Italian Kazakh Korean Latvian Lithuanian Norwegian Polish Portuguese, Brazilian Romanian Russian Simplified Chinese Slovak Slovenian Spanish The HP LaserJet P1000 and P1500 Series Welcome Mat is available in electronic format on the HP LaserJet P1000 and P1500 Series software CD. This guide is also available by clicking Manuals at the following Web site: www.hp.com/support/ljP1000 or www.hp.com/support/ljP1500

14 Chapter 1 Purpose and scope ENWW Table 1-2 User documentation availability and localization (continued) HP LaserJet P1000 and P1500 Series Printing-System Install Notes Swedish Thai Traditional Chinese Ukrainian The HP LaserJet P1000 and P1500 Series Printing-System Install Notes are available in electronic format on the HP LaserJet P1000 and P1500 Series software CD. English ENWW Documentation availability and localization 15 16 Chapter 1 Purpose and scope ENWW 2 Software description Introduction The HP LaserJet P1000 and P1500 Series printer comes with software and installers for Windows and Macintosh systems. Linux systems also support the HP LaserJet P1000 and P1500 Series printer, and software is available on the Web. For information about specific system installers, drivers, and components, see the section that corresponds to that system.

Topics: Windows printing-system software HP Easy Printer Care HP Embedded Web Server (network-ready models only) HP Web Jetadmin HP Extended Capabilities Internal Fonts ENWW Introduction 17 Windows printing-system software In Windows operating systems, insert the HP LaserJet P1000 and P1500 Series printing-system software CD in the CD-ROM drive to open an interactive CD browser. Use the CD browser to install the print drivers and related components, and to gain access to online user documentation and Adobe Acrobat Reader software. The following figure shows the main screen of the HP LaserJet P1000 and P1500 Series printing-system software CD. If the screen does not appear when you insert the software CD into the CD-ROM drive, follow these steps to open the CD browser: 1. 2. 3. 4. Click Start. Click Run. Click Browse.

... and navigate to the root directory of the software CD. Double-click the Setup.

exe file to start the installer. Figure 2-1 Getting Started Guide -- Welcome screen Click on your product to launch an animated setup demonstration and to install the software for your product. For more information, see Installing the software before the printer is connected to the computer on page 35. 18

Chapter 2 Software description ENWW HP Easy Printer Care HP Easy Printer Care software is designed for end users and for those who keep printers up and running in small and large business groups. You can view the status of up to 15 supported HP LaserJet printers, set up printer and supply alerts, generate printer-usage reports, and reorder supplies from HP or a choice of resellers.

The HP Easy Printer Care Software is available through a link in the printing-system software CD, or on the Web at the following Web site: www.hp.com/go/easyprintercare ENWW HP Easy Printer Care 19 HP Embedded Web Server (network-ready models only) The HP Embedded Web Server (HP EWS) is a Web-based application that allows users to control settings on the HP LaserJet P1505n printer through a Web browser. To open the HP EWS, connect the device to the network, open a Web browser, and type the IP address for the device in the address bar.



[You're reading an excerpt. Click here to read official COMPAQ](http://yourpdfguides.com/dref/3235268)

[P1000 user guide](http://yourpdfguides.com/dref/3235268)

<http://yourpdfguides.com/dref/3235268>

NOTE: If the HP LaserJet P1000 or P1500 Series printer is connected to the computer through the USB port, you do not have access to the HP EWS. The following tabs are available in the HP EWS: Information tab Settings tab Networking tab Information tab Use the Information tab to access and print detailed information regarding device and supply status, device configuration, network configuration, and usage. The Information tab contains the following pages: Device Status page Device Configuration page Supplies Status page Network Summary page 20 Chapter 2 Software description ENWW Device Status page The Device Status page shows device status messages. The Device Status page also shows some pertinent device information and device settings. Figure 2-2 HP EWS Device Status page ENWW HP Embedded Web Server (network-ready models only) 21 Device Configuration page The Device Configuration page shows the values of all of the settings that are available in the device. The contents of this page are consistent with the configuration page that the firmware generates.

Figure 2-3 HP EWS Device Configuration page Supplies Status page The Supplies Status page shows the status of all of the device supplies, including the print cartridges. Figure 2-4 HP EWS Supplies Status page 22 Chapter 2 Software description ENWW Network Summary page The Network Summary page contains information about the network and its enabled features. @@Figure 2-5 HP EWS Network Summary page ENWW HP Embedded Web Server (network-ready models only) 23 Settings tab Use the Settings tab to view and change print settings for the device. Figure 2-6 HP EWS Settings tab Networking tab Use the Networking tab to view and change settings for the network connection and communication with the device. The following pages are available: IPv4 Configuration page IPv6 Configuration page Advanced page Bonjour page Password page SNMP settings Network Summary page 24 Chapter 2 Software description ENWW IPv4 Configuration page Figure 2-7 HP EWS IPv4 Configuration page IPv6 Configuration page Figure 2-8 HP EWS IPv6 Configuration page ENWW HP Embedded Web Server (network-ready models only) 25 Advanced page Use the Advanced page to configure the enabled settings and other settings, such as link speed, for the device. Figure 2-9 HP EWS Advanced page Bonjour page Use the Bonjour page to enable or disable the Bonjour settings for the device. Figure 2-10 HP EWS Bonjour page 26 Chapter 2 Software description ENWW Password page Use this page to set or change the administrator password. Figure 2-11 HP EWS Password page SNMP settings Use this page to configure the simple network management protocol (SNMP) settings for the device. Figure 2-12 HP EWS SNMP page ENWW HP Embedded Web Server (network-ready models only) 27 Network Summary page The Network Summary page contains information about the network and its enabled features. Figure 2-13 HP EWS Network Summary page 28 Chapter 2 Software description ENWW HP Web Jetadmin Use the HP Web Jetadmin and a Web browser to manage HP Jetdirect-connected devices within an intranet.

HP Web Jetadmin is a browser-based management tool that should be installed only on a single network-administration server. To download a current version of HP Web Jetadmin, and for the latest list of host systems that support HP Web Jetadmin, go to the following Web site: www.hp.com/go/webjetadmin ENWW HP Web Jetadmin 29 HP Extended Capabilities When you install the HP LaserJet P1000 and P1500 Series printing-system software, you have the option of participating in HP's voluntary program for communication between your system and HP. This feature, available through software that is included on the printing-system software CD, helps HP monitor toner usage.

If you select the option to participate, you receive an invitation about two weeks later. It contains full disclosure of the information to be communicated.

Participation is entirely voluntary, and the impact on processing and connecting speed is negligible. Personal information is never sent to HP without permission. Network addresses are used only to enable the connection and for security purposes.

If you decline the invitation, the invitation dialog box does not appear again, and no data is gathered. 30 Chapter 2 Software description ENWW Internal Fonts The following section lists the fonts that are internal to the HP LaserJet P1505n. Albertus Extra Bold Albertus Medium CG Times CG Times Bold CG Times Bold Italic CG Times Italic Courier Courier Bold Courier Bold Italic Courier Italic Letter Gothic Letter Gothic Bold Letter Gothic Italic Univers Bold Univers Bold Condensed Univers Bold Condensed Italic Univers Bold Italic Univers Medium Condensed Univers Medium Condensed Italic Univers Medium Italic Windings ENWW Internal Fonts 31 32 Chapter 2 Software description ENWW 3 Install Windows printing-system components NOTE: This chapter covers information about the HP LaserJet P1000 and P1500 Series printingsystem software for Windows. For information about Macintosh installations, see Macintosh software and utilities on page 103. This chapter provides information about the following topics: Installation overview Windows installation instructions Installation options Uninstall ENWW 33 Installation overview The software for the HP LaserJet P1000 and P1500 Series is shipped on one CD. On Windows systems, the Setup program installs the HP LaserJet P1000 or P1500 Series printing-system software from the CD onto the hard disk and updates the Windows files. On all of the supported platforms, a series of query dialog boxes guides you through the installation process. You are asked to provide information about your computer environment. The Installer guides you through the installation, whether you are configuring a directly-connected (USB) or a networked product. 34 Chapter 3 Install Windows printing-system components ENWW Windows installation instructions HP recommends that you install the software before connecting the product to the computer.

However, it is possible to install the software if the product is already connected by using Plug-n-Play option from within the Add Printer Wizard. The following sections show the dialog box options that appear during the HP LaserJet P1000 and P1500 Series printing-system software installation on Windows operating systems. Installing the software before the printer is connected to the computer NOTE: HP recommends that you install the software before connecting the product to the computer (software-first installation). These instructions are intended to be used the first time that you install the HP LaserJet P1000 or P1500 Series printing-system software.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>

NOTE: Unless otherwise noted, the following installation instructions apply to all models of the HP LaserJet P1000 and P1500 Series. Figure 3-1 Driver Installation -- Getting Started Guide -- Welcome screen STEP 1 Select your product (HP LaserJet P1000 Series or HP LaserJet P1500 Series) from the Getting Started Guide -- Welcome dialog box. Selecting HP LaserJet P1000 Series takes you to the Software Wizard -- Welcome dialog box (Step 4). Selecting HP LaserJet P1500 Series takes you to the Select Your Connection dialog box (Step 2). ENWW Windows installation instructions 35 Figure 3-2 Driver Installation -- Select Your Connection screen STEP 2 Select the appropriate type of connection (USB or Network) for your product. NOTE: This option is only available if you select the HP LaserJet P1500 Series printer.

Figure 3-3 Driver Installation -- Begin Setup screen 36 Chapter 3 Install Windows printing-system components ENWW STEP 3 Home returns you to the Welcome dialog box (Step 1). Install Printer Software skips the product setup process and opens the Software Wizard (Step 4). View User Guide provides additional information about your product. Begin Setup provides detailed instructions about how to setup your product. NOTE: It may be necessary to reboot your computer at the end of the software installation process.

Ensure all applications are closed before installing the software. Figure 3-4 Driver Installation -- Software Wizard -- Welcome screen STEP 4 Documentation launches the Hewlett-Packard LaserJet P1000/P1500 Series Install Notes in your Web browser. Next takes you to the End User License Agreement dialog box (Step 5). Cancel takes you to the Exit Setup dialog box (Step 18). ENWW Windows installation instructions 37 Figure 3-5 Driver Installation -- End User License Agreement screen STEP 5 Back returns you to the Welcome dialog box (Step 4).

Yes takes you to the Select the Printer dialog box (Step 6). No takes you to the Exit Setup dialog box (Step 18). Figure 3-6 Driver Installation -- Select the Printer screen 38 Chapter 3 Install Windows printing-system components ENWW STEP 6 Back returns you to the End User License Agreement dialog box (Step 5). Next takes you to the Setup Settings dialog box (Step 17) if you select the HP LaserJet P1005, HP LaserJet P1006 or HP LaserJet P1505, or to the Printer Connections dialog box (Step 7), if you select the HP LaserJet P1505n. Cancel takes you to the Exit Setup dialog box (Step 18). NOTE: Steps 716 are only available if you select the HP LaserJet P1505n. Figure 3-7 Driver Installation -- Printer Connections screen STEP 7 Back returns you to the Select the Printer dialog box (Step 6). Next takes you to the Setup Settings dialog box (Step 17) if you select Connect Directly to this Printer, or to the Identify Printers dialog box (Step 8) if you select Connect Via the Network. Cancel takes you to the Exit Setup dialog box (Step 18).

ENWW Windows installation instructions 39 Figure 3-8 Driver Installation -- Identify Printer screen STEP 8 Help launches the Identify Printer troubleshooting tips in your Web browser. Back returns you to the Printer Connections dialog box (Step 7). Next takes you to the Specify Printer dialog box (Step 12) if you select Specify a Printer by Address, or to one of the three following dialog boxes if you select Select from a List of Detected Printers (Recommended): The Firewall Detected dialog box (Step 9) may appear if the Window's Internet Connection Firewall port used by the printer is closed. The Printer Not Found dialog box (Step 10) may appear if the computer is unable to communicate with the printer. The Printer Found dialog box (Step 11) may appear if the computer is able to communicate with the printer. Cancel takes you to the Exit Setup dialog box (Step 18). 40 Chapter 3 Install Windows printing-system components ENWW Figure 3-9 Driver Installation -- Firewall Detected STEP 9 Help launches the Firewall Detected troubleshooting tips in your Web browser. Back returns you to the Identify Printer dialog box (Step 8). Next takes you to the Specify Printer dialog box (Step 12) if you select Specify a Printer by Address, or to one of the three following dialog boxes if you select Select from a List of Detected Printers (Recommended): The Firewall Detected dialog box (Step 9) may appear if the Window's Internet Connection Firewall port used by the printer is closed. The Printer Not Found dialog box (Step 10) may appear if the computer is unable to communicate with the printer.

The Printer Found dialog box (Step 11) may appear if the computer is able to communicate with the printer. Cancel takes you to the Exit Setup dialog box (Step 18). ENWW Windows installation instructions 41 Figure 3-10 Driver Installation -- Printer Not Found screen STEP 10 Help launches the Printer Not Found troubleshooting tips in your Web browser. Back returns you to either the Identify Printer dialog box (Step 8) or the Firewall Detected dialog box (Step 9) depending on the configuration of the Window's Internet Connection Firewall port. Next takes you to the Check Printer Connection dialog box (Step 13). Cancel takes you to the Exit Setup dialog box (Step 18). 42 Chapter 3 Install Windows printing-system components ENWW Figure 3-11 Driver Installation -- Printer Found screen STEP 11 Help launches the Printer Found troubleshooting tips in your Web browser. Back returns you to either the Identify Printer dialog box (Step 8) or the Firewall Detected dialog box (Step 9) depending on the configuration of the Window's Internet Connection Firewall port. Next takes you to the Confirm Network Settings dialog box (Step 14) if you select Yes, or to the Check Printer Connection dialog box (Step 13) if you select No. Cancel takes you to the Exit Setup dialog box (Step 18).

ENWW Windows installation instructions 43 Figure 3-12 Driver Installation -- Specify Printer screen STEP 12 Help launches the Specify Printer troubleshooting tips in your Web browser. Back returns you to either the Identify Printer dialog box (Step 8) or the Firewall Detected dialog box (Step 9) depending on the configuration of the Window's Internet Connection Firewall port. Next takes you to the Printer Found dialog box (Step 11) if a valid Hardware Address, IP Address, or IP Hostname is inserted and the computer can communicate with the printer, or to the Printer Not Found dialog box (Step 10) if an invalid Hardware Address, IP Address, or IP Hostname is inserted or the computer cannot communicate with the printer. Cancel takes you to the Exit Setup dialog box (Step 18). 44 Chapter 3 Install Windows printing-system components ENWW Figure 3-13 Driver Installation -- Check Printer Connection screen STEP 13 Help launches the Check Printer Connection troubleshooting tips in your Web browser. Back returns you to either the Printer Not Found dialog box (Step 10).



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>

Next takes you to the Specify Printer dialog box (Step 12) if you select Specify a Printer by Address, or will try again to detect your printer on the network if you select Search Again for All Available Printers. If a printer can be found on the network, you will be taken to the Printer Found dialog box (Step 11), or if one cannot be found, you will be taken to the Printer Not Found dialog box (Step 10). Cancel takes you to the Exit Setup dialog box (Step 18). ENWW Windows installation instructions 45 Figure 3-14 Driver Installation -- Confirm Network Settings screen STEP 14 Help launches the Confirm Network Settings troubleshooting tips in your Web browser.

Change Settings takes you to the Confirm Change Settings dialog box (Step 15). Back returns you to the Printer Found dialog box (Step 11). Next takes you to the Setup Settings dialog box (Step 17). Cancel takes you to the Exit Setup dialog box (Step 18). 46 Chapter 3 Install Windows printing-system components ENWW Figure 3-15 Driver Installation -- Confirm Change Settings screen STEP 15 Help launches the Verify Settings troubleshooting tips in your Web browser. Back returns you to either the Confirm Network Settings dialog box (Step 14). Next takes you to the Change TCP/IP Settings dialog box (Step 16) if you select Yes, or to the Setup Settings dialog box (Step 17) if you select No. Cancel takes you to the Exit Setup dialog box (Step 18). ENWW Windows installation instructions 47 Figure 3-16 Driver Installation -- Change TCP/IP Settings screen STEP 16 Help launches the Change TCP/IP Settings troubleshooting tips in your Web browser. Suggest Settings allows the installation utility to automatically enter the TCP/IP parameters.

Back returns you to the Confirm Change Settings dialog box (Step 15). Next takes you to the Confirm Change Settings dialog box (Step 15). Cancel takes you to the Exit Setup dialog box (Step 18). 48 Chapter 3 Install Windows printing-system components ENWW Figure 3-17 Driver Installation -- Setup Settings screen STEP 17 Back returns you to the Printer Connections dialog box (Step 7). Next takes you to the HP Extended Capabilities dialog box (Step 19) once the software has been installed.

Cancel takes you to the Exit Setup dialog box (Step 18). Figure 3-18 Driver Installation -- Exit Setup screen STEP 18 Yes cancels the software installation. No returns you to the last open screen of the software install utility. ENWW Windows installation instructions 49 Figure 3-19 Driver Installation -- HP Extended Capabilities screen STEP 19 More Information provides additional details about the HP Extended Capabilities program. Back returns you to the Printer Connections dialog box (Step 7).

Next takes you to the Setup Complete dialog box (Step 20). Cancel takes you to the Exit Setup dialog box (Step 18). 50 Chapter 3 Install Windows printing-system components ENWW Figure 3-20 Driver Installation -- Setup Complete screen STEP 20 You are given the options to register your product and print a test page. Select the desired options and click Finish to be taken to the Setup Complete dialog box (Step 21) Figure 3-21 Driver Installation -- Setup Complete screen 2 STEP 21 ENWW Windows installation instructions 51 Review the information in the dialog box and click OK to be taken to the Reboot dialog box (Step 22). Figure 3-22 Driver Installation -- Reboot screen STEP 22 Yes allows the printer to shut down and restart in order to complete the software installation. No exits the software installation wizard without restarting the computer. NOTE: It is necessary to reboot the computer when prompted in order for the software to install properly. Installing the software when the printer is already connected to a computer If the product is already connected to a computer when you begin installing the software, Windows automatically detects the product and uses Plug-n-Play to install the printer driver. During this process, Plug-n-Play calls the Add Printer Wizard to automatically install the printer driver and the USB port. When Plug-n-Play completes, you are given the option to install the additional support files.

@@@ Select Network printer if the product is connected to a network. Back returns you to the Welcome screen (Step 1). Next takes you to the Select the Printer Port screen (Step 3). @@ Select Create a new port to add a new port. @@ to install the software from the CD-ROM. @@@ Click Next to continue. @@ Click Next to continue. @@@ Select No if you do not want to print a test page. @@@@ 1. 2.

Close all of the programs that are open on the computer. @ NOTE: If your CD does not start automatically, click Start, click Run, and then browse to and double-click the Setup.exe file in the root directory of the CD. 3. Click Next and follow the onscreen prompts until the installation is completed.

For more information, see Installing the software before the printer is connected to the computer on page 35 Setting up Windows sharing (peer-to-peer networking) NOTE: This section describes procedures for sharing a product using Microsoft Windows Sharing (peer-to-peer networking). Peer-to-peer networking is a feature of Microsoft operating systems, not of HP print drivers. If these procedures are not successful, or for more information about peer-to-peer networking procedures, contact Microsoft at the following Web site: <http://www.microsoft.com>.

This section contains instructions for using Windows sharing to make the product available to network users when the product is directly connected to a host computer. NOTE: Using Windows sharing, the person using the computer directly connected to the product can allow other users on the network to print to the product. When the product is shared, install the printer drivers on all of the computers that you want to print to the product. 62 Chapter 3 Install Windows printing-system components ENWW When you have set up the host computer to share your product, you must also configure the client computers. Perform the following steps at the computers of all other network users who want to print to the product. Setting up the host computer running Windows 2000 At the computer that is directly connected to the product, perform the following steps: 1. 2. 3. Click Start, click Settings, and then click Printers. In the printer list, right-click the icon for your HP LaserJet P1000 or P1500 Series printer, and then click Sharing.

On the Sharing tab, click the Share As option button, and then type a name for the product in the Share Name field. Click OK. Setting up the host computer running Windows XP At the computer that is directly connected to the product, perform the following steps: 1. Click Start, and then click Printers and Faxes (Windows XP Professional). -or Printers and Other Hardware Devices (Windows XP Home). 2. 3. 4. In the printer list, right-click the icon for your HP LaserJet P1000 or P1500 Series printer, and then click Sharing.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)

<http://yourpdfguides.com/dref/3235268>

On the Sharing tab, click the Share this printer option button, and then type a name for the product in the Share Name field. Click OK. Click the Ports tab. Click to clear the Enable bidirectional support check box, and then click OK. Setting up client computers running Windows 2000 1. 2.

3. 4. 5. Click Start, click Settings, and then click Printers. Double-click the Add Printer icon to open the Add Printer wizard. Click Next to start the wizard. Click the Network Printer option button, and then click Next. Type in the path and share name of the HP LaserJet P1000 or P1500 Series printer to which you want to connect. - OR Click Browse and navigate to find the HP LaserJet P1000 or P1500 Series printer to which you want to connect. Click Next. ENWW Installation options 63 6. 7. Click the Yes or No option button when asked if you want to use this product as your default printer for Windows-based programs, and then click Next. Click Finish to complete the installation and close the Add Printer wizard. NOTE: You might need the product software CD to complete the printer driver installations.

Setting up client computers running Windows XP 1. Click Start, and then click Printers and Faxes (Windows XP Professional). -orPrinters and Other Hardware Devices (Windows XP Home). 2. 3. 4. 5. On the left-hand column, under Printer Tasks, click Add a printer to open the Add Printer wizard. Click Next to start the wizard. Click the A network printer or a printer attached to another computer option button, and then click Next. Type in the path and share name of the HP LaserJet P1000 or P1500 Series printer to which you want to connect. - OR Click Browse and navigate to find the HP LaserJet P1000 or P1500 Series printer to which you want to connect. Click Next. 6. 7.

Click the Yes or No option button when asked if you want to use this product as your default printer for Windows-based programs, and then click Next. Click Finish to complete the installation and close the Add Printer wizard. Installation instructions for networked computers This section provides information about the following topics: Installing the software on networked computers (HP LaserJet P1505n only) Installing the print driver only Installing the software on networked computers (HP LaserJet P1505n only) Each computer that has the HP LaserJet P1505n printing-system software installed can use all of the product features that are available over a network connection through the internal network port that comes as standard equipment on the HP LaserJet P1505n models. To install the HP LaserJet P1505n printing-system software on networked Windows operating systems, follow these steps: 64 Chapter 3 Install Windows printing-system components ENWW NOTE: XP. 1.

2. You must have administrator privileges to install the software on Windows 2000 or Windows Close all of the programs that are open on the computer. @@NOTE: If the CD does not start automatically, click Start, click Run, and then browse to and double-click the Setup.exe file in the root directory of the CD. 3. 4. 5. 6. Click Next and follow the onscreen prompts. When the Installer software prompts you to select how the product will be connected, select Connected via the network, and then click Next.

Follow the instructions on the screen. When the installation is nearly complete, a setup screen appears that asks whether or not you want to print a test page. Click Yes. If you are prompted to restart the computer, click Yes. Installing the printer driver only NOTE: If the product is directly connected to another user's computer, the product must be shared from that computer by using Windows sharing. Use the following instructions to install the printer driver only. Printer-driver installation for Windows 2000 or Windows XP 1. From the Start menu, click Settings, and then click Printers (Windows 2000). -orPrinters and Faxes (Windows XP Professional). -orPrinters and Other Hardware Devices (Windows XP Home).

2. 3. 4. Double-click Add Printer, and then click Next. When asked if the product is a local or network printer, click Network Printer, and then click Next. You might need to first select the printer from the list of printers or type an IP address. If the printer driver is not available, the Add Printer Wizard dialog box appears. Click Have Disk from the wizard screen. Insert the CD into the CD-ROM drive and navigate to your CD-ROM drive. Double-click the .INF file. Complete the installation. When prompted, print a test page to ensure that the printer driver is installed properly. 5. 6. 7. ENWW Installation options 65 Plug-n-Play If the product is already connected to a computer when you begin installing the software, Windows automatically detects the product and uses Plug-n-Play to install the product. During this process, Plug-n-Play calls the Add Printer Wizard to automatically install the printer driver and the USB port. At the end of the Add Printer Wizard, you are given the option to install the additional support files. Add Printer Wizard If the product is already connected to a computer when you begin installing the software, Windows automatically detects the product and uses Plug-n-Play to install the printer driver.

@@At the end of the Add Printer Wizard, you are given the option to install the additional support files. 66 Chapter 3 Install Windows printing-system components ENWW Uninstall This section provides information about the following topics: Uninstall instructions for Windows Uninstall instructions for Windows Choose one of the following two methods to uninstall the HP LaserJet P1000 or P1500 Series printingsystem software: Uninstalling using the HP program group (recommended) Uninstalling using the Windows Add/Remove Program feature Uninstalling using the HP program group (recommended) NOTE: To uninstall the software from Windows 2000 or Windows XP, you must log on with administrator privileges. 1. 2. Close all of the programs that are open on the computer. Click Start, click All Programs, select HP, select either HP LaserJet P1000 Series or HP LaserJet P1500 Series, and then click either Uninstall HP LaserJet P1000 Series or Uninstall HP LaserJet P1500 Series. The Welcome to the HP LaserJet P1000 / P1500 series Uninstall Wizard dialog box appears. Click Next to continue. Select the model of printer you would like to uninstall and click Next. The HP LaserJet P1000 / P1500 series Driver Uninstall Information dialog box appears to confirm which product is being uninstalled.

Click Next to continue. The progress bar reflects the status of the uninstall process. Click Restart to reboot your computer and finish the uninstall process. 3. 4.

5. 6. 7. Uninstalling using Windows Add/Remove programs feature Follow these steps to uninstall theHP LaserJet P1000 or P1500 Series printing-system software by using the Windows Add/Remove programs feature. NOTE: Using this uninstall method, you do not need theHP LaserJet P1000 or P1500 Series printingsystem software CD.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>

NOTE: To uninstall the software from Windows 2000 or XP, you must log on with administrator privileges. 1. Close all of the programs that are open on the computer. ENWW Uninstall 67 2. For Windows 2000, click Start, click Settings, click Control Panel, and then double-click Add/ Remove programs For Windows XP, click Start, click Control Panel, and then double-click Add/Remove programs. Figure 3-35 Windows Control Panel screen 3. Click Change or Remove Programs, click HP LaserJet P1000 series or HP LaserJet P1500 series, and then click Change/Remove. Figure 3-36 Windows Change or Remove Programs screen 68 Chapter 3 Install Windows printing-system components ENWW 4. The Welcome to the LaserJet P1000 / P1500 series Uninstall Wizard dialog box appears. Figure 3-37 Welcome to the LaserJet P1000 / P1500 series Uninstall Wizard dialog box Click Next to begin the uninstall process.

ENWW Uninstall 69 5. The Uninstalling the HP LaserJet P1000 / P1500 series dialog box appears. Figure 3-38 HP LaserJet P1000 / P1500 series Driver Uninstall Information dialog box Select the printer model you want to uninstall and click Next. 70 Chapter 3 Install Windows printing-system components ENWW 6. The second Uninstalling the HP LaserJet P1000 / P1500 series dialog box appears. Figure 3-39 HP LaserJet P1000 / P1500 series Driver Uninstall Information dialog box, screen 2 Review the information in the dialog box and then click Next. The progress bar reflects the status of the uninstall process. ENWW Uninstall 71 7. The Uninstall Complete dialog box appears. Figure 3-40 Uninstall Complete dialog box Click Restart to reboot your computer and finish the uninstall process.

72 Chapter 3 Install Windows printing-system components ENWW 4 Host-based driver for Windows Topics: Introduction to host-based printing Help system Access to the driver Driver tabs ENWW 73 Introduction to host-based printing The HP LaserJet P1000 and P1500 Series printers are host-based devices. Host-based printing differs from PCL printing by rendering the print job on the host computer rather than on the device formatter. As a host-based printing system, the HP LaserJet P1000 and P1500 Series print drivers use the Windows operating system to convert the graphics device interface (GDI) or device driver interface (DDI) calls from software programs into JBIG (standard-compression) compressed pages. These pages are sent in "chunks" through the driver to the device formatter. The HP LaserJet P1000 and P1500 Series print drivers also receive status messages from the formatter firmware. These messages are passed to the Status Application, which displays them. The HP LaserJet P1000 Series formatter has no read-only memory (ROM) and up to 8 MB of random access memory (RAM). The amount of RAM varies based on the model of printer. Both the firmware and the compressed page must fit into the amount of RAM installed in the printer. Depending on the model of printer, the HP LaserJet P1500 Series formatter has up to 2 MB of readonly memory (ROM) and up to 32 MB of RAM.

Both the firmware and the compressed page must fit into the amount of RAM installed in the printer. 74 Chapter 4 Host-based driver for Windows ENWW Help system The HP LaserJet P1000 and P1500 Series host-based drivers include a full-featured Help system to provide assistance with printing and configuration options. The following Help options are available: What's this? Help Context-sensitive Help Paper Type Warning What's this? Help "What's this?" Help is available in all of the supported operating systems. Access "What's this?" Help messages in the following ways: Right-click a control and click What's this?, and a pop-up Help window appears. Click the ? button at the upper-right corner of the frame, to change the cursor to an arrow with a question mark. Use this special cursor to select a control, and the pop-up Help window for that feature appears. Press the F1 key, and the Help window for the currently selected control appears. Context-sensitive Help Press the Help button on a driver tab or in a dialog box, and context-sensitive Help appears. Paper Type Warning Paper Type Warnings are unsolicited messages that appear in response to specific actions. These messages appear in response to selections that could damage the device.

For example, if you select Bond in the Type is: drop-down menu, a message appears warning you to change the setting before printing on other types of media. Figure 4-1 Paper Type Warning message ENWW Help system 75 Access to the driver To gain access to driver settings from within most software programs, click File, click Print, and then click Properties. The appearance and names of the driver tabs that appear can vary, depending on the operating system. These settings apply only while the software program is open. You can also control the driver directly from the Printers folder. These settings change the default settings for all software programs. In Windows 2000, click Start, select Settings, select Printers, right-click the device name, and then click Printing Preferences to gain access to the same set of driver tabs that the software program controls. In Windows XP, click Start, select Settings, select Printers and Faxes (Windows XP Professional) or Printers and Other Hardware Devices (Windows XP Home), right-click the device name, and then click Printing Preferences to gain access to the same set of driver tabs that the software program controls. Click Properties after right-clicking the device name to gain access to the Properties tab set, which controls the driver behavior and driver connections. Properties tab set The Properties tab set contains information about and options for configuring the device.

NOTE: Windows also has tabs in the Properties tab set. For information about those tabs, see the documentation that came with the computer. Printing Preferences tab set The HP LaserJet P1000 and P1500 Series printer host-based Printing Preferences tabs contain options for formatting documents for the HP LaserJet P1000 and P1500 Series printers. Gain access to the Printing Preferences tabs either through the software program or through the Windows Printers folder. The following tabs are included in Printing Preferences tab set: Advanced Paper/Quality Effects Finishing Services Print Task Quick Sets Use the Print Task Quick Sets control to store the current combination of driver settings that are found on all other Printing Preferences driver tabs. Print Task Quick Sets are either preset or user-defined printing specifications, such as paper size and pages per sheet. The Print Task Quick Sets appear in the upper-left corner of the Paper/Quality, Effects, and Finishing tabs. 76 Chapter 4 Host-based driver for Windows ENWW Document preview image The document preview image is a line-drawn image of a page that represents graphics and text.



[You're reading an excerpt. Click here to read official COMPAQ P1000 user guide](http://yourpdfguides.com/dref/3235268)
<http://yourpdfguides.com/dref/3235268>