



Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW. You'll find the answers to all your questions on the ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

User manual ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW
User guide ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW
Operating instructions ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW
Instructions for use ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW
Instruction manual ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW

E8300
First Edition
July 2013



Notebook PC

ASUS Transformer Book Trio E-Manual



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

Manual abstract:

This limit also applies to ASUS' suppliers and its reseller. It is the maximum for which ASUS, its suppliers, and your reseller are collectively responsible. 7 Conventions used in this manual. 27 Transforming your devices into an ASUS Transformer Book Trio. 29 Undocking the tablet from the PC station. 53 Chapter 3: Working with Windows® 8 Starting for the first time. 83 Chapter 4: Working with Android® Starting up for the first time. 153 □ ASUS Transformer Book Trio E-Manual About this manual This manual provides information about the hardware and software features of your ASUS Transformer Book Trio, organized through the following chapters: Chapter 1: Hardware Parts This chapter details the hardware components of your ASUS Transformer Book Trio. Chapter 2: Getting Started This chapter shows you how to set up and use the different parts of your ASUS Transformer Book Trio. Chapter 3: Working with Windows® 8 This chapter provides an overview of using Windows® 8 in your ASUS Transformer Book Trio. Chapter 4: Working with Android® This chapter provides an overview of using Android® in your ASUS Transformer Book Trio and tablet. Chapter 5: Power-on Self-test (POST) This chapter shows you how to use POST to change the settings of your ASUS Transformer Book Trio. Tips and FAQs This section presents some recommended tips, hardware FAQs, and software FAQs you can refer to for maintaining and fixing common issues with your ASUS Transformer Book Trio. Appendices This section includes notices and safety statements for your ASUS Transformer Book Trio. ASUS Transformer Book Trio E-Manual □ Conventions used in this manual To highlight key information in this manual, some text are presented as follows: IMPORTANT! This message contains vital information that must be followed to complete a task.

NOTE: This message contains additional information and tips that can help complete tasks. WARNING! This message contains important information that must be followed to keep you safe while performing tasks and prevent damage to your ASUS Transformer Book Trio's data and components. Icons The icons below indicate the devices you can use for completing a series of tasks or procedures on your ASUS Transformer Book Trio. = This indicates sections that you can refer to in this manual. ASUS Transformer Book Trio E-Manual Safety precautions Using your ASUS Transformer Book Trio This ASUS Transformer Book Trio should only be used in environments with ambient temperatures between 5°C (41°F) and 35°C (95°F).

Refer to the rating label on the bottom of your ASUS Transformer Book Trio and ensure that your power adapter complies with this rating. Do not leave your ASUS Transformer Book Trio on your lap or near any part of your body to prevent discomfort or injury from heat exposure. Do not use damaged power cords, accessories, and other peripherals with your ASUS Transformer Book Trio. While powered on, ensure that you do not carry or cover your ASUS Transformer Book Trio with any materials that can reduce air circulation. Do not place your ASUS Transformer Book Trio on uneven or unstable work surfaces. You can send your ASUS Transformer Book Trio through x-ray machines (used on items placed on conveyor belts), but do not expose them to magnetic detectors and wands. Contact your airline provider to learn about related inflight services that can be used and restrictions that must be followed when using your ASUS Transformer Book Trio in-flight. ASUS Transformer Book Trio E-Manual □ Caring for your ASUS Transformer Book Trio Disconnect the AC power and remove the battery pack (if applicable) before cleaning your ASUS Transformer Book Trio. Use a clean cellulose sponge or chamois cloth dampened with a solution of nonabrasive detergent and a few drops of warm water. Remove any extra moisture from your ASUS Transformer Book Trio using a dry cloth.

Do not use strong solvents such as thinners, benzene, or other chemicals on or near your ASUS Transformer Book Trio. Do not place objects on top of your ASUS Transformer Book Trio. Do not expose your ASUS Transformer Book Trio to strong magnetic or electrical fields. Do not use or expose your ASUS Transformer Book Trio near liquids, rain, or moisture. Do not expose your ASUS Transformer Book Trio to dusty environments. Do not use your ASUS Transformer Book Trio near gas leaks. 10 ASUS Transformer Book Trio E-Manual Proper disposal Do not throw your ASUS Transformer Book Trio in municipal waste. This product has been designed to enable proper reuse of parts and recycling. The symbol of the crossed out wheeled bin indicates that the product (electrical, electronic equipment and mercury-containing button cell battery) should not be placed in municipal waste. check local regulations for disposal of electronic products.

Do not throw the battery in municipal waste. The symbol of the crossed out wheeled bin indicates that the battery should not be placed in municipal waste. ASUS Transformer Book Trio E-Manual 11 12 ASUS Transformer Book Trio E-Manual Chapter 1: Hardware parts ASUS Transformer Book Trio E-Manual 13 Getting to know your ASUS Transformer Book Trio Your ASUS Transformer Book Trio is made up of two major devices: the tablet and the PC station. When the tablet is docked on the PC station, both devices can be used as the ASUS Transformer Book Trio. If the tablet is undocked from the PC station, each can function as individual devices with their own set of features.

The tablet contains the Android® operating system while the PC station contains Windows® 8. PC station tablet ASUS Transformer Book Trio NOTE: For more details on connecting or disconnecting the tablet and the PC station, refer to the Transforming your devices into an ASUS Transformer Book Trio and the Undocking the tablet from the PC station sections in this manual. 14 ASUS Transformer Book Trio E-Manual Tablet The tablet of your ASUS Transformer Book Trio allows you to perform touch screen gestures while working on Windows® 8 or Android®. When detached from the PC station, the tablet can be used to work on Android® only. Top View Camera The built-in camera allows you to take pictures or record videos using your ASUS Transformer Book Trio. Camera indicator The camera indicator lights up when the built-in camera is in use. ASUS Transformer Book Trio E-Manual 15 Ambient light sensor The ambient light sensor detects the amount of ambient light in your environment. It allows the system to automatically adjust the brightness of the display depending on the ambient light condition. Touch screen panel This high-definition touch screen panel provides excellent viewing features for photos, videos, and other multimedia files on your ASUS Transformer Book Trio or tablet. It also allows you to operate your tablet using touch gestures. NOTE: For more details, refer to the Gestures for the touch screen panel and touchpad section in this manual. 16 ASUS Transformer Book Trio E-Manual Ports and slot Headphone output jack port (for Android® only) This port allows you to connect your ASUS Transformer Book Trio to headphones while working on Android®.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

You can also use this port to connect your ASUS Transformer Book Trio to an external microphone. PC station slots These slots are magnetic and align conveniently with the magnetic PC station tabs to securely attach the tablet. **WARNING!** □ • The PC station tabs are magnetized, please keep them out of children's reach.

Magnetic fields generated by mobile devices may damage data on magnetic storage media, such as credit cards, computer discs or tapes. Do not place your device next to such media. Never expose your device to strong magnetic fields as this may cause temporary malfunction. Magnets can affect functioning pacemakers and implanted defibrillators. Refer to your pacemaker or defibrillator's suggested distance from magnets. • • ASUS Transformer Book Trio E-Manual 17 Micro USB 2.0 port (for Android® only) Connect the bundled micro USB to USB adapter into this micro USB (Universal Serial Bus) 2.0 port to charge the battery or supply power to your tablet. You can use this as a charging port while using the tablet as a separate device. When the tablet is used separately, you may also use this port to facilitate data transfers from an external device.

MicroSD card slot This built-in memory card reader slot supports microSD and microSDHC card formats. **NOTE:** When working on Windows® 8, you need to ensure that the Android® system is also running. 18 ASUS Transformer Book Trio E-Manual Rear view **IMPORTANT!** Battery time varies by usage and by the specifications for this ASUS Transformer Book Trio. The battery pack cannot be disassembled. Microphone The built-in microphone can be used for video conferencing, voice narrations, or simple audio recording.

Camera (for Android® only) The built-in camera allows you to take pictures or record videos while working on Android®. Audio speakers The built-in audio speakers allow you to hear audios straight from your tablet. audio features are software controlled. ASUS Transformer Book Trio E-Manual 19 Volume button Press this button to increase or decrease the volume. Power button The power button turns on your tablet, boots up Android®, and also resets your tablet when needed.

Refer to the following scenarios when using your tablet's power button: • • Press the power button to turn on your tablet and boot up Android®. While working on your tablet, you can press the power button to put your tablet to sleep or wake it up from sleep mode. In the event that your tablet becomes unresponsive, press and hold the power button for about seven (7) seconds until your tablet shuts down. □ 20 ASUS Transformer Book Trio E-Manual PC station The PC station serves as an input device for your ASUS Transformer Book Trio via its keyboard and touchpad. It also provides access to Windows® 8 when the tablet is docked on it or while using an external display. Top View **NOTE:** The keyboard's layout may vary per model, region, or country.

Microphone The built-in microphone can be used for video conferencing, voice narrations, or simple audio recording. PC station hinge This hinge allows you to connect the tablet to the PC station. It also holds the tablet in place as you adjust it to different viewing angles. ASUS Transformer Book Trio E-Manual 21 Tablet release button Press this button all the way in until the hinge unlocks the tablet from the PC station.

Power indicator The power indicator lights up when the PC station is turned on and running Windows® 8. It also blinks slowly when the PC station is in sleep mode. Power button The power button turns on your PC station, boots up the Windows® 8 system, and also resets your PC station when needed. Refer to the following scenarios when using your PC station's power button: • • Press the power button to turn on your PC station and boot up Windows® 8. While working on your PC station, you can press the power button to put your PC station to sleep or wake it up from sleep mode. In the event that your PC station becomes unresponsive, press and hold the power button for about four (4) seconds until your PC station shuts down. □ 22 ASUS Transformer Book Trio E-Manual Operating system (OS) switch key The OS switch key is a special button on the PC station that allows you to toggle between Windows® 8 and Android®. □ The PC station is plugged to a power source, charging its battery, and the battery power is less than 95%. The tablet is connected to the PC station, charging its battery, and the tablet's battery power is less than 30%. **NOTE:** This charging process is automatically enabled even while your system is on sleep mode or turned off.

Solid Orange • Blinking Orange The PC station is running on battery mode and the battery power is less than 10%. Lights off The PC station is running on battery mode and the battery power is between 10% to 100%. Drive activity indicator This indicator lights up when your PC station is accessing the internal storage drives. 28 ASUS Transformer Book Trio E-Manual Transforming your devices into an ASUS Transformer Book Trio To use both devices as an ASUS Transformer Book Trio, align the tablet with the PC station tabs as illustrated below. **NOTE:** The PC station slots and the PC station tabs contain magnetized parts.

The pull between these magnets help align the tablet so that it is properly inserted into the PC station hinge. ASUS Transformer Book Trio E-Manual 29 Undocking the tablet from the PC station To use your tablet or PC station as separate devices, undock the tablet from the PC station as shown in the illustration below. Press the tablet release button to detach the tablet from the PC station. Pull out the tablet from the PC station hinge. 30 ASUS Transformer Book Trio E-Manual Chapter 2: Getting started ASUS Transformer Book Trio E-Manual 31 Setting up your device Using your ASUS Transformer Book Trio

Refer to the following steps when setting up your ASUS Transformer Book Trio.

1. Dock the tablet into the PC station. Plug the AC power adapter into a 100V~240V power source. Connect the DC power connector into your ASUS Transformer Book Trio's power (DC) input. Charge the ASUS Transformer Book Trio for 3 hours before using it in battery mode for the first time. **NOTE:** The power adapter may vary in appearance, depending on models and your region. ASUS Transformer Book Trio E-Manual 33 **IMPORTANT!** □ Locate the input/output rating label on your ASUS Transformer Book Trio and ensure that it matches the input/output rating information on your power adapter. Some ASUS Transformer Book Trio models may have multiple rating output currents based on the available SKU. Ensure that your ASUS Transformer Book Trio is connected to the power adapter before turning it on for the first time. We strongly recommend that you use a grounded wall socket while using your ASUS Transformer Book Trio on power adapter mode.

The socket outlet must be easily accessible and near your ASUS Transformer Book Trio.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

To disconnect your ASUS Transformer Book Trio from its main power supply, unplug your ASUS Transformer Book Trio from the power socket. □ •••••

•• Read the following precautions for your ASUS Transformer Book Trio's battery. Only ASUS-authorized technicians should remove the battery inside the device. The battery used in this device may present a risk of fire or chemical burn if removed or disassembled. Follow the warning labels for your personal safety. Never attempt to short-circuit your ASUS Transformer Book Trio's battery. Never attempt to disassemble and reassemble the battery. discontinue usage if leakage is found. The battery and its components must be recycled or disposed of properly.

Keep the battery and other small components away from children. aSUS Transformer Book Trio E-Manual 35 3. Press the power button on your PC station. iMPORTANT! When using your ASUS Transformer Book Trio for the first time, ensure that the device is running on power adapter mode when you press the power button to unlock the BIOS settings. 36 ASUS Transformer Book Trio E-Manual Using the operating system (OS) switch key When the tablet and the PC station are used individually, they run using their respective operating systems.

But when both devices are connected and used as an ASUS Transformer Book Trio, you can use Android® or Windows® 8 interchangeably using the operating system (OS) switch key. OS switch key To guide you through the process of switching between Android® or Windows® 8, pop-up menus appear whenever you press the switch key under the following scenarios: 1. Both Android® and Windows® 8 are running ASUS Transformer Book Trio E-Manual 37

Using the tablet Refer to the following steps when using the tablet as a separate device. 1. If you need to charge your tablet, connect it to a power source through the following: A.

Connect the micro USB cable to the power adapter. Plug the micro USB connector into your tablet. Plug the power adapter into a grounded power outlet. 2. Press the power button on your tablet. 38 ASUS Transformer Book Trio E-Manual Using the PC station Refer to the following steps when using your PC station as a separate device. Connect your PC station to a power outlet: A. b. Plug the AC power adapter into a 100V~240V power source. Connect the DC power connector into your PC station's power (DC) input port.

3. Press the power button on your PC station. ASUS Transformer Book Trio E-Manual 39 Gestures for the touch screen panel and touchpad Gestures allow you to launch programs and access the settings of your ASUS Transformer Book Trio. Refer to the following illustrations when using hand gestures on your touch screen panel and touchpad. NOTE: The following screenshots are for reference only. The screen panel's appearance may vary depending on model. Touch screen gestures for Windows® 8 Left edge swipe Right edge swipe Swipe from the left edge of the screen to shuffle your running apps. Swipe from the right edge of the screen to launch the Charms bar. 40 ASUS Transformer Book Trio E-Manual Zoom out Zoom in Bring together your two fingers on the touch panel. Top edge swipe Spread apart your two fingers on the touch panel.

Finger slide • In the Start screen, swipe from the top edge of the screen to view the All Apps bar. In a running app, swipe from the top edge of the screen to view its menu. Slide your finger to scroll up and down and slide your finger to pan the screen left or right. □ ASUS Transformer Book Trio E-Manual 41 Touch screen gestures for Android® NOTE: The following screenshots are for reference only. The screen panel's appearance may vary depending on model and the OS may vary depending on the Android® version.

Drag/Tap and hold/Long press ••• To move an app, tap and hold the app and drag it to a new location. To delete an app from the main screen, tap and hold the app and drag it up to the top side of the screen. to capture a screen image , tap and hold . NOTE: To enable this setting, go to Settings > ASUS Customized Setting then tick Capture screenshots by holding the recent apps key. 42 ASUS Transformer Book Trio E-Manual Zoom in Zoom out Spread apart your two fingers on the touch panel to zoom in an image in Gallery, Maps or Places.

Swipe Bring together your two fingers on the touch panel to zoom out an image in Gallery, Maps or Places. Tap/Touch Swipe your finger to the right or to the left on the touch panel display to switch between screens or to flip through the pages of an e-book or a gallery of images. ASUS Transformer Book Trio E-Manual 43 Using the touchpad Moving the pointer You can click or click anywhere on the touchpad to activate its pointer, then slide your finger on the touchpad to move the pointer onscreen. Slide horizontally Slide vertically Slide diagonally 44 ASUS Transformer Book Trio E-Manual One-finger touchpad gestures for Windows® 8 Tap/Double tap •• In the Start screen, tap an app to launch it. in Desktop mode , double-tap an application to launch it. Drag and drop Double-tap an item, then slide the same finger without lifting it off the touchpad. To drop the item to its new location, lift your finger from the touchpad. □ In the Start screen, click an app to select it and launch the settings bar. You can also press this button to launch the All Apps bar. In Desktop mode, use this button to open the rightclick menu.

□ NOTE: The areas inside the dotted line represent the locations of the left mouse button and the right mouse button on the touchpad. 46 ASUS Transformer Book Trio E-Manual Top edge swipe •• In the Start screen, swipe from the top edge to launch the All Apps bar. In a running app, swipe from the top edge to view its menu. Right edge swipe Left edge swipe Swipe from the left edge to shuffle Swipe from the right edge to launch your running apps. the Charms bar. ASUS Transformer Book Trio E-Manual 47 Two-finger touchpad gestures for Windows® 8 Tap Rotate Tap two fingers on the touchpad to simulate the right-click function. To rotate an image, place two fingers on the touchpad then turn one finger clockwise or counterclockwise while the other stays still. two-finger scroll (left/right) Two-finger scroll (up/down) Slide two fingers to scroll up or down. Slide two fingers to scroll left or right. 48 ASUS Transformer Book Trio E-Manual Zoom out Zoom in Bring together your two fingers on Spread apart your two fingers on the touchpad.

the touchpad. Drag and drop Select an item then press and hold the left button. Using your other finger, slide down the touchpad to drag and drop the item to a new location. ASUS Transformer Book Trio E-Manual 49 Three-finger touchpad gestures for Windows® 8 Swipe up Swipe down Swipe three fingers upward to show all running applications. Swipe three fingers downward to show the Desktop mode.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)

50 ASUS Transformer Book Trio E-Manual Two-finger touchpad gestures for Android® Drag and drop Select an item then press and hold the left button. Using your other finger, slide down the touchpad to drag and drop the item to a new location. two-finger scroll (up/down) Two-finger scroll (left/right) Slide two fingers to scroll up or down. Slide two fingers to scroll left or right. ASUS Transformer Book Trio E-Manual 51 Using the keyboard Function keys The function keys on your ASUS Transformer Book Trio's keyboard can trigger the following commands: Puts the ASUS Transformer Book Trio into Sleep mode Turns Airplane mode on or off NOTE: When enabled, the Airplane mode disables all wireless connectivity.

Decreases display brightness Increases display brightness Turns the display panel off Activates the second screen NOTE: Ensure that the second display is connected to your ASUS Transformer Book Trio. Enables or disables the touchpad Turns the speaker on or off 52 ASUS Transformer Book Trio E-Manual Turns the speaker volume down Turns the speaker volume up Function keys for apps Your ASUS Transformer Book Trio also comes with a special set of function keys that can be used to launch some featured apps. Toggles the ASUS Splendid Video Enhancement Technology app to switch between these display color enhancement modes: Gamma Correction, Vivid Mode, Theater Mode, Soft Mode, My Profile, and Normal. launches the default camera application. Launches the ASUS Power4Gear Hybrid app Windows®8 keys There are two special Windows® keys on your ASUS Transformer Book Trio's keyboard used as below: Press this key to go back to the Start screen. If you are already in the Start screen, press this key to go back to the last app you opened. Press this key to simulate the right-click functions. ASUS Transformer Book Trio E-Manual 53 54 ASUS Transformer Book Trio E-Manual Chapter 3: Working with Windows® 8 ASUS Transformer Book Trio E-Manual 55 Starting for the first time When you start your computer for the first time, a series of screens appear to guide you in configuring the basic settings of the Windows® 8 operating system. To start your Windows® 8 for the first time: 1. Press the power button on your PC station.

Wait for a few minutes until the setup screen appears. From the setup screen, pick a language to use on your ASUS Transformer Book Trio. Carefully read the License Terms. Tick I accept the terms for using Windows then click Accept. Follow the onscreen instructions to configure the following basic items: •••••5. Keep your PC secure Personalize Wireless Settings Sign in to your PC After configuring the basic items, the Windows®8 tutorial appears. Watch this to learn more about Windows®8 functionalities. Windows® 8 lock screen The Windows®8 lock screen may appear when your ASUS Transformer Book Trio enters the Windows®8 operating system. To proceed, tap on the lock screen or press any key on your PC station's keyboard. 56 ASUS Transformer Book Trio E-Manual Windows® UI Windows® 8 comes with a tile-based user interface (UI) which allows you to organize and easily access Windows® apps from the Start screen.

It also includes the following features that you can use while working on your ASUS Transformer Book Trio. Start screen The Start screen appears after successfully signing in to your user account. It helps organize all the applications you need in just one place. Zoom in/out button Windows® Apps These are apps pinned on the Start screen and displayed on tiled-format for easy access. NOTE: Some apps require signing in to your Microsoft account before they are fully launched.

ASUS Transformer Book Trio E-Manual 57 Hotspots Onscreen hotspots allow you to launch programs and access the settings of your ASUS Transformer Book Trio. The functions in these hotspots can be activated using the touchpad. Hotspots on a running app Hotspots on the Start screen 58 ASUS Transformer Book Trio E-Manual Hotspot upper left corner Action Hover your mouse pointer on the upper left corner then tap on the recent app's thumbnail to revert back to that running app. If you launched more than one app, slide down to show all running apps. Lower left corner From a running app screen: Hover your mouse pointer on the lower left corner then tap on the Start screen's thumbnail to go back to the Start screen.

NOTE: You can also press the Windows key on your keyboard to go back to the Start screen. From the Start screen: Hover your mouse pointer on the lower left corner then tap on the running app's thumbnail to go back to that app. ASUS Transformer Book Trio E-Manual 59 Hotspot top side Action Hover your mouse pointer on the top side until it changes to a hand icon. Drag then drop the app to a new location. NOTE: This hotspot function only works on a running app or when you want to use the Snap feature. For more details, refer to the Snap feature under Working with Windows® apps. Upper or lower right corner Hover your mouse pointer on the upper or lower right corner to launch the Charms bar. 60 ASUS Transformer Book Trio E-Manual Working with Windows® apps Use your ASUS Transformer Book Trio's touch screen panel, touchpad, or keyboard to launch, customize, and close apps. launching apps Tap an app to launch it. Position your mouse pointer over the app then left-click or tap once to launch it.

Press twice then use the arrow keys to browse to launch an app. through the apps. Press Customizing apps You can move, resize, unpin, or close apps from the Start screen using the following steps: Moving apps Tap and hold the app tile then drag it to a new location. Double-tap on the app then drag and drop the app to a new location. ASUS Transformer Book Trio E-Manual 61 Resizing apps 1. Swipe down the app tile to select and launch the settings bar. Right-click on the app to activate its settings bar then tap or . unpinning apps 1. Swipe down the app tile to select and launch the settings bar. Right-click on the app to activate the settings bar then tap .

62 ASUS Transformer Book Trio E-Manual Closing apps Tap and hold the top side of the running app then drag it down to the bottom of the screen to close it. 1. Move your mouse pointer on the top side of the launched app then wait for the pointer to change to a hand icon. Drag then drop the app to the bottom of the screen to close it. From the running app's screen, press ASUS Transformer Book Trio E-Manual 63 Accessing the Apps screen Aside from the apps already pinned on your Start screen, you can also open other applications through the Apps screen.

Horizontal scroll bar 64 ASUS Transformer Book Trio E-Manual Launching the Apps screen Launch the Apps screen using your ASUS Transformer Book Trio's touch screen panel, touchpad, or keyboard. 1. Swipe from the top or bottom edge of the screen to launch the All Apps bar. Swipe from the top edge to launch the All Apps bar.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

From the Start screen, press All Apps icon then press to select the .

ASUS Transformer Book Trio E-Manual 65 Pinning more apps on the Start screen You can pin more apps on the Start screen using your touch screen panel or touchpad. 1. In the Apps screen, swipe down the app to select and launch the settings bar. tap screen. To pin the selected app on the Start 2. Position the mouse pointer over the app you want to pin on the Start screen. Right-click on the app to activate its settings. tap on the icon. 66 ASUS Transformer Book Trio E-Manual Charms bar The charms bar is a toolbar that can be triggered on the right side of your screen. It consists of several charms that allow you to share applications and provide quick access for customizing the settings of your ASUS Transformer Book Trio.

Charms bar ASUS Transformer Book Trio E-Manual 67 Launching the charms bar NOTE: When called out, the charms bar initially appears as a set of white icons. The image above shows how the charms bar looks like once activated. Use your ASUS Transformer Book Trio's touch screen panel, touchpad, or keyboard to launch the charms bar. Swipe from the right edge of the screen to launch the charms bar. Move your mouse pointer on the upper or lower right corner of the screen. press . 68 ASUS Transformer Book Trio E-Manual Inside the charms bar Search This charm allows you to look for files, applications, or programs in your ASUS Transformer Book Trio. Share This charm allows you to share applications via social networking sites or email. Start This charm reverts the display back to the Start screen. From the Start screen, you can also use this to revert back to a recently opened app.

Devices This charm allows you to access and share files with the devices attached to your ASUS Transformer Book Trio such as an external display or printer. Settings This charm allows you to access the PC settings of your ASUS Transformer Book Trio. ASUS Transformer Book Trio E-Manual 69 Snap feature The Snap feature displays two apps side-by-side, allowing you to work or switch between apps. iMPORTANT! Ensure that your ASUS Transformer Book Trio's screen resolution is set to 1366 x 768 pixels or higher before using the Snap feature. Snap bar 70 ASUS Transformer Book Trio E-Manual Using Snap Use your ASUS Transformer Book Trio's touch screen panel, touchpad or keyboard to activate and use Snap.

Launch the app you wish to snap. Tap and hold the app's topmost part then drag it to the left or right side of the screen until the snap bar appears. Launch the app you wish to snap. Hover the mouse point on the top side of your screen. Once the pointer changes to a hand icon, drag then drop the app to the left or right side of the display panel.

Launch the app you wish to snap. ASUS Transformer Book Trio E-Manual 71 Other keyboard shortcuts Using the keyboard, you can also use the following shortcuts to help you launch applications and navigate Windows®. \ Switches between the Start screen and the last running app Launches the desktop

Launches the Computer window on Desktop mode Opens the File charm Opens the Share charm Opens the Settings charm Opens the Devices charm Activates the Lock screen Minimizes the currently active window 72 ASUS Transformer Book Trio E-Manual Opens the Second screen pane Opens the Apps search pane Opens the Run window Opens Ease of Access Center Opens the Settings charm Opens a menu box of Windows® tools Launches the magnifier icon and zooms in your screen Zooms out your screen Opens the Narrator Settings ASUS Transformer Book Trio E-Manual 73 Connecting to wireless networks Wi-Fi Access emails, surf the Internet, and share applications via social networking sites using your ASUS Transformer Book Trio's Wi-Fi connection. iMPORTANT! The Airplane mode disables this feature. Ensure that Airplane mode is turned off before enabling the Wi-Fi connection of your ASUS Transformer Book Trio. NOTE: 5GHz is supported on selected models. Enabling Wi-Fi Activate Wi-Fi in your ASUS Transformer Book Trio using the following steps on your touch screen panel or touchpad. NOTE: You may be prompted to enter a security key to activate the Wi-Fi connection. or 5. If you want to enable sharing between your ASUS Transformer Book Trio and other wireless-enabled systems, tap Yes, turn on sharing and connect to devices.

Tap*/click No, don't turn on sharing or connect to devices if you do not want to enable the sharing function. The Airplane mode disables this feature. Ensure that Airplane mode is turned off before enabling the Bluetooth connection of your ASUS Transformer Book Trio. Pairing with other Bluetooth-enabled devices You need to pair your ASUS Transformer Book Trio with other Bluetooth-enabled devices to enable data transfers. To do this, use your touch screen panel* or touchpad as follows: 1. Under PC Settings, select Devices then tap/click Add a Device to search for Bluetooth-enabled devices. Compare the passcode on your ASUS Transformer Book Trio with the passcode sent to your chosen device. If they are the same, tap/click Yes to successfully pair your ASUS Transformer Book Trio with the device. NOTE: For some bluetooth-enabled devices, you may be prompted to key in the passcode of your ASUS Transformer Book Trio. ASUS Transformer Book Trio E-Manual 77 Airplane mode The Airplane mode disables wireless communication, allowing you to use your ASUS Transformer Book Trio safely while in-flight.

Move the slider to the right to turn the Airplane mode on. Or Move the slider to the left to turn the Airplane mode off. . Press NOTE: Contact your airline provider to learn about related inflight services that can be used and restrictions that must be followed when using your ASUS Transformer Book Trio in-flight. 78 ASUS Transformer Book Trio E-Manual Connecting to wired networks You can also connect to wired networks, such as local area networks and broadband Internet connection, using your ASUS Transformer Book Trio's LAN port.

NOTE: Contact your Internet Service Provider (ISP) for details or your network administrator for assistance in setting up your Internet connection. To configure your settings, refer to the following procedures. iMPORTANT! Ensure that a network cable is connected between your ASUS Transformer Book Trio's LAN port and a local area network before performing the following actions. From the Windows® taskbar, right-click the network icon Center. In the Network and Sharing Center window, click Change adapter settings.

Right-click on your LAN then select Properties. Click Obtain an IP address automatically then tap OK. 6. NOTE: Proceed to the next steps if you are using PPPoE connection. 7. Return to the Network and Sharing Center window then tap Set up a new connection or network. Select Connect to the Internet then tap Next. click Broadband (PPPoE). Type your User name, Password, and Connection name then tap Connect. click Close to finish the configuration.

Tap on the taskbar then tap the connection 8.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

ASUS Transformer Book Trio E-Manual 99 Viewing apps under the Recents screen The Recents screen allows you to view a list of app shortcuts based from your recently launched apps. Using the Recents screen, you can easily go back to or switch between the apps you recently launched. to access the Recents screen: 1. Play Store Tap on the system bar. 2. Camera A list shows up to display all of your recently launched apps. Tap on the app you want to launch. Play Music Maps y Lite Email App Backup SuperNote Lite SuperNote MyNet e AudioWizard ASUS Studio People Phone 100 ASUS Transformer Book Trio E-Manual To view a recent app's menu: 1. To remove the app from the list, select Remove from list. to view its information , select App info. NOTE: You can also remove a recent app from the list by swiping it up or down. ASUS Transformer Book Trio E-Manual 101 Task Manager ASUS Task Manager displays a list of currently running utilities and applications, including their usages in percentages, on your ASUS Transformer Book Trio.

You can also open and close the running apps individually or close all apps and utilities at once using the One-click Clean function. to manage Task Manager: 1. File Manager Tap Settings to go to the All Apps screen then tap WIDGETS to Play Store display the Widgets menu. gallery 2. Polaris Office Tap and hold ASUS Task Manager to display the ASUS Task Manager box on the Home Screen.

myLibrary Lite Camera Play Music Maps Email Gmail SuperNote MyNet MyCloud App Locker asus@vibe App Backup SuperNote Lite AudioWizard ASUS Studio ASUS Artist BuddyBuzz MyLibrary People Phone Email 102 ASUS Transformer Book Trio E-Manual 3. Swipe the list up and down to view all launched apps. 4. Tap beside the running app to close it. Tap One-click Clean to close all running apps at once. ASUS Transformer Book Trio E-Manual 103 File Manager File Manager allows you to easily locate and manage your data either on the internal storage or the connected external storage devices. Accessing the internal storage To access the internal storage: 1. Polaris Office Tap MyLibrary Lite > Internal Storage on the left panel to view the Camera Play Music Maps Email File Manager Gmail contents of your ASUS Transformer Book Trio then tap an item to select. If a microSD card is inserted, tap MicroSD to view the contents of your microSD card. superNote MyNet 3.

MyCloud Tap App Locker asus@vibe to return to the root directory of My Storage. App Backup SuperNote Lite AudioWizard ASUS Studio Play Music Accessing the external storage device ASUS Artist BuddyBuzz MyLibrary People Phone Maps To access the external storage device: Email Email 1. SuperNote Swipe down the notification bar on top of the screen to display the notification box. tap MyNet 2. To display the contents of your microSD card. . To unmount the microSD card from your ASUS Transformer Book AudioWizard rNote Lite Trio, tap ASUS Studio hone IMPORTANT! Ensure to save your data stored in your microSD card before unmounting the microSD card from your ASUS Transformer Book Trio. 104 ASUS Transformer Book Trio E-Manual Customizing your contents From File Manager, you can copy, cut, share and delete the contents of your device and the installed external storage device. When you customize a file or folder, tick the box beside the file or folder and the action bar appears on the upper right corner of the screen. Action bar Settings Settings screen allows you to configure the system settings of your ASUS Transformer Book Trio.

With this system app, you can configure your ASUS Transformer Book Trio's wireless connectivity, hardware, personal, account and system settings. There are two ways to launch the Settings screen. From the All Apps screen, tap Settings to display the menu. Swipe down the notification bar on top of the screen to display ASUS Quick Settings panel then tap . ASUS Transformer Book Trio E-Manual 105 Turning Android® off You can shut down your Android® operating system by doing any of the following: NOTE: The following steps also shuts down your tablet.

However, the PC station should be turned off separately when the tablet is docked and used as part of your ASUS Notebook Trio. □ • Press the power button for about two (2) seconds and when prompted, tap Power Off then tap OK. If your tablet is unresponsive, press and hold the power button for about seven (7) seconds until your ASUS Transformer Book Trio turns off. This will also reset your Android® OS. iMPORTANT! Forcing the system to shut down may result to data loss.

Ensure that you back up your data regularly. When you turn on your tablet after resetting, the Setup Wizard would automatically show up and guide you through the process of setting up Android®. Putting your tablet to sleep To put your tablet to sleep, press the power button once. 106 ASUS Transformer Book Trio E-Manual Chapter 5: Power-on Self Test (POST) ASUS Transformer Book Trio E-Manual 107 The Power-On SelfTest (POST) The Power-On Self-Test (POST) is a series of software-controlled diagnostic tests that run when you turn on or restart your ASUS Transformer Book Trio. The software that controls the POST is installed as a permanent part of the ASUS Transformer Book Trio's architecture. Using POST to access BIOS and Troubleshoot During POST, you can access the BIOS settings or run troubleshooting options using the function keys of your ASUS Transformer Book Trio. You may refer to the following information for more details. BIOS The Basic Input and Output System (BIOS) stores system hardware settings that are needed for system startup in the ASUS Transformer Book Trio. The default BIOS settings apply to most conditions of your ASUS Transformer Book Trio. Do not change the default BIOS settings except in the following circumstances: ••An error message appears onscreen during system bootup and requests you to run the BIOS Setup.

You have installed a new system component that requires further BIOS settings or updates. WARNING: Using inappropriate BIOS settings may result to system instability or boot failure. We strongly recommend that you change the BIOS settings only with the help of a trained service personnel. Accessing BIOS Restart your ASUS Transformer Book Trio then press during POST. 108 ASUS Transformer Book Trio E-Manual BIOS Settings NOTE: The BIOS screens in this section are for reference only. The actual screens may differ by model and territory. Boot This menu allows you to set your boot option priorities. You may refer to the following procedures when setting your boot priority. Advanced Boot Security Save & Exit Sets the system boot order [Windows Boot Manager] Boot Configuration Boot Option Priorities Boot Option #1 Add New Boot Option Delete Boot Option Boot Option #1 Windows Boot Manager Disabled →← : : ↵ Enter: +/— : F1 : F9 : F10 : ESC : Select Screen Select Item Select Change Opt. 110 ASUS Transformer Book Trio E-Manual Security This menu allows you to set up the administrator and user password of your ASUS Transformer Book Trio.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

It also allows you to control the access to your ASUS Transformer Book Trio's hard disk drive, input/output (I/O) interface, and USB interface. NOTE: • If you install a User Password, you will be prompted to input this before entering your ASUS Transformer Book Trio's operating system. If you install an Administrator Password, you will be prompted to input this before entering BIOS. The password length must be in the following range: Minimum length 3 Maximum length 20 Password Description If ONLY the Administrator's password is set, then this only limits access to Setup and is only asked for when entering Setup. If ONLY the user's password is set, then this is a power on password and must be entered to boot or enter Setup.

In Setup, the User will have Administrator rights. Type in a password then press . Re-type to confirm the password then press To clear the password: 1. on the Security screen , select Administrator Password or User Password. Type in the current password then press .

Leave the Create New Password field blank then press . 4. Select Yes in the confirmation box then press . 112 ASUS Transformer Book Trio E-Manual I/O Interface Security In the Security menu, you can access I/O Interface Security to lock or unlock some interface functions of your ASUS Transformer Book Trio. Select an interface you would like to lock then press . ASUS Transformer Book Trio E-Manual 113 USB Interface Security Through the I/O Interface Security menu, you can also access USB Interface Security to lock or unlock ports and devices. Select an interface that you would like to lock then select Lock.

NOTE: Setting the USB Interface to Lock also locks and hides the External Ports and other devices included under USB Interface Security. 114 ASUS Transformer Book Trio E-Manual Set Master Password In the Security menu, you can use Set Master Password to set up a password-enabled access to your hard disk drive. Password Description If ONLY the Administrator's password is set, then this only limits access to Setup and is only asked for when entering Setup.

If ONLY the user's password is set, then this is a power on password and must be entered to boot or enter Setup. In Setup, the User will have Administrator rights. Type in a password then press . Re-type to confirm the password then press Select Set User Password then repeat the previous steps to set up the user password. ASUS Transformer Book Trio E-Manual 115 Save & Exit To keep your configuration settings, select Save Changes and Exit before exiting the BIOS. main Aptio Setup Utility - Copyright (C) 2012 American Megatrends , Inc. Advanced Boot Security Save & Exit Exit system setup after saving the changes. Save Changes and Exit Discard Changes and Exit Save Options Save Changes Discard Changes Restore Defaults Boot Override Windows Boot Manager Launch EFI Shell from filesystem device →← : : ↑↓ Enter: +/— : F1 : F9 : F10 : ESC : Select Screen Select Item Select Change Opt. Verify the ASUS Transformer Book Trio's exact model then download the latest BIOS file for your model from the ASUS website.

Save a copy of the downloaded BIOS file to a flash disk drive. Connect your flash disk drive to your ASUS Transformer Book Trio. Restart your ASUS Transformer Book Trio then press POST. Locate your downloaded BIOS file in the flash disk drive then press . aSUSTek Easy Flash Utility FLASH TYPE: MXIC 25L Series Current BIOS Platform: TX300/TX200 Version: 101 Build Date: Oct 26 2012 Build Time: 11:51:05 New BIOS Platform: Unknown Version: Unknown Build Date: Unknown Build Time: Unknown FSO FS1 FS2 FS3 FS4 0 EFI <DIR> [←→]: Switch [↑↓]: Choose [q]: Exit [Enter]: Enter/Execute 7.

After the BIOS update process, select Exit > Restore Defaults to restore the system to its default settings. 118 ASUS Transformer Book Trio E-Manual Troubleshoot By pressing during POST, you can access Windows® 8 troubleshoot options which includes the following: ••• Refresh your PC Reset your PC Advanced options Refresh your PC Use Refresh your PC if you want to refresh your system without losing your current files and applications. to access this during POST: 1. Restart your ASUS Transformer Book Trio then press during POST. Wait for Windows® to load the Choose an option screen then tap Troubleshoot.

tap Refresh your PC. In the Refresh your PC screen, read the bullet points to learn more about using this option then tap Next. Tap the account you would like to refresh. Type your account password then tap Continue. Ensure that your ASUS Transformer Book Trio is plugged in to a power source before refreshing your system. Back up all your data before performing this option. Use Reset your PC to restore your ASUS Transformer Book Trio to its default settings. to access this during POST: 1. Restart your ASUS Transformer Book Trio then press during POST. Wait for Windows® to load the Choose an option screen then tap Troubleshoot.

tap Reset your PC. In the Reset your PC screen, read the bullet points to learn more about using this option then tap Next. Tap your preferred reset option: Just remove my files or Fully clean the drive. Ensure that your ASUS Transformer Book Trio is plugged in to a power source before resetting your system.

Restart your ASUS Transformer Book Trio then press during POST. Wait for Windows® to load the Choose an option screen then tap Troubleshoot. tap Advanced options. In the Advanced options screen, select the troubleshooting option you wish to perform. Follow the succeeding steps to complete the process. Using System Image Recovery Under Advanced options, you can use System Image Recovery to recover your system using your ASUS Transformer Book Trio's original image file.

to access this during POST: 1. Restart your ASUS Transformer Book Trio then press during POST. Wait for Windows® to load the Choose an option screen then tap Troubleshoot. Choose an account you would like to recover using a system image file. Type your account password then tap Continue.

Select Use the latest available system image (recommended), then tap Next. You can also choose Select a system image if your system image is in an external device or DVD. Follow the succeeding steps to complete the system image recovery procedure. NOTE: We strongly recommend that you regularly backup your system to prevent data loss in case your ASUS Transformer Book Trio stops working. 8.

122 ASUS Transformer Book Trio E-Manual Tips and FAQs ASUS Transformer Book Trio E-Manual 123 Useful tips for your ASUS Transformer Book Trio To help you maximize the use of your ASUS Transformer Book Trio, maintain its system performance, and ensure all your data are kept secured, here are some useful tips that you can follow: •• Update Windows® periodically to ensure that your applications have the latest security settings. Use ASUS Live Update to update ASUS-exclusive applications, drivers and utilities in your ASUS Transformer Book Trio.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>

Refer to the ASUS Tutor installed in your ASUS Transformer Book Trio for more details. Use an anti-virus software to protect your data and keep this updated too. Unless absolutely necessary, refrain from using force shutdown to turn off your ASUS Transformer Book Trio. Always backup your data and make it a point to create a backup data in an external storage drive. Refrain from using the ASUS Transformer Book Trio at extremely high temperatures. If you are not going to use your ASUS Transformer Book Trio for a long period of time (at least a month), we recommend that you take out the battery if the battery is removable. Disconnect all external devices and ensure you have the following items prior to resetting your ASUS Transformer Book Trio: - - - - 124
•••••Product key for your operating systems and other installed applications Backup data Log in ID and password Internet connection information ASUS Transformer Book Trio E-Manual Hardware FAQs 1. A black dot, or sometimes a colored dot, appears onscreen when I turn on the ASUS Transformer Book Trio.

what should I do? Although these dots normally appear onscreen, they will not affect your system. If the incident continues and subsequently affects system performance, consult an authorized ASUS service center. How can I fix this? The color and brightness of your display panel may be affected by the angle and current position of your ASUS Transformer Book Trio. The brightness and color tone of your ASUS Transformer Book Trio may also vary per model. You may use the function keys or the display settings in your operating system to adjust the appearance of your display panel. You can try doing any of the following suggestions: •••••Use Battery Mode under Power4Gear. Use the function keys to adjust the display brightness. enable Battery Saving mode under Instant On. If you are not using any Wi-Fi connection, switch your system into Airplane mode. disconnect unused USB devices.

Close unused applications, especially those that take up too much system memory. □ Check whether the power adapter or battery pack is attached correctly. You may also disconnect the power adapter or battery pack, wait for a minute, then reconnect them again to the power outlet and ASUS Transformer Book Trio. If the problem still exists, contact your local ASUS service center for assistance. •5.

Why is my touchpad not working? ••Press to enable your touchpad. Check if ASUS Smart Gesture has been set to disable the touchpad when connecting an external pointing device. 6. When I play audio and video files, why can't I hear any sound from my ASUS Transformer Book Trio's audio speakers? You can try doing any of the following suggestions: ••••Press to turn up the speaker volume. Check if your speakers were set to mute.

check if a headphone jack is connected to your ASUS Transformer Book Trio and remove it. Unlock the I/O Interface Security in your system's BIOS. For more details, refer to the I/O Interface Security section in this manual. 7. What should I do if my ASUS Transformer Book Trio's power adapter gets lost or my battery stops working? Contact your local ASUS service center for assistance. 126 ASUS Transformer Book Trio E-Manual 8. Why does audio still come out from my ASUS Transformer Book Trio's audio speakers even if I already connected my headphone into the right jack port? Go to Control Panel > Hardware and Sound then access Audio Manager to configure the settings. My ASUS Transformer Book Trio cannot do keystrokes correctly because my cursor keeps on moving. what should I do? Make sure that nothing accidentally touches or presses on your touchpad while you type on the keyboard. You can also disable your touchpad by pressing .

You can try doing any of the following suggestions: • Check if ASUS Smart Gesture is set to disable touchpad by connecting an external pointing device to your ASUS Transformer Book Trio. If yes, disable this function. Instead of showing letters, pressing the "U", "I", and "O" keys on my keyboard displays numbers. how can I change this? Press the key or (on selected models) on your ASUS Transformer Book Trio to turn off this feature and use the said keys for inputting letters. aSUS Transformer Book Trio E-Manual 127 Software FAQs 1. When I turn on my ASUS Transformer Book Trio, the power indicator lights up but not my drive activity indicator. system bootup does not happen as well. What can I do to fix this? You can try doing any of the following suggestions: • Force shutdown your ASUS Transformer Book Trio by pressing the power button for more than four (4) seconds. Check if the power adapter and battery pack are inserted correctly then turn on your ASUS Transformer Book Trio. If the problem still exists, contact your local ASUS service center for assistance. •2. What should I do when my screen displays this message: "Remove disks or other media. You can try doing any of the following suggestions: ••• Remove all connected USB devices then restart your ASUS Transformer Book Trio. Remove any optical discs that are left inside the optical drive then restart. If the problem still exists, your ASUS Transformer Book Trio might have a memory storage problem.

Contact your local ASUS service center for assistance. How can I fix this? Delete the applications you recently installed or were not included with your operating system package then restart your system. How can I fix this? You can try doing any of the following suggestions: •• Remove all connected devices to your ASUS Transformer Book Trio then restart your system. press F9 upon startup. When your ASUS Transformer Book Trio enters Troubleshooting, select Refresh or Reset your PC.

If the problem still exists, contact your local ASUS service center for assistance. •5. Why can't my ASUS Transformer Book Trio wake up from sleep or hibernate mode? □ • You need to press the power button to resume your last working state. Your system might have completely used up its battery power. Connect the power adapter to your ASUS Transformer Book Trio and connect to a power outlet then press the power button. aSUS Transformer Book Trio E-Manual 129 6. How can I boot to DOS using my USB drive or ODD? Restart your ASUS Transformer Book Trio and enter BIOS by pressing F2 on your keyboard. go to Boot > Launch CSM > Enabled. Go to the Security menu then set Secure Boot Control to Disabled. 130 ASUS Transformer Book Trio E-Manual Appendices ASUS Transformer Book Trio E-Manual 131 DVD-ROM Drive Information (on selected models) The DVD-ROM drive allows you to view and create your own CDs and DVDs.

You can purchase an optional DVD viewer software to view DVD titles. regional Playback Information Playback of DVD movie titles involves decoding MPEG2 video , digital AC3 audio and decryption of CSS protected content.



[You're reading an excerpt. Click here to read official ASUS TRANSFORMER BOOK TRIO TX201LAF-CQ004DW user guide](http://yourpdfguides.com/dref/5743008)
<http://yourpdfguides.com/dref/5743008>