



Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for BLACKBERRY STORM2 9500. You'll find the answers to all your questions on the BLACKBERRY STORM2 9500 in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

User manual BLACKBERRY STORM2 9500
User guide BLACKBERRY STORM2 9500
Operating instructions BLACKBERRY STORM2 9500
Instructions for use BLACKBERRY STORM2 9500
Instruction manual BLACKBERRY STORM2 9500



BlackBerry Storm2 9520/9550 Smartphone

Safety and Product Information



[You're reading an excerpt. Click here to read official BLACKBERRY STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)
<http://yourpdfguides.com/dref/3247138>

Manual abstract:

Use of batteries that have not been approved by Research In Motion might present a risk of fire or explosion, which could cause serious harm, death, or property loss. Use only RIM approved holsters. Use of holsters that have not been approved by RIM might, in the long term, present a risk of serious harm. Use only RIM approved chargers. Use of chargers that have not been approved by RIM might present a risk of fire or explosion, which could cause serious harm, death, or property loss. When you wear the BlackBerry device close to your body, use a RIM approved holster with an integrated belt clip or maintain a distance of 0.98 in. (25 mm) between your BlackBerry device and your body while the BlackBerry device is transmitting. Use of bodyworn accessories, other than RIM approved holsters with an integrated belt clip, might cause your BlackBerry device to exceed radio frequency (RF) exposure standards if the accessories are worn on your body while the BlackBerry device is transmitting. The long term effects of exceeding RF exposure standards might present a risk of serious harm.

For more information about the compliance of this BlackBerry device with the FCC RF emission guidelines, visit www.fcc.gov/oet/ea/fccid and search for the FCC ID for your BlackBerry device as listed below: · BlackBerry® Storm2TM 9520 smartphone: FCC ID L6ARCP50UW · BlackBerry® Storm2TM 9550 smartphone: FCC ID L6ARCK70CW 3 Do not rely on your BlackBerry device for emergency communications. The wireless networks that are necessary to make emergency calls or send messages are not available in all areas, and emergency numbers (such as 911, 112, or 999) might not connect you to emergency services in all areas. If you have the BlackBerry® Mobile Voice System installed on your BlackBerry device, see the "About emergency calls and the BlackBerry Mobile Voice System" section for more information about emergency calls.

Do not disassemble your BlackBerry device. Your BlackBerry device contains small parts that might be a choking hazard. Keep your BlackBerry device away from medical devices, including pacemakers and hearing aids, as they might malfunction causing serious harm or death to you or others. Do not put your BlackBerry device in contact with liquids as this might cause a short circuit, a fire, or an electric shock. When you use your BlackBerry device speakerphone, never hold the BlackBerry device to your ear.

Serious and permanent hearing damage could occur. Exposure to flashing lights on the BlackBerry device can cause epileptic seizures or blackouts and might be dangerous to you or others. If you are susceptible to epileptic seizures or blackouts, consult your physician before you use the BlackBerry device. Do not use your BlackBerry device while driving unless you are permitted by law to use the BlackBerry device in hands-free mode. Using your BlackBerry device while driving could put you and others at greater risk of an accident causing serious injury, death, or property loss. Do not use your BlackBerry device in the presence of gas fumes as it might present a risk of fire or explosion. Do not use or store your BlackBerry device in temperatures that exceed 104° F (40°C) as the BlackBerry device might become hot. 4 Do not dispose of your BlackBerry device in a fire as this might cause an explosion resulting in serious injury, death, or property loss. Turn off your BlackBerry device in aircrafts. Using your BlackBerry device on an aircraft might affect aircraft instrumentation, communication, and performance; might disrupt the network; might otherwise be dangerous to the operation of the aircraft, its crew, and its passengers; and might be illegal.

BlackBerry devices are not inherently safe and cannot be used in the presence of explosive fumes, explosive dust, or other explosive chemicals. Sparks in such areas could cause an explosion or fire resulting in serious injury, death, or damage to property. 5 6 Safety information Please read these safety and operation instructions before using the BlackBerry® device or any accessories provided with the device. Retain these instructions for future use. In some countries there may be restrictions on using Bluetooth® enabled and wireless devices with encryption software. Check with your local authorities. Electrical safety Charge the BlackBerry® device using only the charging accessories provided by or specifically approved by Research In Motion for use with this BlackBerry device. Any approval from RIM under this document must be in writing and must be from a person authorized to provide such approval. Use of any other accessory might invalidate any warranty provided with the BlackBerry device and might be dangerous. Approved charging accessory models for the BlackBerry® Storm2TM 9520 smartphone ASY-04195-002 ASY-14396-012 ASY-18071-001 ASY-18072-002 ASY-18078-001 Approved charging accessory models for the BlackBerry® Storm2TM 9550 smartphone ASY-04195-002 ASY-14396-012 ASY-18071-001 ASY-18078-003 ASY-18080-003 ASY-18080-007 ASY-18683-001 ASY-18685-001 ASY-18976-002 7 ASY-18078-003 ASY-18080-003 ASY-18080-007 ASY-18083-001 ASY-18683-001 ASY-18685-001 ASY-18976-002 ASY-24479-005 Approved charging accessory models for the BlackBerry® Storm2TM 9550 smartphone ASY-18072-002 ASY-18078-001 Use the charging accessories provided with the BlackBerry device or any other RIM approved charging accessories only from the type of power source indicated on the marking label.

Before you use any power supply, verify that the mains voltage is in accordance with the voltage printed on the power supply. Connect the BlackBerry device only to products that bear the USB-IF logo or have completed the USB-IF compliance program. Do not overload power outlets, extension cords, or convenience receptacles as this might result in a risk of fire or electric shock. To reduce the risk of damage to the cord or the plug, pull the plug rather than the cord when you disconnect the charging accessory from the power outlet or convenience receptacle. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where the power cord connects to the BlackBerry device.

Unplug charging accessories during lightning storms or when unused for long periods of time. Do not use charging accessories outside or in any area exposed to the elements. For more information about inserting the lithium-ion battery and connecting the power supply, see the documentation that came with the BlackBerry device. To buy accessories for your BlackBerry device, contact your wireless service provider or visit www.shopblackberry.com. ASY-18083-001 ASY-24479-005 Battery safety and disposal The BlackBerry® device contains a removable lithium-ion battery. Do not dispose of either the BlackBerry device or the lithium-ion battery in a fire. Dispose of the lithium-ion battery in accordance with the laws and regulations in your area governing disposal of such cell types.



[You're reading an excerpt. Click here to read official BLACKBERRY STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)
<http://yourpdfguides.com/dref/3247138>

8 The lithium-ion battery might present a fire or chemical burn hazard if mistreated. Do not disassemble, crush, or puncture the lithium-ion battery. Do not heat the lithium-ion battery above 140°F (60°C). Do not allow metal objects to contact the battery terminals. Use only the lithium-ion battery that Research In Motion specifies for use with your particular BlackBerry device model. RIM specifies lithium-ion batteries for use in BlackBerry table: Device operating Device storage Travel charger operating Travel charger storage 32 to 104°F (0 to 40°C) 50 to 86°F (10 to 30°C) 32 to 104°F (0 to 40°C) -22 to 167°F (-30 to 75°C) Interference with electronic equipment Most modern electronic equipment is shielded from radio frequency (RF) signals.

However, certain electronic equipment might not be shielded against the RF signals from the BlackBerry® device. Pacemakers: Consult a physician or the manufacturer of your pacemaker if you have any questions regarding the effect of RF signals on your pacemaker. Verify that you are using the BlackBerry device in accordance with the safety requirements associated with your particular pacemaker, which might include the following requirements: · Always keep the BlackBerry device more than 7.88 inches (20 cm) from the pacemaker when the BlackBerry device is turned on. · Do not carry the BlackBerry device in your breast pocket. · When using the phone on the BlackBerry device, use the ear opposite the pacemaker for making and receiving calls to minimize the potential interference. · If you have any reason to suspect that interference is taking place, turn off all wireless connections on the BlackBerry device immediately. Stop using your BlackBerry device and consult a physician. 11 Hearing aids: Some digital wireless devices might interfere with some hearing aids. In the event of such interference, consult your wireless service provider or contact the manufacturer of your hearing aid to discuss alternatives. Other medical devices: If you use any other personal medical device, consult the manufacturer of your device to determine if the device is adequately shielded from external RF energy. Your physician might be able to assist you in obtaining this information. Health care facilities: Turn off all wireless connections on the BlackBerry device in health care facilities when any regulations posted in these areas instruct you to do so. Hospitals or health care facilities might be using equipment that could be sensitive to external RF energy. Aircraft: Federal Aviation Administration (FAA) and Federal Communications Commission (FCC) regulations prohibit using the radio of wireless devices while in the air.

Turn off all wireless connections on the BlackBerry device before boarding an aircraft. The effect of using the BlackBerry device with wireless connections turned on in an aircraft is unknown. Such use might affect aircraft instrumentation, communication, and performance, might disrupt the network, might otherwise be dangerous to the operation of the aircraft, and might be illegal. With all wireless connections on the BlackBerry device turned off, use only non-radio based device applications in accordance with airline regulations for electronic devices. Dangerous areas The BlackBerry® device is not an intrinsically safe device and is not suitable for use in hazardous environments, where such devices are required, including without limitation, in presence of gas fumes, explosive dust situations, operation of nuclear facilities, aircraft navigation or communication services, air traffic control, and life support or weapons systems.

Potentially explosive atmospheres: Turn off all wireless connections on the BlackBerry device when in any area with a potentially explosive atmosphere, and obey all signs and instructions. Sparks in such areas could cause an explosion or fire resulting in bodily injury or even death. 12 Areas with a potentially explosive atmosphere are often, but not always, clearly marked. They include fueling areas such as gasoline or petrol stations; below deck on boats; fuel or chemical transfer or storage facilities; vehicles using liquefied petroleum gas (such as propane or butane); areas where the air contains chemicals or particles, such as grain, dust, or metal powders; and any other area where you would normally be advised to turn off your vehicle engine. Do not use the phone on the BlackBerry device to report a gas leak in the vicinity of the leak. Leave the area and, if the phone is available and active on the BlackBerry device, make the call from a safe location. Blasting areas: To avoid interfering with blasting operations, turn off all wireless connections on the BlackBerry device when in a "blasting area" or in areas posted: "Turn off two-way radio." Obey all signs and instructions. Service Only qualified service personnel should perform repairs to the BlackBerry® device. Disconnect the power supply cables from the computer or electrical outlet and refer the BlackBerry device or charging accessory for service to qualified service personnel if any of the following situations occur: the power supply cord, plug, or connector is damaged liquid has been spilled or objects have fallen into the BlackBerry device or charging accessory the BlackBerry device or charging accessory has been exposed to rain or water the BlackBerry device or charging accessory becomes very hot to the touch the BlackBerry device or charging accessory has been dropped or damaged in any way the BlackBerry device or charging accessory does not operate normally by following the instructions in the user documentation · the BlackBerry device or charging accessory exhibits a distinct change in performance Do not attempt to disassemble the BlackBerry device or any charging accessory.

13 To reduce the risk of fire or electric shock, adjust only those controls that are covered in the user documentation for the BlackBerry device. An improper adjustment of other controls might cause damage and will often require extensive work by a qualified technician to restore the BlackBerry device, charging accessory, or any other accessory to normal operation. Failure to observe all safety instructions contained in the user documentation for the BlackBerry device will void the Limited Warranty and might lead to suspension or denial of services to the offender, legal action, or both. About emergency calls and the

BlackBerry Mobile Voice System If you have the BlackBerry® Mobile Voice System installed on your BlackBerry device, the following statements are applicable to you: Emergency calls to 911, 112, 000, 999, or other internationally recognized numbers intended to connect to a public safety answering point or similar emergency services are not processed through the BlackBerry® Mobile Voice System, and are only processed from your BlackBerry device where mobile network coverage is available from a wireless service provider.



[You're reading an excerpt. Click here to read official BLACKBERRY STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)
<http://yourpdfguides.com/dref/3247138>

The BlackBerry MVS is not designed or intended to be a replacement for traditional telephone service. Additional arrangements must be made, separate from the BlackBerry MVS, for you to obtain access to traditional fixed or wireless telephone services, such as emergency calling capability. RIM and its affiliates, and their respective officers, directors, and employees shall have no responsibility or liability whatsoever for any personal injury, death, or damages arising out of or in connection with the inability to access emergency call services (for example, 911, 112, 000, or 999) through the BlackBerry MVS. By using the BlackBerry MVS Client, you agree to the above. If you do not agree to the above, remove the BlackBerry MVS Client from your device. Additional safety guidelines Speakerphone: The BlackBerry® device is equipped with a speakerphone that can generate audio levels loud enough for phone call operation while holding the BlackBerry device at an arm's length from your head.

When using your BlackBerry device speakerphone, never hold the BlackBerry device to your ear. Serious and permanent hearing damage could occur. Camera: Certain jurisdictions might prohibit or restrict your use of certain features on the BlackBerry device. If your BlackBerry device model has a camera, the following statements are applicable to you: 14 When taking, processing, or using pictures, obey all laws, regulations, procedures, and policies, including, without limitation, any copyright, personal privacy, trade secret, or security laws which might govern or restrict you while using the BlackBerry device.

Honor the personal rights of others.

Copyright protections might prevent you from copying, modifying, transferring, or forwarding some pictures, music (including ring tones), or other content. Do not aim the camera directly at the sun or any other bright light. This action could cause serious damage to your eyes or damage the BlackBerry device. Flashing lights: Exposure to flashing lights on the BlackBerry device can cause epileptic seizures or blackouts and might be dangerous to you or others. In the event that you experience, or your use of the BlackBerry device causes in others, any disorientation, loss of awareness, twitching, convulsions, or any involuntary movements, stop using the BlackBerry device immediately and consult a physician.

If you are susceptible to epileptic seizures or blackouts, consult your physician before using the BlackBerry device. The LED notification light is located on the front of your BlackBerry device, in the top right corner. If your BlackBerry device model has a camera, the camera flash LED aperture is located on the back of your BlackBerry device, either above or to the right of the camera lens. Caution: Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure. Audio files: The BlackBerry device has the capability to play audio files. When listening to audio files using headphones, permanent hearing loss might occur if headphones are used at a high volume. Avoid increasing the volume of your headphones to block out noisy surroundings. If you experience ringing in your ears or muffled speech, consult a physician to have your hearing checked.

Liquids and foreign objects: Never push objects of any kind into the BlackBerry device or device accessories through openings as this action might cause a short circuit, a fire, or electric shock. Do not use the BlackBerry device or device accessories near water (for example, near a bathtub or a sink, in a wet basement, or near a swimming pool).

Never spill liquid of any kind on the BlackBerry device or device accessories. Stability: Do not place the BlackBerry device or device accessory on any unstable surface. It could fall, thereby potentially causing serious injury to a person and serious damage to the BlackBerry device or device accessory. Take care when using the BlackBerry device with any charging accessories to route the power cord in a way that reduces the risk of injury to others, such as by tripping or choking. Cleaning: Do not use liquid, aerosol cleaners, or solvents on or near the BlackBerry device or device accessory. Clean only with a soft dry cloth. @@@@If discomfort persists, consult a physician. @@@@ (25 mm) from your body when the BlackBerry device is transmitting. @@ (25 mm) from your body. @@@@ (25 mm) from your body when the BlackBerry device is transmitting. @@ (25 mm) from your body. @@ (25 mm) from your body when the BlackBerry device is transmitting. @@@@Three or more bars indicate a strong signal.

A reduced signal display, which might occur in areas such as an underground parking structure or if you are traveling by train or car, might indicate increased power output from your BlackBerry device as it attempts to connect to a weak signal. · Use hands-free operation if it is available and keep the BlackBerry device at least 0.

98 in. (25 mm) from your body (including the abdomen of pregnant women and the lower abdomen of teenagers) when the BlackBerry device is turned on and connected to the wireless network. For more information about carrying your BlackBerry device, see the holster information in the "Additional safety guidelines" section of this document. · Reduce the amount of time spent on calls. Specific absorption rate data THIS WIRELESS DEVICE MODEL MEETS GOVERNMENT REQUIREMENTS FOR EXPOSURE TO RADIO WAVES WHEN USED AS DIRECTED IN THIS SECTION.

The BlackBerry® device is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission (FCC) of the U.S. Government, Industry Canada of the Canadian Government (IC), and recommended by The Council of the European Union when used as directed in the previous section. These limits are part of 18 comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The exposure standard for wireless devices employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC/IC is 1.6W/kg*. The SAR limit recommended by The Council of the European Union is 2.

0W/kg**. Tests for SAR are conducted using standard operating positions specified by the FCC/IC with the device transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the device while operating can be well below the maximum value. This is because the device is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output.



[You're reading an excerpt. Click here to read official BLACKBERRY](http://yourpdfguides.com/dref/3247138)

[STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)

<http://yourpdfguides.com/dref/3247138>

Before a wireless device model is available for sale to the public, it must be tested and certified to the FCC, IC, and The Council of the European Union that it does not exceed the limit established by the government-adopted requirement for safe exposure under the recommendations of the International Commission on Non-Ionizing Radiation Protection (ICNIRP). The tests are performed in positions and locations (for example, at the ear and worn on the body) as required by the FCC, IC, and The Council of the European Union for each model. The highest SAR value for your BlackBerry device model when tested for use at the ear is outlined as follows: Device BlackBerry® Storm2™ 9520 smartphone BlackBerry® Storm2™ 9550 smartphone SAR (W/kg) for 1g 0.97 1.01 SAR (W/kg) for 10g 1.

02 0.92 The highest reported SAR value for this BlackBerry device when clipped on a belt, in a Research In Motion approved holster equipped with an integrated belt clip, is outlined below. Carrying solutions, including RIM approved carrying solutions and carrying solutions not approved by RIM, that do not come equipped with an 19 integrated belt clip SHOULD NOT be worn or carried on the body. For more information regarding the wearing or carrying of this BlackBerry device without using a RIM approved carrying solution equipped with an integrated belt clip, see the holster information in the "Additional safety guidelines" section of this document. Device BlackBerry Storm2 9520 smartphone BlackBerry Storm2 9550 smartphone SAR (W/kg) for 1g 0.

60 0.63 SAR (W/kg) for 10g 0.53 0.45 Body-worn measurements differ among wireless device and phone models, depending upon available accessories and FCC, IC, and The Council of the European Union requirements. The FCC has granted an Equipment Authorization for this wireless device model with all reported SAR levels evaluated as in compliance with the FCC RF emission guidelines when the BlackBerry device is used as directed in this section.

SAR information on this wireless device model is on file with the FCC and can be found under the Display Grant section of www.fcc.gov/oet/ea after searching for the FCC ID for your device listed below. Additional information on SAR can be found on the CTIA - The Wireless Association® web site at www.ctia.org. In Japan, additional information on SAR can be found on the Association of Radio Industries and Businesses (ARIB) web site at www.arib-emf.org/index.html, or on the Telecommunications Bureau of the Ministry of Internal Affairs and Communications (MIC) web site at www.tele.soumu.go.jp/e/index.htm.

Device BlackBerry Storm2 9520 smartphone BlackBerry Storm2 9550 smartphone _____
FCC ID L6ARCP50UW L6ARCK70CW 20 * In the United States and Canada, the SAR limit for mobile devices used by the public is 1.6 watts/kg (W/kg) averaged over 1 g of tissue for the body or head (4.0 W/kg averaged over 10 g of tissue for the extremities hands, wrists, ankles, and feet). ** In Europe, the SAR limit for mobile devices used by the public is 2.0 watts/kg (W/kg) averaged over 10 g of tissue for the body or head (4.0 W/kg averaged over 10 g of tissue for the extremities - hands, wrists, ankles, and feet). Studies suggest that the standard incorporates a substantial margin of safety to give additional protection for the public and to account for any variations in measurements. The long-term characteristics or the possible physiological effects of Radio Frequency Electromagnetic fields have not been evaluated by Underwriters Laboratories Inc. (UL). FCC compliance statement (United States) FCC Class B Part 15 This device complies with Part 15 of the Federal Communications Commission (FCC) Rules.

Operation is subject to the following two conditions: · This device may not cause harmful interference. · This device must accept any interference received, including interference that may cause undesired operation. CAUTION: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the manufacturer's instructions, may cause interference harmful to radio communications. 21 There is no guarantee, however, that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: · · · · Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment to an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio or TV technician for help. US Information Concerning the Federal Communications Commission ("FCC") Requirements for Hearing Aid Compatibility with Wireless Devices When wireless devices are used near hearing devices (such as hearing aids and cochlear implants), users may detect a buzzing, humming, or whining noise. Some hearing devices are more immune than others to this interference, and wireless devices also vary in the amount of interference that they generate. The wireless telephone industry has developed ratings to assist hearing device users in finding wireless devices that may be compatible with their hearing devices. Not all wireless devices have been rated.

Wireless devices that are rated will have the rating displayed on the box together with other relevant approval markings. The ratings are not guarantees. Results will vary depending on the user's hearing device and hearing loss. If your hearing device is vulnerable to interference, you may not be able to use a rated wireless device successfully. Consulting with your hearing health professional and testing the wireless device with your hearing device is the best way to evaluate it for your personal needs. This BlackBerry® device has been tested and rated for use with hearing aids for some of the wireless technologies that the BlackBerry device uses. However, other wireless technologies may be used in this BlackBerry device that have not been tested for use with hearing aids. It is important to try the different features of your 22 BlackBerry device thoroughly and in different locations to determine if you hear any interfering noise when using this BlackBerry device with your hearing aid or cochlear implant. Consult your wireless service provider about its return and exchange policies and for information about hearing aid compatibility.



[You're reading an excerpt. Click here to read official BLACKBERRY STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)
<http://yourpdfguides.com/dref/3247138>

How the ratings work M-Ratings: Wireless devices rated M3 or M4 meet FCC requirements and are likely to generate less interference to hearing devices than wireless devices that are not labeled.

M4 is the better or higher of the two ratings. T-Ratings: Wireless devices rated T3 or T4 meet FCC requirements and are likely to be more usable with a hearing device's telecoil ("T Switch" or "Telephone Switch") than unrated wireless devices. T4 is the better or higher of the two ratings. (Note that not all hearing devices have telecoils in them.) Hearing devices may also be measured for immunity to this type of interference.

Your hearing device manufacturer or hearing health professional may help you find results for your hearing device. The more immune your hearing aid is, the less likely you are to experience interference noise from wireless devices. For more information about the actions that the FCC has taken with regard to hearing aid compatibility with wireless devices and other steps that the FCC has taken to ensure that individuals with disabilities have access to telecommunications services, visit www.fcc.gov/cgb/dro.

Industry Canada certification The BlackBerry® Storm2TM 9520 smartphone complies with Industry Canada RSS 102, RSS 132, RSS 133, RSS 210 under certification number 2503A-RCP50UW. The BlackBerry® Storm2TM 9550 smartphone complies with Industry Canada RSS 102, RSS 132, RSS 133, RSS 210 under certification number 2503A-RCK70CW. Class B compliance This BlackBerry® device complies with the Class B limits for radio noise emissions as set out in the interference-causing equipment standard entitled "Digital Apparatus," ICES-003 of Industry Canada. 23 EU regulatory conformance Research In Motion hereby declares that this BlackBerry® device is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. Device BlackBerry® Storm2TM 9520 smartphone BlackBerry® Storm2TM 9550 smartphone Applicable CE marking The Declaration of Conformity made under Directive 1999/5/EC (HG nr.88/2003) is available for viewing at the following location in the EU community:

www.blackberry.com/go/declarationofconformity. Research In Motion UK Limited 200 Bath Road Slough, Berkshire SL1 3XE United Kingdom If you have a Wi-Fi® enabled BlackBerry device, your BlackBerry device may be operated on Wi-Fi networks in all European Union member countries. When operated in France, this equipment uses non-harmonized frequency bands.

This equipment may be operated in Turkey. If you have a Wi-Fi enabled BlackBerry device, in France, outdoor operation of a wireless device is only permitted using the 2.4 to 2.454 GHz frequency band. The BlackBerry device only operates in infrastructure mode and as a result, will not transmit in the 2.4 to 2.454 GHz frequency band other than to communicate with a wireless access point. 24 Additional regulatory conformance Specific details about compliance with the following standards and regulatory bodies for your BlackBerry® device may be obtained from Research In Motion: Device BlackBerry® Storm2TM 9520 smartphone BlackBerry® Storm2TM 9550 smartphone Applicable conformance information · PCS Type Certification Review Board (PTCRB) · Underwriters Laboratories (UL) 60950-1 requirements for Canada and the United States · Radio and Telecommunications Terminal Equipment (R&TTE) Directive 1999/5/EC · Global Certification Forum Certification Criteria (GCF CC) requirements · International Electrotechnical Commission (IEC) 60825-1 2001: Safety of Laser Products This BlackBerry device supports the Turkish SMS characters as outlined in ETSI TS 123.038 V8.0.

0 (or newer version code) and ETSI TS 123.040 V8.1.0 (or newer version code). This BlackBerry device is in conformity with Turkey's EEE Directive. 25 26 BlackBerry device product information Product information: BlackBerry Storm2 9520 smartphone Mechanical properties: · weight: approximately 5.6 oz (160 g) including lithium-ion battery · size (L x W x H): 4.43 x 2.44 x 0.53 in.

(112.5 x 62 x 13.5 mm) · 2 GB on-board device memory, 256 MB flash memory Power specifications: · removable, rechargeable lithium-ion cell battery · supports 3V, 1.8V SIM cards · micro-USB-compatible port for data synchronization and charging LED camera flash properties: · Class 1 LED product · maximum radiated power: 3.2 mW Mobile network radio specifications: · single-band support: UMTS®/HSPA 2100 MHz · quad-band support: GSM® 850, GSM 900, DCS 1800, PCS 1900 MHz · networks: UMTS, HSPA, GSM 27 · power class: Class 3 (UMTS 2100), Class 1 (DCS 1800, PCS 1900), Class 4 (GSM 850) as defined in GSM 5.05, Class 4 (GSM 900) as defined in GSM 02.06, Class E2 (GSM 850, GSM 900, DCS 1800, PCS 1900) · transmitting frequency: UMTS 1920 to 1980 MHz, GSM 824 to 849 MHz, GSM 880 to 915 MHz, DCS 1710 to 1785 MHz, PCS 1850 to 1910 MHz · receiving frequency: UMTS 2110 to 2170 MHz, GSM 869 to 894 MHz, GSM 925 to 960 MHz, DCS 1805 to 1880 MHz, PCS 1930 to 1990 MHz, A-GPS 1575 MHz, A-GPS E911 1575 MHz Wi-Fi® network radio specifications: · wireless LAN standard: IEEE® 802.11bTM, IEEE® 802.11gTM · transmitting and receiving frequency: 2412 to 2472 MHz Bluetooth® radio specifications: · single-band support: ISM 2.4 GHz · transmitting and receiving frequency: 2402 to 2480 MHz · Bluetooth Class 1 Product information: BlackBerry Storm2 9550 smartphone Mechanical properties: · weight: approximately 5.

6 oz (160 g) including lithium-ion battery · size (L x W x H): 4.43 x 2.44 x 0.53 in. (112.5 x 62 x 13.5 mm) · 2 GB on-board device memory, 256 MB flash memory 28 Power specifications: · removable, rechargeable lithium-ion cell battery · supports 3V, 1.8V SIM cards · micro-USB-compatible port for data synchronization and charging LED camera flash properties: · Class 1 LED product · maximum radiated power: 3.2 mW Mobile network radio specifications: · single-band support: UMTS®/HSPA 2100 MHz · dual-band support: CDMA 800, CDMA 1900 MHz · quad-band support: GSM® 850, GSM 900, DCS 1800, PCS 1900 MHz · networks: UMTS, HSPA, CDMA2000® 1xEV-DO Rev A, GSM · power class: Class 3 (UMTS 2100), Class 3 (CDMA 800), Class 2 (CDMA 1900), Class 1 (DCS 1800, PCS 1900), Class 4 (GSM 850) as defined in GSM 5.05, Class 4 (GSM 900) as defined in GSM 02.06, Class E2 (GSM 850, GSM 900, DCS 1800, PCS 1900) · transmitting frequency: UMTS 1920 to 1980 MHz, Cell 824.70 to 848.31 MHz, GSM 824 to 849 MHz, GSM 880 to 915 MHz, DCS 1710 to 1785 MHz, PCS 1850 to 1910 MHz · receiving frequency: UMTS 2110 to 2170 MHz, Cell 869.70 to 893.31 MHz, GSM 869 to 894 MHz, GSM 925 to 960 MHz, DCS 1805 to 1880 MHz, PCS 1930 to 1990 MHz, A-GPS 1575 MHz, A-GPS E911 1575 MHz Wi-Fi® network radio specifications: 29 · wireless LAN standard: IEEE® 802.



[You're reading an excerpt. Click here to read official BLACKBERRY STORM2 9500 user guide](http://yourpdfguides.com/dref/3247138)

<http://yourpdfguides.com/dref/3247138>

11bTM, IEEE® 802.11gTM · transmitting and receiving frequency: 2412 to 2472 MHz Bluetooth® radio specifications: · single-band support: ISM 2.4 GHz · transmitting and receiving frequency: 2402 to 2480 MHz · Bluetooth Class 1 30 Legal notice ©2010 Research In Motion Limited. All rights reserved. BlackBerry®, RIM®, Research In Motion®, and related trademarks, names, and logos are the property of Research In Motion Limited and are registered and/or used in the U.

S. and countries around the world. ANSI is a trademark of the American National Standards Institute. Bluetooth is a trademark of Bluetooth SIG. CDMA2000 is a trademark of the Telecommunications Industry Association. CTIA - The Wireless Association is a trademark of CTIA - The Wireless Association. GSM is a trademark of the GSM MOU Association. IEEE, 802.11b, 802.11g, and IEEE Std 1725 are trademarks of the Institute of Electrical and Electronics Engineers, Inc.

UMTS is a trademark of European Telecommunications Standard Institute. Wi-Fi is a trademark of the Wi-Fi Alliance. All other trademarks are the property of their respective owners. Portions of the BlackBerry® Device Software are copyright © 2007-2008 The FreeType Project (www.freetype.org). All rights reserved. This documentation including all documentation incorporated by reference herein such as documentation provided or made available at www.blackberry.com/go/docs is provided or made accessible "AS IS" and "AS AVAILABLE" and without condition, endorsement, guarantee, representation, or warranty of any kind by Research In Motion Limited and its affiliated companies ("RIM") and RIM assumes no responsibility for any typographical, technical, or other inaccuracies, errors, or omissions in this documentation.

@@@The inclusion of a reference to Third Party Products and Services in this documentation does not imply endorsement by RIM of the Third Party Products and Services or the third party in any way. EXCEPT TO THE EXTENT SPECIFICALLY PROHIBITED BY APPLICABLE LAW IN YOUR JURISDICTION, ALL CONDITIONS, ENDORSEMENTS, GUARANTEES, REPRESENTATIONS, OR WARRANTIES OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING WITHOUT LIMITATION, ANY CONDITIONS, ENDORSEMENTS, GUARANTEES, REPRESENTATIONS OR WARRANTIES OF DURABILITY, FITNESS FOR A PARTICULAR PURPOSE OR USE, MERCHANTABILITY, MERCHANTABILITY, NON-INFRINGEMENT, SATISFACTORY QUALITY, OR TITLE, OR ARISING FROM A STATUTE OR CUSTOM OR A COURSE OF DEALING OR USAGE OF TRADE, OR RELATED TO THE DOCUMENTATION OR ITS USE, OR PERFORMANCE OR NON-PERFORMANCE OF ANY SOFTWARE, HARDWARE, SERVICE, OR ANY THIRD PARTY PRODUCTS AND SERVICES REFERENCED HEREIN, ARE HEREBY EXCLUDED. YOU MAY ALSO HAVE OTHER RIGHTS THAT VARY BY STATE OR PROVINCE. SOME JURISDICTIONS MAY NOT ALLOW THE EXCLUSION OR LIMITATION OF IMPLIED WARRANTIES AND CONDITIONS. TO THE EXTENT PERMITTED BY LAW, ANY IMPLIED WARRANTIES OR CONDITIONS RELATING TO THE DOCUMENTATION TO THE EXTENT THEY CANNOT BE EXCLUDED AS SET OUT ABOVE, BUT CAN BE LIMITED, ARE HEREBY LIMITED TO NINETY (90) DAYS FROM THE DATE YOU FIRST ACQUIRED THE DOCUMENTATION OR THE ITEM THAT IS THE SUBJECT OF THE CLAIM.

TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW IN YOUR JURISDICTION, IN NO EVENT SHALL RIM BE LIABLE FOR ANY TYPE OF DAMAGES RELATED TO THIS DOCUMENTATION OR ITS USE, OR PERFORMANCE OR NON-PERFORMANCE OF ANY SOFTWARE, HARDWARE, SERVICE, OR ANY THIRD PARTY PRODUCTS AND SERVICES REFERENCED HEREIN INCLUDING WITHOUT LIMITATION ANY OF THE FOLLOWING DAMAGES: DIRECT, CONSEQUENTIAL, EXEMPLARY, INCIDENTAL, INDIRECT, SPECIAL, PUNITIVE, OR AGGRAVATED DAMAGES, DAMAGES FOR LOSS OF PROFITS OR REVENUES, FAILURE TO REALIZE ANY EXPECTED SAVINGS, BUSINESS INTERRUPTION, LOSS OF BUSINESS INFORMATION, LOSS OF BUSINESS OPPORTUNITY, OR CORRUPTION OR LOSS OF DATA, FAILURES TO TRANSMIT OR RECEIVE ANY DATA, PROBLEMS ASSOCIATED WITH ANY APPLICATIONS USED IN CONJUNCTION WITH RIM PRODUCTS OR SERVICES, DOWNTIME COSTS, LOSS OF THE USE OF RIM PRODUCTS OR SERVICES OR ANY PORTION 32 THEREOF OR OF ANY AIRTIME SERVICES, COST OF SUBSTITUTE GOODS, COSTS OF COVER, FACILITIES OR SERVICES, COST OF CAPITAL, OR OTHER SIMILAR PECUNIARY LOSSES, WHETHER OR NOT SUCH DAMAGES WERE FORESEEN OR UNFORESEEN, AND EVEN IF RIM HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW IN YOUR JURISDICTION, RIM SHALL HAVE NO OTHER OBLIGATION, DUTY, OR LIABILITY WHATSOEVER IN CONTRACT, TORT, OR OTHERWISE TO YOU INCLUDING ANY LIABILITY FOR NEGLIGENCE OR STRICT LIABILITY. THE LIMITATIONS, EXCLUSIONS, AND DISCLAIMERS HEREIN SHALL APPLY: (A) IRRESPECTIVE OF THE NATURE OF THE CAUSE OF ACTION, DEMAND, OR ACTION BY YOU INCLUDING BUT NOT LIMITED TO BREACH OF CONTRACT, NEGLIGENCE, TORT, STRICT LIABILITY OR ANY OTHER LEGAL THEORY AND SHALL SURVIVE A FUNDAMENTAL BREACH OR BREACHES OR THE FAILURE OF THE ESSENTIAL PURPOSE OF THIS AGREEMENT OR OF ANY REMEDY CONTAINED HEREIN; AND (B) TO RIM AND ITS AFFILIATED COMPANIES, THEIR SUCCESSORS, ASSIGNS, AGENTS, SUPPLIERS (INCLUDING AIRTIME SERVICE PROVIDERS), AUTHORIZED RIM DISTRIBUTORS (ALSO INCLUDING AIRTIME SERVICE PROVIDERS) AND THEIR RESPECTIVE DIRECTORS, EMPLOYEES, AND INDEPENDENT CONTRACTORS. IN ADDITION TO THE LIMITATIONS AND EXCLUSIONS SET OUT ABOVE, IN NO EVENT SHALL ANY DIRECTOR, EMPLOYEE, AGENT, DISTRIBUTOR, SUPPLIER, INDEPENDENT CONTRACTOR OF RIM OR ANY AFFILIATES OF RIM HAVE ANY LIABILITY ARISING FROM OR RELATED TO THE DOCUMENTATION. Prior to subscribing for, installing, or using any Third Party Products and Services, it is your responsibility to ensure that your airtime service provider has agreed to support all of their features.

Some airtime service providers might not offer Internet browsing functionality with a subscription to the BlackBerry® Internet Service. Check with your service provider for availability, roaming arrangements, service plans and features. Installation or use of Third Party Products and Services with RIM's products and services may require one or more patent, trademark, copyright, or other licenses in order to avoid infringement or violation of third party rights. You are solely responsible for determining whether to use Third Party Products and Services and if any third party licenses are required to do so. If required you are responsible for acquiring them. You should not install or use Third Party 33 Products and Services until all necessary licenses have been acquired. Any Third Party Products and Services that are provided with RIM's products and services are provided as a convenience to you and are provided "AS IS" with no express or implied conditions, endorsements, guarantees, representations, or warranties of any kind by RIM and RIM assumes no liability whatsoever, in relation thereto. Your use of Third Party Products and Services shall be governed by and subject to you agreeing to the terms of separate licenses and other agreements applicable thereto with third parties, except to the extent expressly covered by a license or other agreement with RIM.



[You're reading an excerpt. Click here to read official BLACKBERRY
STORM2 9500 user guide
http://yourpdfguides.com/dref/3247138](http://yourpdfguides.com/dref/3247138)

Certain features outlined in this documentation require a minimum version of BlackBerry® Enterprise Server, BlackBerry® Desktop Software, and/or BlackBerry® Device Software. The terms of use of any RIM product or service are set out in a separate license or other agreement with RIM applicable thereto.

NOTHING IN THIS DOCUMENTATION IS INTENDED TO SUPERSEDE ANY EXPRESS WRITTEN AGREEMENTS OR WARRANTIES PROVIDED BY RIM FOR PORTIONS OF ANY RIM PRODUCT OR SERVICE OTHER THAN THIS DOCUMENTATION. Licensed by QUALCOMM Incorporated under one or more of the following United States Patents and/or their counterparts in other nations: 5,490,165 5,228,054 5,568,483 5,657,420 5,778,338 5,504,773 5,535,239 5,337,338 5,416,797 5,506,865 5,267,261 5,600,754 5,659,569 5,511,073 5,544,196 5,414,796 5,710,784 BlackBerry® Storm2™ 9520 smartphone model number: RCP51UW 34 BlackBerry® Storm2™ 9550 smartphone model number: RCK71CW Research In Motion Limited 295 Phillip Street Waterloo, ON N2L 3W8 Canada Research In Motion UK Limited Centrum House 36 Station Road Egham, Surrey TW20 9LF United Kingdom Published in Canada 35 .



[You're reading an excerpt. Click here to read official BLACKBERRY
STORM2 9500 user guide
http://yourpdfguides.com/dref/3247138](http://yourpdfguides.com/dref/3247138)