



Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for MOTOROLA T5000. You'll find the answers to all your questions on the MOTOROLA T5000 in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.

User manual MOTOROLA T5000
User guide MOTOROLA T5000
Operating instructions MOTOROLA T5000
Instructions for use MOTOROLA T5000
Instruction manual MOTOROLA T5000

T5000 & T5500 user guide -- Pg. 1

Contents	
Safety and General Information	2
FCC Licensing Information	10
Control Buttons	11
Getting Started	13
Installing in the AA Batteries	13
Installing the NiCd Battery Pack	13
Battery Meter	14
Attaching the Belt Clip	15
Removing the Belt Clip	15
Turning Your Radio On and Off	16
Setting the Volume	16
Setting a Channel	16
Channels and Frequencies	16
Talking and Listening	17
Belt Range	17
Checking the Channel Before Transmitting	17
Special Features	18
Interference Eliminator Code	18
Push-to-Talk Timeout Timer	18
Locking the Keypad	18
Scanning Channels	19
Advanced Scan	19
Alerts	20
Change Busy Indication	20
Setting and Transmitting Call Woes	20
Transmitting a Talk Confirmation Tone	21
QT Noise Filtering	21
Accessories	23
Using Audio Accessories	23
Voice Activation (VOX)	23
Setting the Sensitivity Level	24
Patent Information	25
Copyright Information	26
Warranty	27

Content

1

T5000 & T5500 user guide -- Pg. 2

Safety and General Information

Important Information on Safe and Efficient Operation

Read This Information Before Using Your Radio

The information provided in this document supersedes the general safety information in user guides published prior to December 1, 2002.

Transmit and Receive Procedure

Your two-way radio contains a transmitter and a receiver. To control your exposure and ensure compliance with the general population/uncontrolled environment exposure limits, always adhere to the following procedure:

- Transmit no more than 50% of the time.
- To transmit (talk), press the Push-to-Talk (PTT) button.
- To receive calls, release the PTT button.

Transmitting 50% of the time, or less, is important because the radio generates measurable RF energy exposure only when transmitting (in terms of measuring standards compliance).

Exposure to Radio Frequency Energy

Your Motorola radio is designed to comply with the following national and international standards and guidelines regarding exposure of human beings to radio frequency electromagnetic energy:

- United States Federal Communications Commission, Code of Federal Regulations, 47 CFR part 2, sub-part J



[You're reading an excerpt. Click here to read official MOTOROLA T5000 user guide](http://yourpdfguides.com/dref/2811491)
<http://yourpdfguides.com/dref/2811491>

Manual abstract:

· To receive calls, release the PTT button. @ @ Exposure To Radio Frequency Energy Your Motorola radio is designed to comply with the following national and international standards and guidelines regarding exposure of human beings to radio frequency electromagnetic energy: · United States Federal Communications Commission, Code of Federal Regulations; 47 CFR part 2 sub-part J 2 Content 1 T5000 & T5500 user guide --- Pg 3 To assure optimal radio performance and make sure human exposure to radio frequency electromagnetic energy is within the guidelines set forth in the above standards, always adhere to the following procedures. Portable Radio Operation and EME Exposure Antenna Care Use only the supplied or an approved replacement antenna. Unauthorized antennas, modifications, or attachments could damage the radio and may violate FCC regulations. DO NOT hold the antenna when the radio is "IN USE." Holding the antenna affects the effective range. T5000 & T5500 user guide --- Pg 4 Two-way Radio Operation Safety and General Information When using your radio as a traditional two-way radio, hold the radio in a vertical position with the microphone 1 to 2 inches (2.5 to 5 cm) away from the lips. Body-Worn Operation T maintain compliance with FCC/Health Canada RF exposure guidelines, if you wear o a radio on your body when transmitting, always place the radio in a Motorola-supplied or approved clip, holder, holster, case, or body harness for this product. Use of nonMotorola-approved accessories may exceed FCC/Health Canada RF exposure guidelines.

If you do not use one of the Motorola-supplied or approved body-worn accessories, and are not using the radio held in the normal use position, ensure the radio and its antenna are at least 1 inch (2.5 cm) from your body when transmitting. Data Operation If applicable, when using any data feature of the radio with or without an accessory cable, position the radio and its antenna at least 1 inch (2.5 cm) from the body. Approved Accessories For a list of approved Motorola accessories, visit our website at www.motorola.com.

Motorola.com. Electromagnetic Interference/Compatibility Note: Nearly every electronic device is susceptible to electromagnetic interference (EMI) if inadequately shielded, designed, or otherwise configured for electromagnetic compatibility. 4 Safety and General Information 3 · American National Standards Institute (ANSI) / Institute of Electrical and Electronic Engineers (IEEE) C95. 1-1992 · Institute of Electrical and Electronic Engineers (IEEE) C95. 1-1999 Edition · International Commission on Non-Ionizing Radiation Protection (ICNIRP) 1998 · Ministry of Health (Canada) Safety Code 6. Limits of Human Exposure to Radio Frequency Electromagnetic Fields in the Frequency Range from 3 kHz to 300 GHz, 1999 · Australian Communications Authority Radiocommunications (Electromagnetic Radiation - Human Exposure) Standard 2001 (applicable to wireless phones only) · ANATEL, Brasil Regulatory Authority, Resolution 256 (April 11, 2002) "additional requirements for SMR, cellular, and PCS product certification." T5000 & T5500 user guide --- Pg 5 Facilities Aircraft When instructed to do so, turn off your radio when on board an aircraft. Any use of a radio must be in accordance with applicable regulations per airline crew instructions. Medical Devices - Pacemakers The Advanced Medical Technology Association recommends that a minimum separation of 6 inches (15 cm) be maintained between a handheld wireless radio and a pacemaker. These recommendations are consistent with the independent research by, and recommendations of the U.S. Food and Drug Administration. Persons with pacemakers should: · ALWAYS keep the radio more than 6 inches (15 cm) from their pacemaker when the radio is turned ON. · Not carry the radio in the breast pocket.

· Use the ear opposite the pacemaker to minimize the potential for interference. · Turn the radio OFF immediately if you have any reason to suspect that interference is taking place. T5000 & T5500 user guide --- Pg 6 Medical Devices - Hearing Aids Safety and General Information Some digital wireless radios may interfere with some hearing aids. In the event of such interference, you may want to consult your hearing aid manufacturer to discuss alternatives. Other Medical Devices If you use any other personal medical device, consult the manufacturer of your device to determine if it is adequately shielded from RF energy. Your physician may be able to assist you in obtaining this information. Safety and General Use While Driving Check the laws and regulations on the use of radios in the area where you drive. Always obey them. When using your radio while driving, please: · Give full attention to driving and to the road. · Use hands-free operation, if available.

· Pull off the road and park before making or answering a call if driving conditions so require. Operational Warnings For Vehicles with an Air Bag Do not place a portable radio in the area over an air bag or in the air bag deployment area. Air bags inflate with great force. If a portable radio is placed in the air bag deployment area and the air bag inflates, the radio may be propelled with great force and cause serious injury to occupants of the vehicle. 6 Safety and General Information 5 To avoid electromagnetic interference and/or compatibility conflicts, turn off your radio in any facility where posted notices instruct you to do so.

Hospitals or health care facilities may be using equipment that is sensitive to external RF energy. T5000 & T5500 user guide --- Pg 7 Potentially Explosive Atmospheres Note: The areas with potentially explosive atmospheres referred to above include fueling areas such as below decks on boats, fuel or chemical transfer or storage facilities, areas where the air contains chemicals or particles, such as grain, dust, or metal powders, and any other area where you would normally be advised to turn off your vehicle engine. Areas with potentially explosive atmospheres are often but not always posted. Blasting Caps and Areas To avoid possible interference with blasting operations, turn off your radio when you o are near electrical blasting caps, in a blasting area, or in areas posted: "T urn off twoway radio." Obey all signs and instructions.

Operational Cautions Antennas Do not use any portable radio that has a damaged antenna. If a damaged antenna comes into contact with your skin, a minor burn can result. T5000 & T5500 user guide --- Pg 8 Batteries Safety and General Information All batteries can cause property damage and/or bodily injury such as burns if a conductive material such as jewelry, keys, or beaded chains touch exposed terminals. The conductive material may complete an electrical circuit (short circuit) and become quite hot. Exercise care in handling any charged battery, particularly when placing it inside a pocket, purse, or other container with metal objects.



[You're reading an excerpt. Click here to read official MOTOROLA T5000 user guide](http://yourpdfguides.com/dref/2811491)

<http://yourpdfguides.com/dref/2811491>

Battery Charger Safety Instructions Save these Instructions 1. Do not expose the charger to rain or snow. 2. Do not operate or disassemble the charger if it has received a sharp blow, or has been dropped or damaged in any way. 3.

Never alter the AC cord or plug provided with the unit. If the plug will not fit the outlet, have the proper outlet installed by a qualified electrician. An improper condition can result in a risk of electric shock. 4. To reduce the risk of damage to the cord or plug, pull the plug rather than the cord when disconnecting the charger from the AC receptacle. 5. To reduce the risk of electric shock, unplug the charger from the outlet before attempting any maintenance or cleaning. 6. Use of an attachment not recommended or sold by Motorola may result in a risk of fire, electric shock, or personal injury. 8 Safety and General Information 7 Turn off your radio prior to entering any area with a potentially explosive atmosphere, unless it is a radio type especially qualified for use in such areas as "Intrinsically Safe."

Do not remove, install, or charge batteries in such areas. Sparks in a potentially explosive atmosphere can cause an explosion or fire resulting in bodily injury or even death. T5000 & T5500 user guide --- Pg 9 T5000 & T5500 user guide --- Pg 10 FCC Licensing Information Your Motorola radio operates on General Mobile Radio Service (GMRS) frequencies and is subject to the Rules and Regulations of the Federal Communications Commission (FCC). The FCC requires that all operators using GMRS frequencies obtain a radio license before operating their equipment. To obtain the FCC forms, please request Form 605 and 159, which includes all forms and instructions.

If you wish to have the document faxed or mailed, or have questions, please use the following contact information. Faxed Contact the Fax-OnDemand system at: 1-202-418-0177 Mailed Call the FCC forms hotline at: 1-800-418-FORM 1-800-418-3676 Questions Regarding FCC license Contact the FCC at: 1-888-CALL-FCC 1-888-225-5322 Or: <http://www.fcc.gov> FCC Licensing Information Changes or modifications not expressly approved by Motorola may void the user's authority granted by the FCC to operate this radio and should not be made. To comply with FCC requirements, transmitter adjustments should be made only by or under the supervision of a person certified as technically qualified to perform transmitter maintenance and repairs in the private land mobile and fixed services as certified by an organization representative of the user of those services.

Replacement of any transmitter component (crystal, semiconductor, etc.) not authorized by the FCC equipment authorization for this radio could violate FCC rules. Note: Use of this radio outside the country where it was intended to be distributed is subject to government regulations and may be prohibited. 10 Safety and General Information 9 7. Make sure the cord is located so it will not be stepped on, tripped over, or subjected to damage or stress. 8. An extension cord should not be used unless absolutely necessary. Use of an improper extension cord could result in a risk of fire and/or electric shock. If an extension cord must be used, make sure that: · The pins on the plug of the extension cord are the same number, size and shape as those on the plug of the charger. · The extension cord is properly wired and in good electrical condition.

· The cord size is 18 AWG for lengths up to 100 feet, and 16 AWG for lengths up to 150 feet. 9. The supply cord of this charger cannot be replaced. If the cord is damaged, call Motorola Product Services at 1-800-353-2729 in USA or 1-888-390-6456 TTY (Text Telephone). T5000 & T5500 user guide --- Pg 11 Control Buttons - Model T5000 Use Use to: · Turn radio on/off · Adjust volume LED indicator light Use to: · Select menu options · Exit the menu (when pressed while clockwise to turn the radio on and counterclockwise to turn the radio off. The radio chirps and the display briefly shows all feature icons available on your radio. The display then scrolls through the available channels and Interference Eliminator Codes. Setting the Volume Rotate while holding down or until you reach a comfortable listening level. Rotate clockwise to increase the volume or counterclockwise to decrease the volume. T5000 & T5500 user guide --- Pg 16 Setting a Channel Your radio has 22 channels.

Channels 1-7 and 15-22 are 1 watt. Channels 8-14 are 0.5 watt. When the radio is on a 1 watt channel, displays. When the radio is on a 0.5 watt channel, displays. 1. With the radio on, press . The current channel flashes. 2.

Press or to set the channel. 3. Press to save the channel setting. Channels and Frequencies Channel 1 2 3 4 5 6 7 8 9 10 11 Frequency 462.5625 MHz 462.5875 MHz 462.6125 MHz 462.6375 MHz 462.6625 MHz 462.6875 MHz 462.

7125 MHz 467.5625 MHz 467.5875 MHz 467.6125 MHz 467.6375 MHz Description GMRS/FRS GMRS/FRS GMRS/FRS GMRS/FRS GMRS/FRS GMRS/FRS GMRS/FRS GMRS/FRS FRS FRS FRS FRS FRS Channel 12 13 14 15 16 17 18 19 20 21 22 Frequency 467.6625 MHz 467.6875 MHz 467.7125 MHz 462.5500 MHz 462.5750 MHz 462.

6000 MHz 462.6250 MHz 462.6500 MHz 462.6750 MHz 462.7000 MHz 462.

7250 MHz Description FRS FRS FRS GMRS GMRS GMRS GMRS GMRS GMRS Getting Started 15 T5000 & T5500 user guide --- Pg 17 Talking and Listening To communicate, all radios in your group must be set to the same channel and Interference Eliminator Code. To talk, press and hold . Hold the radio 2 to 3 inches away from your mouth when talking. When you finish talking, release (press to talk, release to listen). @@Do not use the radios closer than 5 feet apart.

@@@To set the code for a channel: 1. Press 2. Press 3. Press until the code starts to flash. or to select the code. @@@@To start scanning, briefly press and release or . The scan indicator displays. @@To respond to the transmitting, press within 5 seconds. @@@@This temporarily removes the channel from the scan list. To restore the channel, turn the radio off and then back on.

@@@To set a call tone: 1. With the radio on, press 3 times. The current call tone setting flashes and displays. or to change and hear the call tone. 2. Press or to set the new call tone. 3. @@Notes · The T5000 model has 5 call tones. The T5500 and T5550 model has 10 call tones. @@@@To turn talk confirmation off, turn your radio off and then back on while pressing and holding .

QT Noise Filtering The QT noise filtering feature helps ensure uninterrupted communication with other Motorola radios that have this feature. This feature filters out unwanted transmissions from other radios. It is useful in places where there is heavy radio traffic, such as at an amusement park or ski resort. Note: QT noise filtering is not available while the radio is scanning. To turn QT noise filtering on or off: 1.

Press until displays. 2. Press or until displays to turn noise filtering on, or until displays to turn noise filtering off.



[You're reading an excerpt. Click here to read official MOTOROLA T5000 user guide](http://yourpdfguides.com/dref/2811491)
<http://yourpdfguides.com/dref/2811491>

to confirm your selection. 3.

Press T5000 & T5500 user guide --- Pg 22 To transmit to a radio that has QT noise filtering turned on: 1. Select the same channel and Interference Eliminator Code as the other radio. 2. Press to send a call tone. This allows your voice to pass through the QT noise filter on the receiving radio. and speak normally. 3. Press Note: If you skip step 2, the beginning of your message may not be heard on the receiving radio. For a 30-second period, starting after the last transmission, all transmissions received on the selected channel and code will pass through the QT noise filter. Alerts 22 Alerts 21 T50800 & T5500 user guide --- Pg 23 Accessories There are many accessories (sold separately) available for your radio.

For more information, refer to the brochure included with your radio, contact the place of purchase. Using Audio Accessories 1. Turn the radio off. Plug the accessory connector into the jack. See page 11 and 12 for the location of the accessory jack on your radio. 2. Turn the radio on. Lower the volume before placing the accessory on your head or in your ear. or while rotating to adjust the volume to a comfortable level. 3.

Press and speak into the accessory microphone, if any. 4. To transmit, press . 5. To receive, release Voice Activation (VOX) (T5500 and T5550 models only) Voice activation (VOX) allow you to talk handsfree when used with optional accessories connected to the radio.

See the Motorola Talkabout accessory brochure for available VOX accessories. 1. 2. 3. 4.

Turn the radio off. Insert the plug of the audio accessory firmly into the accessory jack (see page 12). Turn the radio on. displays. Lower the radio volume before placing the accessory on your head or in your ear. T5000 & T5500 user guide --- Pg 24 5. To transmit, speak into accessory microphone. There is a short delay between the time you start talking and when the radio transmits. 6. To receive, stop talking.

To turn VOX off, press or remove the audio accessory. Setting the Sensitivity Level Adjusting the radio's sensitivity level helps minimize the possibility of unintended noises triggering a transmission and helps the radio pick up soft voices. Accessories 1. Press 2. Press until displays. or to select the sensitivity level: = Medium Sensitivity for most environments = Low Sensitivity for noisy environments = High Sensitivity for quiet environments Note: When you connect a VOX accessory, the radio is automatically set to the last chosen sensitivity level. 24 Accessories 23 T5000 & T5500 user guide --- Pg 25 Patent Information This product is manufactured under one or more of the following United States patents. 5896277 5894292 5864752 5699006 5742484 D408396 D399821 D387758 D389158 5894592 5893027 5789098 5734975 5861850 D395882 D383745 D389827 D389139 5929825 5926514 5953640 6071640 D413022 D416252 D416893 D433001 This product is controlled under the export regulations of the United States of America and Canada. The Governments of the United States of America and Canada may restrict the exportation or re-exportation of this product to certain destinations. For further information contact the U.

S. Department of Commerce or the Canadian Department of Foreign Affairs and International Trade. T5000 & T5500 user guide --- Pg 26 Copyright Information Manufactured, distributed or sold by Giant International Ltd., official licensee for this product. Motorola, the Motorola logo trademarks and the Motorola trade dress are owned by Motorola, Inc.

and are used under license from Motorola, Inc. Please contact Giant International Ltd. at 800-638-5119 for questions/comments, warranty, support, or service related to this product. MOTOROLA and the Stylized M Logo are registered in the U.S.

Patent & Trademark Office. All other product or service names are the property of their respective owners. © Motorola, Inc. 2004. Copyright Information 26

Patent Information 25 Export Law Assurances T5000 & T5500 user guide --- Pg 27 Motorola Limited Warranty for Personal Communication Products, Accessories and Software Purchased in the United States or Canada What Does this Warranty Cover? Subject to the exclusions contained below, Motorola, Inc. or its licensees warrants its consumer two-way radios that operate via Family Radio Service or General Mobile Radio Service ("Products"), Motorola-branded or certified accessories sold for use with these Products ("Accessories") and Motorola software contained on CD-Roms or other tangible media and sold for use with these Products ("Software") to be free from defects in materials and workmanship under normal consumer usage for the period(s) outlined below. This limited warranty is a consumer's exclusive remedy, and applies as follows to new Motorola Products, Accessories and Software purchased by consumers in the United States or Canada, which are accompanied by this written warranty: Products Covered Length of Coverage A. Products as defined above, unless otherwise provided for below. A. One (1) year from the date of purchase by the first consumer purchaser of the product unless otherwise provided for below.

Exclusions Normal Wear and Tear. Periodic maintenance, repair and replacement of parts due to normal wear and tear are excluded from coverage. Batteries. T5000 & T5500 user guide --- Pg 28 Products Covered Length of Coverage 1. Consumer Two- 1. Ninety (90) days from the date of purchase by Way Radio the first consumer Accessories. purchaser of the product. Exclusions Normal Wear and Tear. Periodic maintenance, repair and replacement of parts due to normal wear and tear are excluded from coverage. Batteries.

@@Abuse & Misuse. @@Products and Accessories that are Repaired or Replaced. 2. @@Use of Non-Motorola Products and Accessories. @@Unauthorized Service or Modification.

Defects or damages resulting from service, testing, adjustment, installation, maintenance, alteration, or modification in any way by someone other than Motorola, or its authorized service centers, are excluded from coverage. Altered Products. Products or Accessories with (a) serial numbers or date tags that have been removed, altered or obliterated; (b) broken seals T5000 & T5500 user guide --- Pg 30 Products Covered Length of Coverage Exclusions or that show evidence of tampering; (c) mismatched board serial numbers; or (d) nonconforming or non-Motorola housings, or parts, are excluded from coverage.

Communication Services. Defects, damages, or the failure of Products, Accessories or Software due to any communication service or signal you may subscribe to or use with the Products Accessories or Software is excluded from coverage.

Warranty Who is covered? This warranty extends only to the first consumer purchaser, and is not transferable. What will Motorola Do? Motorola or its licensees, at its option, will at no charge repair, replace or refund the purchase price of any Products, Accessories or Software that does not conform to this warranty.



[You're reading an excerpt. Click here to read official MOTOROLA](http://yourpdfguides.com/dref/2811491)

[T5000 user guide](http://yourpdfguides.com/dref/2811491)

<http://yourpdfguides.com/dref/2811491>

We may use functionally equivalent reconditioned/refurbished/pre-owned or new Products, Accessories or parts. No data, software or applications added to your Product, Accessory or Software, including but not limited to personal contacts, games and ringer tones, will be reinstalled. To avoid losing such data, software and applications please create a back up prior to requesting service. 30 Warranty 29 T5000 & T5500 user guide --- Pg 31 How to Obtain Warranty Service or Other Information? To obtain service or information, please call: USA Two-Way Radios 1-800-638-5119 Canada Two-Way radio 1-800-638-5119 For Accessories and Software, please call the telephone number designated above for the product with which they are used. You will receive instructions on how to ship the Products, Accessories or Software, at your expense, to a Motorola Authorized Repair Center. To obtain service, you must include: (a) a copy of your receipt, bill of sale or other comparable proof of purchase; (b) a written description of the problem; (c) the name of your service provider, if applicable; (d) the name and location of the installation facility (if applicable) and, most importantly; (e) your address and telephone number. What Other Limitations Are There? ANY IMPLIED WARRANTIES, INCLUDING WITHOUT LIMITATION THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, SHALL BE LIMITED TO the duration of this Limited WARRANTY, otherwise the REPAIR, REPLACEMENT, OR REFUND AS PROVIDED UNDER THIS EXPRESS Limited WARRANTY IS THE EXCLUSIVE REMEDY OF THE CONSUMER, and is provided in lieu of all other warranties, express of implied. In no event shall Motorola be liable, whether in contract or tort (including negligence) for damages in excess of the purchase price of the Product, Accessory or Software, or for any indirect, incidental, special or consequential damages of any kind, or loss of revenue or profits, loss of business, loss of information or data, software or applications or other financial loss arising out of or in connection with the ability or T5000 & T5500 user guide --- Pg 32 inability to use the Products, Accessories or Software to the full extent these damages may be disclaimed by law.

Some states and jurisdictions do not allow the limitation or exclusion of incidental or consequential damages, or limitation on the length of an implied warranty, so the above limitations or exclusions may not apply to you. This warranty gives you specific legal rights, and you may also have other rights that vary from state to state or from one jurisdiction to another. Warranty Laws in the United States and other countries preserve for Motorola certain exclusive rights for copyrighted Motorola software such as the exclusive rights to reproduce and distribute copies of the Motorola software. Motorola software may only be copied into, used in, and redistributed with, the Products associated with such Motorola software. No other use, including without limitation disassembly of such Motorola software or exercise of the exclusive rights reserved for Motorola, is permitted. 32 Warranty 31 T5000 & T5500 user guide --- cover User's Guide FRS/ GMRS RECREATIONAL TWO-WAY RADIOS KEM-PK10751 Models T5000,T5500, T5550 T5000 & T5500 user guide --- back · 22 Channels (8 GMRS, 7 GMSR/FRS, 7 FRS) with 38 Interference Eliminator Codes GMRS channels feature increased power for longer range. 14 channels ensure backward compatibility with FRS two-way radios. Eliminator Codes minimize interference from other groups. · Audible Call Tones 5 call tones (Model T5000) 10 call tones (Model T5500, T5550). · Weather-resistant Helps protect radios against the elements. · Talk Handsfree · 1 Year Limited Warranty For warranty details, please ask your retailer. With Voice Activation (VOX) when used with optional accessories. · Low Battery Alert Audible tone and visual display tell you when the battery is running down. · Motorola Quality Shock, drop, and temperature tested to meet Motorola's high quality standards. · Illuminated Display Easy to read your settings in dark places. · Scanning Easily finds channel and code by searching all combinations · Talk Confirmation Tones Signals others you are finished talking. · QT Noise Filter Filters out unwanted transmissions in heavy radio traffic areas. · Quick Release Swivel Belt Clip Included · User's Guide Included · Durable, Fixed Antenna Maximizes talk range. WARNING CHOKING HAZARD SMALL PARTS Not for children under 3 years. This product is not intended to be used as a toy or plaything.

FRS/GMRS use approved in the US only; GMRS License Required. MOTOROLA and the Stylized M Logo are registered in the US Patent & Trademark Office. All other product or service names are the property of their respective owners. © Motorola, Inc. 2004. .



[You're reading an excerpt. Click here to read official MOTOROLA T5000 user guide](http://yourpdfguides.com/dref/2811491)
<http://yourpdfguides.com/dref/2811491>