



Your PDF Guides

You can read the recommendations in the user guide, the technical guide or the installation guide for TOSHIBA BDX-1100-KB. You'll find the answers to all your questions on the TOSHIBA BDX-1100-KB in the user manual (information, specifications, safety advice, size, accessories, etc.). Detailed instructions for use are in the User's Guide.


User manual TOSHIBA BDX-1100-KB
User guide TOSHIBA BDX-1100-KB
Operating instructions TOSHIBA BDX-1100-KB
Instructions for use TOSHIBA BDX-1100-KB
Instruction manual TOSHIBA BDX-1100-KB



TOSHIBA



Blu-ray Disc Player



BDX1100KB
Owner's Manual



[You're reading an excerpt. Click here to read official TOSHIBA BDX-1100-KB user guide](http://yourpdfguides.com/dref/3873130)
<http://yourpdfguides.com/dref/3873130>

Manual abstract:

and.important.notice. @@@@3-4 2 Your Product. @@5-7 . Regions.codes....
. 5 Product.overview. 6 Remote.Control.
.. 7 . 3 Connections..
. 8-9 Connecting.to.a.TV.....

8 Optional.Connection. 9 Inserting.an.SD.Card.
.. 9 . Connect.power.
... 9 4 Preparation..
... 10 Prepare.the.remote.control....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

10 Setting.up.the.player. @@10. . . 5 Playback. ..
. 11-13 . Playback.Functions11-13 . 6 Customizing14-20 General.
Setting.
14-17 . Display.Setting.....18-19 . Audio.

Setting.19-20 . System.
information.... 20 7 Specification.
.. 21 8 Troubleshooting,22-23 9 Glossary..
....24-25 10 License Information.....

.....
.....
.....
.....

.....
.....
.....
.....

.....
.....
.....
.....

.....26-44 English 1.

.Important Safety and important notice Warning:Risk.of.overheating!.Never.install.
the.product.in.a. confined space.

Always leave a space of at least 4.inches.around.the.product.
for.ventilation.. Ensure.curtains.or.other.objects.never.cover.

the.ventilation.slots.on.the.product. ·Never place the product, remote control or batteries near naked flames or other heat sources, including direct sunlight.

·...

.Only.use.this.product.

indoors..Keep.this.product.

away from water, moisture and liquid-filled objects. ·....Never.place.this.product.on.

other.electrical. equipment. ·....Keep.away.from.
this.product.during.lightning. storms.

·....Where.

the.mains.plug.or.an.appliance.coupler.is. used as the disconnect device, the disconnect device.shall.

remain.readily.operable. LASER CAUTION: USE.OF.CONTROLS.OR.ADJUSTMENTS.OR. PERFORMANCE.
OF.PROCEDURES.OTHER.THAN. THOSE.
SPECIFIED.HEREIN.MAY.RESULT.IN.
HAZARDOUS.RADIATION.EXPOSURE. CAUTION: VISIBLE.AND.INVISIBLE.LASER.RADIATION. WHEN.OPEN.

AND.INTERLOCKS.DEFEATED..DO. NOT.STARE.INTO.BEAM. LOCATION: INSIDE, NEAR THE DECK MECHANISM.
Pb,Hg,Cd This.product.and.-.if.
applicable.-.the.supplied. accessories.
too.are.marked.with."CE".and. comply.therefore.with.the.

applicable.harmonized. European.standards..the.Low.Voltage.Directive. 2006/95/EC, the EMC Directive 2004/108/EC ,the ErP Directive 2009/125/EC.
Responsible.for.CE-marking.is.TOSHIBA.

INFORMATION SYSTEMS (U.K.) LTD, Toshiba Court, Weybridge Business Park, Addlestone Road, Weybridge,Surrey,KT15 2UL, United.Kingdom.
Following information is only valid for EU member States: Disposal of products The crossed out wheeled dust bin symbol indicates that products must be
collected and disposed of separately from household waste.

Integrated batteries and accumulators can be disposed of with the product. They will be separated at the recycling centres. The black bar indicates that the
product was placed on the market after August 13, 2005. By participating in separate collection of products and batteries, you will help to assure the proper
disposal of products and batteries and thus help to prevent potential negative consequences for the environment and human health. For more detailed
information about the collection and recycling programmes available in your country,please visit our website (www.home-entertainment.toshiba. co.uk) or
alternatively please contact your retailer where the product was purchased. Disposal of batteries and/or accumulators The crossed out wheeled dust bin
symbol indicates that batteries and/or accumulators must be collected and disposed of separately from household waste.

If the battery or accumulator contains more than the specified values of lead (Pb), mercury (Hg),and/or cadmium (Cd) defined in the Battery Directive
(2006/66/EC), then the chemical symbols for lead (Pb), mercury (Hg) and/or cadmium (Cd) will appear below the crossed out wheeled dust bin symbol. By
participating in separate collection of batteries, you will help to assure the proper disposal of products and batteries and thus help to prevent potential
negative consequences for the environment and human health. For more detailed information about the collection and recycling programmes available in
your country,please visit our website (www.home-entertainment.toshiba. co.uk) or alternatively please contact your retailer where the product was purchased.

General Information . This. appliance.
may. be. fitted. with. a.
nonrewireable. plug.. If. it.
is. necessary. to. change. the. fuse.in.a.non-rewireable.plug.

the.fuse.cover.must. be.refitted. If.the.fuse.cover.is.lost.or.damaged, the. plug. must. . not.
be. used. until. a. replacement.
available. from. the. appliance. manufacturer.
is. obtained..If.the.plug.has.to.be.changed.

because. it.is.not.suitable.for.your.socket, or.becomes.damaged, it.should.be.cut.off.and.an.appropriate.plug.fitted.following.the.wiring.instructions.below.
The.plug.removed.must.be.disposed.of.safely.
as. it.is.hazardous.if.
inserted.into.a.live.socket.

English Disposal of your old product and batteries IMPORTANT The. wires. in. this. mains. lead. are. coloured. in.accordance.

with.the.following.code: BLUE:..NEUTRAL BROWN:..LIVE . As.the.
colours.of.the.wires.in.
the.mains. lead. of. this.
unit. may. not. correspond. with. the. coloured. markings. identifying. the. terminals. in. your. plug, proceed. as. follows:.

. The. wire. that. is. coloured. blue. must. be. connected.
to. the. terminal. in. the.
plug. which. is. marked. with.
the. letter. N. or. coloured.black. . The. wire. that.
is. coloured. brown. must. be. connected. to. the. terminal. which.
is. marked. with. the. letter.
L. or. coloured. red. Do.
not. connect. either. wire. to. the. earth. terminal,which.is.

marked.by.the.letter.E.or. by.the.safety.earth.
symbol. .or.colored.green.or.
green-and-yellow. Use. a. 5A. BS1362.
fuse. which. is. approved. by. ASTA. or. BSI.. Always.

replace. the. fuse. cover.after.changing.the.fuse. Copyright notice This.product.
incorporates.copyright. protection.technology.that.
is.protected.by. U.S.

.patents.and.other.intellectual.property.rights...Use.

of.this.copyright.protection.technology.must.be.authorized.by.Rovi.Corporation.and.is.intended.for.home.and.other.limited.viewing.uses.only.unless.otherwise.authorized.by.Rovi.Corporation...Reverse.engineering.or.disassembly.is.prohibited. Blu-ray.

Disc'.and. Blu-ray.Disc'.logo.are.trademarks..English.Manufactured.under.license.from.Dolby.Laboratories..Dolby.and.the.double-D.symbol.are.trademarks.of.Dolby.Laboratories.Manufactured.under.license.under.U.

S..Patent #'s: 5,451,942; 5,956,674; 5,974,380; 5,978,762; 6,226,616; 6,487,535; 7,392,195; 7,272,567; 7,333,929; 7,212,872 & other U.S. and worldwide patents issued & pending. DTS and.the.Symbol.are.registered.trademarks, & DTS-HD, DTS-HD Master Audio \ Essential.and.the.DTS.logos.are.trademarks.of.DTS,Inc.Product.includes.software.©DTS,Inc.All.Rights.Reserved..BONUSVIEW TM 'BD-Live'.and.the.'BONUSVIEW'.are.trademarks.of.Blu-ray.

Disc.Association.'AVCHD'.and.the.'AVCHD'.logo.are.trademarks.of.Panasonic.Corporation.and.Sony.Corporation.DVD.Video'.is.a.trademark.

of.DVD.Format/Logo.Licensing.Corporation... Notice for Trademark HDMI, the HDMI logo and High-Definition Multimedia.Interface.are.

trademarks.or.registered.trademarks.of.HDMI.Licensing.LLC.in.the.United.States.and.other.countries..Oracle.and.Java.are.

registered.trademarks.of.Oracle.and/or.its.affiliates.Other.names.may.be.trademarks.of.their.respective.owners.

2.Your.Product.Regions.Codes.Both.the.Blu-ray.Disc.player.and.the.discs.are.coded.by.region..These.regional.codes.must.match.in.order.to.play.the.disc..If.the.codes.do.not.match,the.disc.will.not.play.The.

Region.Number.for.this.Blu-ray.Disc.player.is.described.on.the.rear.panel.of.the.

Blu-ray.Disc.player.Region.DVD.discs.that.can.be.played.Region.North.America,Central.America,South.America,Korea,Japan,Taiwan,Hong.Kong.and.South.East.Asia.



[You're reading an excerpt. Click here to read official TOSHIBA BDX-1100-KB user guide](http://yourpdfguides.com/dref/3873130)
<http://yourpdfguides.com/dref/3873130>

Europe, Greenland, French territories, Middle East, Africa, Australia and New Zealand.

BD discs that can be played U.S.A. and Canada regions U.K., Europe regions and Japan Asia Pacific, Taiwan, Korea ALL ALL ALL ALL ALL ALL 1 2 3 4 5 6 India, China, Russia, Central and South Asia. Australia, New Zealand, Latin America Russia and India regions China, Calcos Islands, Walls and Futuna Islands Feature highlights High-Definition entertainment Watch high-definition content disc with HDTV (High Definition Television). Connect.it.through.

a.high.speed.HDMI. cable.(1.3.or.category.2).

.You.can.enjoy. excellent picture quality up to 1080p resolution.
with.the.frame.rate.of.

24. frames.per.second.with.progressive.scan. output. BD-Live Connect.this.

player.to.the.movie.studios. website via the LAN jack to access a variety of up-to-date content (e.g. refreshed previews and exclusive special features). Blu-ray

Disc Java Blu-ray.Disc.

Java(BD-J).Application The.BD-ROM.format.supports.

Java.for. interactive.functions..

"BD-J".offers. content.providers.almost.unlimited. functionality.when.creating.interactive.

BD-ROM.titles. English Product overview English Main Unit 8 7 6 5 4 3 2 1 NO a b c d e f g h Control SD.card.slot 1 B/X x Display.panel IR.Sensor Z

Disc.compartment Function Insert.an.SD.

card Turns.the.power.on.or.

restores.the.unit.to.the.

standby.mode. Playback/Pause. Stop.play. Show.information.about.the.current.

status.of.this.unit. Point.the.remote.control.at.the.

IR.sensor. Open.or.close.

the.disc.compartment. Loads.a.

disc.into.the.disc.drive. 1 2 3 4 5 6 NO a b c d e f Control AC.power.cord COAXIAL.jack ANALOG AUDIO OUTPUT jacks VIDEO.OUTPUT.

jack HDMI OUTPUT jack LAN jack Function Connects.to.a.standard.AC.outlet. Output.digital.audio.signals.

when.connecting.the.coaxial.digital.

cable. Outputs audio signals to a connected TV or AV amplifier. Output.video.signals.

to.a.connected.TV. Outputs video/audio signals to a connected TV, monitor or AV amplifier. Connect to a TV, monitor or AV amplifier equipped with HDMI input. Use.this.to.connect.

to.a.network.with.an.always-on.broadband.connection..It.

is. reserved.for.future.usage.

of..BD-Live.. Remote Control REMOTE SIGNAL EMITTER · Point remote control to the sensor on the front panel ON / STANDBY · To switch the BD player to ON or stag.

back MP3/JPEG/MPEG4 files stored in the card. 1..Connect.a.coaxial.cable.from.the. COAXIAL.

jack.on.this.product.to.the. COAXIAL.jack.on.the.

device. Option 2: Connect to an analogue stereo system AUDIO IN 1. Gently push the SD card, with its label side facing up, into the SD card slot until it clicks. Notes: - Insert only SD Card to the SD card slot on this product. - When you enjoy BD-live bonus content, as your local storage, use a 1 GB or larger SD Card.

- TOSHIBA does not guarantee 100% compatibility with all SD Cards. Connect Power 1..Connect.the.
AC.power.cable.to:-the.wall.

socket.The.product.is.ready.

to.be.set.up.for.

use. Notes: Before connecting the AC power cord, ensure you have completed all other connections. Risk of product damage! Ensure that the power supply voltage corresponds to the voltage printed on the back of the unit. The type plate is located on the back of the unit. 1.

.Connect.the.audio.cable.from.the. analogue.AUDIO.OUT.

jacks.on.this.product. to.the.audio.input.jacks.on.

the.system. Option 3: Connect to network Connect.this.product.

to.the.network.to. enjoy.

BD-Live.bonus.content. 1..Connect.the.network.cable.from.

the.LAN. jack.on.the.product.to.the.LAN.jack.

on.the. network.system. English 4 Preparation English 10 Always.

follow.the.instructions.in.this.

chapter. in sequence. Note: - Use of controls or adjustments or performance of procedures other than herein may result in hazardous radiation exposure or other unsafe operation. Setting up the player Find the correct viewing channel Iprevious. chapter.or.track..Each.press.

of.this.button. will.allow.you.to.skip.a.chapter.

or.track.till. the.beginning.

of.the.disc. Press.of.

NEXT.>.button.during.playback. will.allow.you.to.skip.

the playback to next chapter or track. Slow Forward 1..Press.
=B.during.normal.playback..
The.slow.forward.speed.is.

1/16.in.default. 2. To change slow forward speed, press =B. repeatedly, and the slow forward speed will be changed in the following sequence: 1/16, 1/8, 1/4, 1/2, normal. 3..To.exit.

slow.forward.mode.and.return.to. normal playback, press B/X. Step Forward Use.this.feature.
to.help.you.to.enjoy.
the.video.frame.by.frame.

1..Press.B/X during normal playback, then playback.will.change.to.pause.state. 2.

.Press.=B.repeatedly.to.advance.the.picture.frame.by.
frame.. 3..Press.

B/X.to.resume.normal.playback.

HDMI When there is file or disc being played, it is not.allowed.to.switch.resolution.through.the.HDMI.button.of.

the.Remote.Control. 11 English Advanced Playback DISPLAY Press.this.button.and.the.screen.will.
display.some.information.about.disc,such.as: Title number, Chapter number, Track number, Elapsed Time, Mode, Audio, Angle, and
Subtitle.languages..Press.
this.button.again.to.turn.

off.the.information.display. During DVD/CD playback, you may edit the chapter.and.track. REPEAT Press.REPEAT.repeatedly.

to.select.different.repeat.modes.. DVD:Repeat Chapter, Repeat Title, and All. VCD.PBC.Off/CD/JPEG/MP3:Repeat.
Track.and.All.A-B.To.play.
certain.section.within.the.video.

or.song, press A-B button to set the start-point. Then, press A-B button again to set the endpoint.and.complete.the.setting..The.selected.

section.will.be.played.repeatedly.. Press.A-B.button.the.
third.time.to.cancel.this.
function. The.end.point.cannot.
be.set.until.5.seconds.of.playback.has.elapsed.from.

the.start.point. SEARCH During playback, press SEARCH button to edit Title, Chapter, and Time. Press. / .and.OK.button.on.
the.remote.control.to.select.Title,Chapter,or.Time. Then press.
the.numeric.buttons.or. / .
and.then.press.OK..The.playback.will.skip.to.

the.desired.location. For Time Search, press / .to.select.Title.or.Chapter.time.
search. SUBTITLE Press.this.button.repeatedly.
and.the.screen.will.display.
"X/XX.XXX".or."Off"..The."X". indicates.the.current.

number.of.this.language; "XX" indicates the total number of language; "XXX" indicates the language. The.number.of.available.languages.depends.
on.the.disc. RETURN Press.this.
button.to.return.to.the.

previous.on-screen.menu.in.setup.menu.such.as Information, Parental Control, Country Code etc.. During MP3/JPEG/VIDEO playback, press return once,
it will return back to Media Center.

page. During.VCD.disc.playback.and.PBC.On.is.selected, press the button to return to PBC Menu.

ANGLE During playback, press this button to change the.angle.of.the.picture.

.The.screen.will.display"Angle X/X.

"The first "X" indicates the current number of angle, and the second "X" indicates.total.number.of.angle. Not.all.BD.or.DVD.

has.the.multi-angle.feature..The.screen.will.take.around.

5.seconds.to.change. TOP MENU You may press this button at any time, and the.
BD.or.DVD.video.disc.

playback.will.pop.up.the.disc.menu. POP MENU/MENU During Blu-ray Disc playback, press POP MENU/MENU to display the disc title, and the
playback.will.not.

be.stopped.even.the.menu.is.on.the.screen. 1.
.Press.the.///.buttons.

to.select.an.option, then press OK to confirm. 2..

Press.POP.MENU/MENU.to.close.the.menu.. During DVD playback, press POP MENU/ MENU.to.

open.the.disc.menu.. During VCD playback, press POP MENU/ MENU.to.switch.PBC.On/Off.

During displaying SD card and Data Disc file content in media center, press POP MENU/ MENU to add the Photo/Music/Video files to the.



[You're reading an excerpt. Click here to read official TOSHIBA
BDX-1100-KB user guide
http://yourpdfguides.com/dref/3873130](http://yourpdfguides.com/dref/3873130)

playlist. 1.Press. / / / .

buttons.to.select.an. option.under.the.Photo/Music/Video.files.

2. In the file browser, press .to.select.the. file(s) to be added to the playlist. " " will appear beside the selected files. 3. Press POP MENU/MENU button, a pop up menu will appear, then press / .and.

OK. button.to.select."Add.to.Playlist".to.add.the.

files.to.the.Playlist."Select.all"and."Clear.all"options.are.also.available.

.Select."Cancel".to. exit.

the.pop.up.menu. All the selected files will be added to the. "Playlist".folder..You.can.

play.or.delete.the. files.in.the.playlist.Press.POP.MENU/MENU.to.delete.

the. selected.files.in"Playlist"SETUP Press the SETUP button, and the screen will display some information about the player, such.as: ·General.Setting ·Display.Setting ·Audio.

Setting ·System.Information PROGRAM. During CD/DVD/VCD playback, you can press this button to edit the sequence of the playlist. BOOKMARK During VCD/DVD disc playback,press the BOOKMARK button to add the bookmark; press.and.

hold.for.a.few.seconds.to.display. the.list.of.

bookmark.which.you.added.before. on.the.screen, then you can press the OK button.to.select.the.bookmark.

or.CLEAR. button.to.delete.

the.bookmark. English 1 AUDIO Press.AUDIO.button.

on.the.remote.control.to. select.the.audio.streams.that.

set.within.the. Blu-ray.or.DVD.disc. The.screen.will.

display: AUDIO: .X./XX.XXX.

XXXX. "X".-the.Current.

Audio.Stream.Number "XX"-.The.total.number.of.Audio.Stream "XXX".

-Audio.Language. "XXXX"-.Audio.Technology MC Press this button to play media files in the SD card. ZOOM 1..Press.

ZOOM.button.repeatedly.to.Zoom.

in/ out.playback.in.the.video.

Zoom.mode.:.Zoom.2x.->.Zoom.3x.->.

Zoom. 4x.->.Zoom.1/2.->.Zoom.1/3.->.Zoom.

1/4. DIGEST During.playback.of.JPG disc, press DIGEST to.

view.a.page.of.12.

thumbnail.images. -.Use. / / / .to.select.an.image. Press.

OK.to.view.the.selected.image.in.fullscreen and subsequent images will be displayed.one.after.

another.automatically. -.Press.PREV.

./NEXT. .to.

view.the. previous.or.next.thumbnail.screen. PIP AUDIO Press.PIP.AUDIO.

button.to.open.the. secondary.audio.of.secondary.video(PIP's. sub-window.

video).. OSC Press.OSC.to.

open.On.Screen.Control.menu.

during playback. In this menu, you can make some playback-related.control. The.on.screen.control.contains.following.

items: [Title]:The.title.in.current.playback/titles.in. total..Select.

your.desired.title.to.playback.

[Chapter]:The.chapter.in.current.

playback/ chapters.in.total..Select.your.desired.chapter. to.playback.

[Time]:View.the.elapsed/remaining.playback. time.of.title/chapter..Use.

./to.view:.the. elapsed playback time of title, the remaining playback time of title, the elapsed playback time of chapter, and the remaining playback time. of.chapter. [Mode]:.Select.playback.

mode.among. shuffle, random, and normal. [Audio]:The.BD/DVD.disc's.soundtrack. language..

Use.. /to.view.the.audio. available.in.the.disc.

and.select.your.desired. Audio.

type. [Angle]:The.angle.view.

of.current.playback/ the.angles.in.total..Please.reference. Playback>Angle.

to.see.more.detailed.info.. Use. /to.select.your.

desired.angle.view.. [Subtitle]:.

The.Subtitle.in.current.playback.

. Use. /to.view.the.subtitles.available.in. the.disc.

and.select.your.desired.subtitle.type. or.turn.it.off.
· [Subtitle.Style]:.When.you.
play.the.BD.or.DVD.
disc and if it has external subtitle, you will see it.in.OSC.menu. [Bitrate]:Use. / to.select.your.desired.Bitrate.

[Still.Off]:.Close.the.Still.feature.of.DVD.disc..
For some DVD discs, a certain video picture will. be. freeze. as. a.
still. picture. during. the. process.
of.playback.to.let.user.better.view.the. certain picture. To continue playback, select Still.

Off... [Ins. Search]:. Instant. skip. 30. seconds. for.
search. [Ins. Replay]:. Replay. the.
content. from. 10. seconds.before.

Tip: - The specified operation for each item will vary with disc types. And some items are available only when the disc is supportable. Blu-ray Disc Bonus View Playing.Secondary.Video.(Picture-in-Picture). and.Secondary.Audio.is.

for.Blu-ray.Disc.only.. Secondary.video.can.be.played.
from.a.disc. compatible.with.
the.Picture-in-Picture.(PIP). function. For the playback method, refer to the instructions.
for.the.disc. 1..Turn.on.secondary.video.by.

pressing.the. PIP.button. 2..Press.the.PIP.AUDIO.
button.to.select.the. secondary audio, and select an option except Off.
The secondary audio is opened, you can hear.the.disc.secondary.video.
sound.. In order to hear the secondary audio, the PIP feature.on.the.disc.must.be.turned.on.

3..Press.the.PIP.AUDIO.button.again.to.turn.
off.the.secondary.video. Primary video This.
function.is.not.available.when.

the. primary video is played in Search, SlowMotion, or Frame-by-Frame or Fast Forward/ Reverse.mode. To listen to the secondary audio, the digital audio output must be set to "Bitstream", "Re-encode" or "PCM". Otherwise, only the primary.audio.can.be.heard. Notes: -Not all the BD discs can support this function.

-High Definition PIP (Second Video) is not supported. Secondary video with Secondary Audio 1 English 6 Customizing English 1 This. section. describes. the.
various. setting. option.of.this.

BD.player.. If the setup option is grayed out, it means the. setting.
cannot. be. changed. at. the.
current.state. General Setting 1..Press.SETUP.button.on.the.remote.

control.The.Setup.Menu.appears. ... General Setting ..
. System Language Playback Security Network Screen Saver Disc Auto Playback CEC Easy Setup Load Default On On On More... More.
.. Move cursor key to select menu option then use "OK" key to select SETUP Exit 2. Press to select an option, then press .to.
access. 3. Press / to.select.a.setup.option.and press .. 4.

Select.the.setting.you.wish.to.change and press OK to confirm. - Press to.return.to.
the.previous.menu. [System] To.change.
the.following.system.option.to.
personalize.your.BD.player. · [Screen Saver] Turn.On.or.Off.the.screen.

saver.mode. It.helps.to.protect.the.TV.screen. {.
On.}..Set.the.
screen.saver.active. after.approximately.
10.minutes.with.no. operation. -.The.BD.player.will.

switch.to.standby. mode.if.there.is.no.operation.after.
the. screen.saver.is.engaged.
for. approximately.10.minutes. {.
Off.}..Turn.off.the.screen.saver. mode..

· [Disc Auto Playback] Turn.On.or.Off.the.disc.automatic. playback.switching.mode.
{On}..The.disc.playback.
automatically. after.loading. {Off}..
Turn.off.disc.auto.playback. mode. · [CEC] This.player.supports.REGZA-LINK.

which. uses.the.HDMI.CEC.(Consumer. Electronics.Control).protocol..
You.can. use.one.single.
remote.control.to.control. all.

REGZA-LINK-compliant devices that are connected through HDMI connectors. {On}.

Turns on REGZA-LINK features. -With CEC on, during TV standby with the BD player on, pressing SETUP, PLAY/ PAUSE will power on the TV. {Off}. -Disables REGZA-LINK.

*features. · [Easy Setup] Re-configure some settings. It is the same as "Load Default".
of steps 4-8. Tip: For setting OSD and TV resolution and TV aspect. · [Load Default] Reset all settings of BD player.*

to initial default state. -Follow the instruction on the TV screen to confirm the default setting operation. 1..

Select Load Default. 2..A.

dialogue box pops up shown as below. Select OK.

. Load Default Do you want to load default? OK Cancel 3. It may take awhile when loading default is in progress. Please wait.

.. Load Default Loading default, please wait..

30% 4. TV will display as follow: Welcome to the Toshiba BD Player Setting Wizard. Some simple settings are suggested before you begin.



[You're reading an excerpt. Click here to read official TOSHIBA](#)

[BDX-1100-KB user guide](#)

<http://yourpdfguides.com/dref/3873130>

You can also access detailed settings from the Setup Menu. OK Next 5.

Press OK, enter language setting. . Press/ to.select.a.language.option. Choose an OSD language before starting. The language selected will be applied not only here but also in other OSD windows, menus etc. English Previous OK Next 6.

Press OK, enter Resolution setting. . Choose a resolution that fits your TV. Change will be applied immediately, you have 15s to determine whether to save the setting or rollback to prior resolution. Better performance will be provided by a HDMI connection! Auto 480I/576I 480P/576P 720P 1080I 1080P Previous OK Next Press.

/ to.select.an.option..

Press.OK. Select."Yes".or."No".using./ Note: -When the player is connected to both VIDEO OUTPUT jack and HDMI OUTPUT jack, resolution is set to 720p/1080i/1080p, there will be no video output through VIDEO OUTPUT jack. Resolution has been changed! 14s Does everything looks all right with this resolution? Press Yes if you want to apply it.

Press No to rollback to previous one. Yes No Previous OK Next 7. Press OK, enter Aspect ratio setting. . Choose an aspect ratio that fits your TV. The change will be applied in the next page. Determine whether to save the setting or rollback to the previous aspect ratio. 16:9 Full 16:9 Normal 4:3 Pan&Scan 4:3 Letterbox Notes: - If set [Disc Auto Playback]to [Off], after you insert the disc that contains the upgraded information to upgrade system, you have to start upgrade from this option of SETUP Menu. - If the upgrade file package did not pass the verification, error prompt is displayed , check the package again (such as the package is not complete) - Make sure the firmware version is not an old version. - When you upgrade the system using SD card, you should make a new folder named UPG_ALL, and copy the upgrade file into this folder.

· [Disc Auto Upgrade] Turn.On.or.Off.the.

disc.automatic.upgrade. switching.mode.

{On}. -. Start. upgrading. from. the. insert. disc. {Off}.-.

Disable.disc.auto.upgrade.mode. · [External Memory] External. Memory. would. be. used. in. BDLive.function..When.

you.plug.in.the.SD.

card.which.has.at.least.1GB.free.space.to. play BD-Live function, the BD system would.

make. a. directory. named. BUDA. automatically.. Information. will. display.

the.Free.size. 1..

Press.OK. 2..Follow.

the.instruction.on.the.TV. screen.to.select.{Information}. .

.. General Setting ... System Language Playback Security Network Screen Save Information Disc Auto Playback CEC Free size is : 0MB Previous OK Next Press./ to.select.an.option.

.Press.OK. Setting wizard is complete! Now press the OK button to finish and return to the Setup Menu. Off On On On More.

.. Erase Disc Auto Upgrade Load Default Previous OK Finish Move cursor key to select menu option then use "OK " key to select RETURN Return 8. Press OK to return to [General Setting] ..

Press.OK.to.return.to.[General.Setting]. Menu. · [Upgrade] For.software.

upgrades.to.enhance. performance, you could select the following.upgrade.method.and.start.to. upgrade.

{Disc.}/(SD CARD). Upgrade.the.

software.from.the.disc.or.

SD.card. 1..Insert.the.disc.or.connect.the.

SD. card which contains the upgrade file package. 2..Follow.the.instruction.on.the.TV.

screen to confirm upgrade operation. -.The.system.will.

reboot.after.5.seconds. .

or.OK.key.is.pressed. 3.Press OK to select "Erase", the data in the.BUDA.folder.will.

be.cleared. [Language] Select the OSD(On-Screen Display), set up Menu, Audio, Subtitle default language for the.player. ... General Setting ...

System Language Playback Security Network Move cursor key to select menu option then use "OK " key to select SETUP Exit OSD Menu Audio Subtitle

English English English English · [OSD] Select.the.default.on-screen.display.

language. 1 English Select.the.menu.language.

· [Audio] Select.the.default.audio.language. · [Subtitle] Select.the.default.subtitle.language.

[Playback] ... General Setting ... System Language Playback Security Network Closed Caption Angle Mark PIP Mark Secondary Audio... Last Memory On On On On · [Menu] · [Closed Caption] Move cursor key to select menu option then use "OK " key to select SETUP Exit playback.

from.the.memorized.point.next.

time.. {On}..Active.

Last.Memory.feature. {Off}..Disable.Last.Memory.feature. Note: -Not all the BD discs can support this function.

· [PBC] VCD2.0.has.PBC.control.(Playback. Control) menu, which allow you to interact.with.the.system.

via.menu.. {On} Display playback control menu, use.NUMBER.

keys.to.select.desired.option.

{Off}..Hide.playback.control.menu.and. start.playback.from.

track1.automatically. [Security] ... General Setting ... System Language Playback Security Network Move cursor key to select menu option then use "OK " key

to select SETUP Exit Change Password Parental Control Country code More.
. More... More.
.. English Allow people who
are deaf or hearing impaired, to have access to television programming by displaying the audio portion.

of a television programme as text on the screen. {On}.
. Display the Closed Caption.
. {Off}.. Hide the
Closed Caption. · [Angle Mark] Some BDs/DVDs contain the scenes recorded with multiple angles, which allow you to enjoy

the videos with your desired angles, therefore the angle mark is displayed only when the BD/DVD
disc is supportable for multi-angle
and Angle Mark is set
to ON. {On}.. Display the angle mark. {Off}..

Hide the angle mark. · [PIP Mark] The Picture-In-Picture (PIP) mode
display two pictures on the
TV screen at the same
time, the full screen picture is called Main Window and the small inset window is called Sub Window.

. The PIP mark is displayed when in PIP mode.
and PIP Mark is set
to ON. {On}..
Display the PIP mark. {Off}.. Hide the PIP mark.

Note: -High Definition PIP (Second Video) is not supported. · [Secondary Audio Mark] {On}.. Display Secondary Audio Mark. {Off}.. Hide
the Secondary Audio Mark. · [Last Memory] If
you open the disc tray
or switch this BD player to standby state during normal

playback, the BD Player can memorize the end playing point, the BD player will start · [Change password] Follow the instruction on the TV set or
change the
password for locked discs and
play restricted BDs/DVDs. ..

· General Setting ... System Language Playback Security Network Screen Save Off Change Password Disc Auto Playback On Please enter current password:
CEC On On More... Disc Auto Upgrade Load Default Move cursor key to select menu option then use "OK " key to select RETURN Return 1. Use

NUMBER keys to enter four digit old password. The
default password is "0000". 2.
. Enter the new password .

.. General Setting ... System Language Playback Security Network Screen Save Off Change Password Disc Auto Playback On CEC New password : On On
More... Disc Auto Upgrade Load Default Confirm password : Move cursor key to select menu option then use "OK " key to select RETURN Return 3. Enter
the new password again to confirm.

· [Parental Control] Restricts access to discs that are unsuitable for children..
These discs must be recorded
with rating 1.. Press
OK. 2.. Use NUMBER keys to enter.



[You're reading an excerpt. Click here to read official TOSHIBA
BDX-1100-KB user guide
http://yourpdfguides.com/dref/3873130](http://yourpdfguides.com/dref/3873130)

the password.

1 ... General Setting ... System Language Playback Security Network Screen Save Off Parental Control Disc Auto Playback On Enter password: CEC On On More... Disc Auto Upgrade Load Default Move cursor key to select menu option then use "OK" key to select RETURN Return 3.

Select a rating level, then press OK. ... General Setting .

.. System Language Playback Security Network Screen Save Off Parental Control Disc Auto Playback On CEC Off [1] KID SAFE Select level: On On Disc Auto Upgrade G [2] Load Default More...

Off RETURN Return Items G PG PG-13 PGR R NC-17 ADULT Description All children and general guidance Parental guidance Parental guidance for children under 13 Parental guidance Recommended Restricted viewing No one 17 and under allowed Adult only KID SAFE Safe for kids Notes: - Rated discs above the level you set in [Parental Control] require a password to be entered. - The ratings are country-dependent. To allow all discs to play, select 'Off'. [Country Code] This ensures that you will be able.

to see the scenes intended for your current residential..

Country/Area. Use NUMBER Keys to enter your password, then you can choose.

your Country/Area. [Network] ...

General Setting ... System Language Playback Security Network Internet Connection Information Connection Test IP Setting BD-Live Connection Permitted Enable 3. Select [IP Setting] in the menu, then press OK to select [Auto]..

An IP address is obtained automatically. If no IP address is obtained, select [Manual] to input IP Address, Subnet Mask, Default Gateway, DNS and press OK to re-connect.

again to the network..

It will try to obtain.

the IP address again. 4. Press RETURN or press.

OK to exit. Notes: - A contract with the provider is needed to connect to the Internet. - This player does not support automatic detection of cross-cables. Use the straight (standard) LAN cable. - Loading BD-Live content from the internet may take some time, depending on the file size and the speed of the internet connection. [Internet Connection] {Enable}..Enable.

connection to internet. {Disable}..

Disable connection to internet..

[Information] Display all Network Information.. [Connection Test] Display Network connection status information.

[IP Setting] {Auto}..Auto obtain network information. {Manual}..Manual.

setup network information. [BD-Live Connection] {Permitted}..

During playback of BD-Live disc, the disc may automatically download all.

information from appointed network. {Partial Permitted}..During playback of BD-Live disc, the disc may automatically download partial.

of the information from appointed network. {Prohibited}..Disable downloading.

information from network. To enjoy BD-Live bonus contents, set up the network.

connection. Note: - Ensure that the network cable is properly connected and the router is switched on. 1. Connect.

the BD player to the broadband modem or router. 2.

In the Setup menu, select [Network], then press.. Move cursor key to select menu option then use "OK" key to select SETUP Exit 1 English Display Setting 1. Press SETUP [General Setting] menu is displayed. 2. Press to.

select [Display Setting], then press...

3. Select an option, press to access ..

Display Setting... TV Video Process Motion Video... TV Screen Resolution Color Space HDMI Deep Color HDMI 1080P 24F Move cursor key to select menu option then use "OK" key to select 16:9 Normal Auto YCbCr422 Off On SETUP Exit 4. Press / to select.

a setup option and press .. 5. Select the setting you.

wish to change and press OK to confirm. - Press to.

return to the previous menu.

- Press SETUP to exit the menu.. [TV] [TV Screen] Select the screen.

format according to how you want the picture to appear.

on the TV. {16:9 Full}..

for a disc with the.

aspect ratio of 4:3, the output video is stretched into 16:9 full screen. {16:9 Normal}..for a.

disc with the aspect ratio of 4:3, the output video is resized vertically to match what will be.

seen on the display. {4:3 Pan&Scan} for standard TV, Display.

a wide picture on the.

entire screen and cuts off the redundant portions. {4:3 Letterbox} for standard TV, Display a.

wide picture with two black borders on the top and.

bottom of 4:3 screen. [Resolution] Select.

a video output resolution that.

is compatible with your TV display capability. {Auto}..Select.

the most suitable resolution according to the TV.. {480i/576i}, {480P/576P}, {720P}, {1080i}, {1080P}.

.Select a video resolution setting that is best supported.

by the TV. See TV manual for details. Note: -When resolution is set to 720p/1080i/1080p: (1) If only CVBS connected, the resolution of CVBS video output will be set to 480i/576i automatically. (2) If HDMI and CVBS are both connected, there will be no CVBS video output, instead, a message will be shown as follows: Out Of Range: Check Display Resolution · [Color Space] Select a predefined Color space of picture.

{RGB}..select.RGB.Color.space. {YCbCr}..select.YCbCr.

Color.space. {YCbCr422}..Select.

YCbCr422.Color.space. {Full RGB}..select.Full.RGB.Color.space. · [HDMI Deep Color] This feature is available only.

when the display device is connected by a HDMI cable, and when it supports deep Color feature.

{30 bits}..Output.30.bits.

Color. {36 bits}..Output.36.

bits.Color. {Off}..Output.standard.24.bit.Color. Note: -When the color space is "YCbCr422", even if HDMI Deep Color is set to 30bits/36bits, it is not output with Deep Color.

· [HDMI 1080p 24F] {On}..Enable.1080p.24F.video.resolution.setting. {Off}..Disable.1080p.24F.video.resolution.

setting. About HDMI 1080p 24F Notes: If you want the 24Hz output, it should fulfill below 3 conditions: 1.TV supports the 24Hz display; 2.Player choose the 24Hz option in the setup menu; 3.Media must be the 24Hz video.

English 1 Notes: -This resolution becomes effective only when the playing BD-Disc contents are Film source. -During HDMI 1080p 24F playback, there will be no composite output. [Video Process] ... Display Setting... TV Video Process Motion Video..

. Video Adjust Sharpness More... Low Move cursor key to select menu option then use "OK" key to select SETUP Exit {Brightness}..press./to.adjust the brightness of display, goes left means dark and right means

bright. {Contrast}..press./

to.adjust the contrast of display, goes left means low contrast and right means high contrast.

{Hue}..press./to.adjust the Hue of display, goes left means low hue and right

means high hue. {Saturation}..-

press./to.adjust the saturation of display, goes left means

low Saturation and right means high saturation. 3..Press.

RETURN to exit. Brightness Contrast Hue Saturation 1. Press SETUP [General Setting] menu is displayed. 2. Press to

select [Audio Setting], then press...

3. Select an option, press to access...

. Audio Setting... Audio Output Spdif HDMI Down_samp DRC Move cursor key to select menu option then use "OK" key to select PCM PCM 48K Off SETUP Exit Change RETURN Exit · [Sharpness] Select the level of sharpness: High, Medium, Low {High}..Select High sharpness level {Medium}.

..Select Medium sharpness level {Low}..Select Low sharpness level [Motion Video Process] .



[You're reading an excerpt. Click here to read official TOSHIBA](http://yourpdfguides.com/dref/3873130)

[BDX-1100-KB user guide](http://yourpdfguides.com/dref/3873130)

<http://yourpdfguides.com/dref/3873130>

.. Display Setting...

TV Video Process Motion Video... Video Mode Move cursor key to select menu option then use "OK" key to select SETUP Exit · [Video Mode] Select the output mode of video, options include: Standard, Vivid, Smooth, these can change the output display. {Standard}.output.video.signal.without.any.processing.

and.in.standard.mode. {Vivid}.output.video.signal.in.vibrant.
color.mode. {Smooth}.output.video.
signal.in.smooth. mode. 4.

Press / to select a setup option and press .. 5. Select the.

setting you wish to change and press OK to confirm. -. Press to return to the previous menu. -. Press SETUP to exit the menu. [Audio Output] · [Spdif] Select.

the output mode of COAXIAL jack, options include Bitstream, PCM, Re-encode and Off. {Bitstream}..

Output digital signal without any processing. {PCM}.. Output digital signal with processing, only two channels export. {Re-encode}..

Auto select signal type from.

COAXIAL jack according to the Audio stream on disc. {Off}.

.No output for S/PDIF. · [HDMI] Select the output mode of HDMI Out jack, options include Bitstream, PCM, Re-encode and Off. {Bitstream}.. Output HDMI digital signal without any processing. {PCM}.. Output HDMI digital signal.

with processing, only two channels export. {Re-encode}.. Auto select signal type from HDMI Out jack according to the Audio stream on disc. {Off}..

No output for HDMI. · [Down_samp] Select the digital audio signal sampling.

frequency. {48K}.. For discs recorded at sampling rate of 48 kHz. {96K}.. For

discs recorded at sampling .

rate of 96 kHz. 1 English · [Video Adjust] Select a predefined setting of the video. 1.. Press OK.

. 2.. Press / to adjust the video Brightness, Contrast, Hue and Saturation. Audio Setting {192K}.. For discs recorded at sampling rate of 192 kHz.

· [DRC]. Select the Dynamic Range.

Control mode which makes it available to listen to a

movie at a low volume without losing sound clarity. {Off}.

.Non-dynamic range compress..

{On}.. Dynamic range compress.

{Auto}. Adjust the DRC according to input audio. The

setting of Auto is effective for Dolby TrueHD. English 0 System Information 1. Press.

SETUP [General Setting] menu is displayed. 2.

Press to select [System Information], -. The current

software version and MAC address display -. Press to return to the

previous menu. -. Press SETUP to exit the menu. ..

System Information ... Software version: V XX MAC: E8-9D-87-XX-XX-XX Move cursor key to select menu option then use "OK" key to select SETUP Exit 7 Specification.

Playable media This product can play: · BD-Video, BD-R/RE2.

0 · DVD, DVD-Video, DVD+R/+RW, DVD-R/-RW, DVD+R/-R DL (Dual Layer) · Video CD/SVCD · Audio CD, CD-R/CD-RW · AVCHD, AVCREC · SD card Video Signal system: PAL/NTSC Composite video output: 1Vp-p.

(75 ohm). HDMI Output: 480i/576i, 480p/576p, 720p, 1080i, 1080p, 1080P/24F. Audio · 2 Channel analogue output - Audio L&R : 2 Vrms (> 1 kohm) Signal-to-noise Ratio 95 dB THD+N 1kHz -85 dB Dynamic Range 1kHz 85 dB Crosstalk 1kHz -95dB · Digital output.

(Coaxial): 0.5 Vp-p (75

ohm) · HDMI output LAN · LAN terminal..

. 10BASE-T/100BASE-TX SD · SD, SDHC · mini-SD, micro-SD, micro-SDHC (adapter is necessary). · Maximum size: 32GB · Supported file systems: FAT16/32 · Type of files supported: MP3/JPEG/MPEG4 · Maximum.

No. of folders supported: 1000. MP3 tracks · Supported file extension: '.mp3'. ·

Supported audio codec: MP3 ·

ISO format · Supported corresponding bitrate:.

8kbps-320.kbps Supported sampling frequencies :.... 32kHz,44.1kHz, 48kHz JPEG Supported file extension:'.jpg'

or.'.jpeg'.JPEG/ISO.format Does.not.support.Picture.

CD Main Unit Power.supply.rating:.

...110V-240V.50/60Hz .

.Power.consumption:.20W Power.consumption.in.standby.mode:.

<IW Dimensions.(w.x.h.x.d):.360.x.

54.x.232.(mm). .

.Net.Weight:.1.73.

kg Operating.temperature:.5°C.to.35°C Operating.humidity:.

Less.than.80.%(no.

condensation) Accessories supplied Remote.control.and.

Size.'R03'.carbon...

...zinc.batteries.(Two) Simple.IB 1 English 8 Troubleshooting If you experience any of the following difficulties while using this unit, check the list below before consulting.

your.nearest.TOSHIBA.dealer. Problem Tip No.reaction.to.the.remote. Connect.

the.product.to.the.power.

outlet. control. Point.the.remote.

control.at.the.product. Insert.the.batteries.correctly. Insert.new.

batteries.in.the.remote.control. No.video.output..through.

Set.Resolution.of.HDMI.to.

480i/576i.or.480p/576p. VIDEO.OUT.

jack. No.video.signal.on.the. display.device. Turn.on.

the.TV. Set.the.TV.to.the.correct.external.input.

Select.the.correct.video.resolution.

Set.TV.System.of.TV.

correctly. No.audio./video.signal. on.the.display.device.

via. HDMI.cable. No high-definition video signal.on.the.TV. If.the.unit.

is.connected.to.the.unauthorized.

display.device.with. an HDMI cable, the audio/video signal may not be output. Does the disc contain high-definition video? High-definition video.

is.not.available.when.the.disc.does.not.contain.it.

Does the TV support high-definition video? High-definition video is.not.available.when.the.TV.does.not.support.it.

No.audio.signal.from.the.

loudspeakers.of.the..TV.

Assign.the.audio.input.of.the.TV.to.the.corresponding.

video. input. English No.audio.signal.from.the. Turn.on.the.

audio.system. loudspeakers.of.the.

audio. Set.the.audio.system.

to.the.correct.external.input. system. Increase.the.volume.level.

of.the.audio.system. Cannot.play.back.a.disc. Make.

sure.that.the.BD.Player.

supports.the.disc. For DVD+RW/+R or DVD-RW/-R, make sure that the disc is finalized. Clean.

the.disc. Cannot.play.back.JPEG. files from a disc. Cannot play MP3 files from.a.disc.

POWER Make sure that the disc was recorded in the UDF, ISO9660 or JOLIET.format. Make sure that the disc was recorded in the UDF, ISO9660 or

JOLIET.format. Make sure that the bit rate of the MP3 files is between 8 and 320.kbps. Make sure that the sample rate of the MP3 files is 32kHz,

44.1kHz.or.48kHz.

Cannot find a JPEG file. Make.sure.that.the.

selected.group.(folder).does.not.

contain. more than 9,999 files for DVD, and 999 files for CD. Make sure that the file extension is .jpg, .JPG, .jpeg or .JPEG. Make.sure.that.

the.selected.folder.does.not.contain.more.than. 9,999 files for DVD, and 999 files for CD. Make sure that the file extension is .

mp3 or .MP3. When you upgrade the system with SD card, you should make a new folder named UPG_ALL, and copy the upgrade file into this.folder. When

playing a DVD disc or BD disc, press STOP button once, the player will go into stop resume mode, meanwhile you.

cannot.change.some.settings.in.

setup.menu.such.as. language subitem menu, audio, subtitle etc. If you want to change that, press STOP button twice, the player will go into full stop mode,

then you can do it. Cannot find a MP3 file. .Cannot.upgrade.

*SW Sometimes the options of setup menu cannot be selected.
English Make sure that the Blu-ray.
Disc player supports the region.
code of the DVD or BD. 9 Glossary Aspect ratio Aspect ratio refers.*

*to the length to height ratio of TV screens.
The ratio of a standard.
TV is 4:3, while the ratio of a high definition or wide TV is 16:9. The letter box allows you to.
enjoy a picture with a wider perspective on a standard.*

4:3.



[You're reading an excerpt. Click here to read official TOSHIBA
BDX-1100-KB user guide
http://yourpdfguides.com/dref/3873130](http://yourpdfguides.com/dref/3873130)

screen. Blu-ray.Disc.(BD) Blu-ray.Disc.is.a.next.generation.
optical. video disc capable of storing five times more.data.than.a.
conventional.DVD..The. large capacity makes it possible to benefit from the features such as high-definition videos, multichannel surround sound, interactive.
menus.and.so.on. BONUSVIEWTM. This is a BD-Video (Final Standard Profile or Profile 1.1) that supports interactive content encoded on the disc, such as
picture-in-picture..This.means.

you.can.play. the.primary.video.and.secondary.video. simultaneously.
Digital.Audio Digital.Audio.is.a.
sound.signal.that.has. been.
converted.into.numerical.values.. Digital.sound.can.be.transmitted.

through. multiple.channels..Analogue.sound.can. only.be.transmitted.
through.two.channels. Dolby®.Digital.
. The.system.to.compress.
digital.sound. developed.by.Dolby.Laboratories..It.offers. you.

sound.of.stereo.(2ch).or.multichannel audio. Dolby®.Digital.Plus Dolby.Digital.
Plus.is.the.next.generation.
digital.audio.compression.technology. developed.
as.an.extension.to.Dolby.Digital.. Blu-ray.Disc.supports.

7.1.multi-channel surround.sound.output. Dolby®.TrueHD Dolby.TrueHD.is.a.
lossless.coding. technology.developed.for.
next.generation. optical.discs..
Blu-ray.Disc.supports.7.1 multi-channel.surround.sound.output. DTS®.

DTS.is.a.multi-channel.surround.sound. system. By connecting to DTS decoder, you.can.enjoy.
movie.dynamic.and.realistic. sound.
like.movie.theater..DTS.
surround sound.technologies.were.developed.by. DTS, Inc. DTS-HD® DTS-HD.is.a.lossless.

coding.technology. developed.as.an.extension.of.the.original. DTS.
Coherent.Acoustics.format. Blu-ray.Disc.
supports.7.1.multi-channel. surround.
sound.output. DTS-HD.Master.Audio™ A.disc.encoded.with.DTS-HD.Master.

Audio. delivers.ALL.of.the.information.from.the. original master recording -- bit-for-bit, it's identical.to.
what.the.sound.engineers.laid.
down..Audio.doesn't.get.
any.better.than. this. HDCP High-bandwidth.Digital.Content.Protection.. This is a specification that provides a secure.

transmission.of.digital.contents. between.different.devices.(to.prevent. unauthorized.
copyright.) HDMI® High-Definition Multimedia Interface (HDMI).is.a.high-speed.
digital.interface. that.can.transmit.
uncompressed.high. definition video and digital multichannel audio. It delivers high quality picture and sound quality. HDMI is fully backwardcompatible
with DVI. As required by the HDMI standard, connecting to HDMI or DVI products.without.HDCP.(Highbandwidth.

Digital.Content.Protection).will. result.in.no.Video.or.Audio.
output. JPEG. A.very.common.
digital.still.picture.format..
A.still-picture.data.compression.system. proposed.by.the.Joint.Photographic.

Expert. Group, which features small decrease in image quality in spite of its high English compression.ratio..Files.are.recognized.by. their file extension `jpg`
or `

jpeg.` LAN.(Local.Area.Network).
A group of linked devices in a company, school.or.home..Indicates.
the.boundaries. of.a.particular.network.. Local.storage. This.

storage.area.is.used.as.destination.for. storing.additional.contents.
from.BD-Live. enabled.BD-Video. MP3 A file format with a sound data compression.
system..MP3.is.the.
abbreviation.of.Motion.Picture.Experts. Group.1.(or.MPEG-1).Audio.

Layer.3..With. the MP3 format, one CD-R or CD-RW can contain.about.10.times.more.data.
than.a. regular.CD..
PBC.. Playback.Control..
A.system.where.you. navigate.through.a.Video.CD/Super.VCD.

with on-screen menus that are recorded onto the disc.
You can enjoy interactive playback
and search. PCM Pulse Code Modulation.
A digital audio encoding system. Region code A system.

that allows discs to be played only in the region
designated. This unit only
plays discs that have compatible
region codes. You can find the region code of your unit on the product label. Some

discs are compatible with more than one region (or ALL regions.) English This document is statement purpose only. Not concerned with operation of this product. The software pre-installed in this product consists of multiple, independent software components. Each software component is copyrighted by a third party. This product uses software components that

are distributed as freeware under a third-party end-user license agreement or copyright notice (hereinafter referred to as a "EULA"). Some EULAs require that the source code of the applicable component be disclosed as the condition for distributing the software component in executable format. You can

check the software components subject to such EULA requirements on the following e-mail address: E-mail address: linux@toshiba-dme.co.jp
TOSHIBA provides a

warranty for this product you
have purchased under conditions set
forth by TOSHIBA. However, some of the software components distributed under an EULA are made available for use by the user on

the assumption that they are not copyrighted or warranted by
a third party. These
software components are licensed to
the user free of charge and therefore not covered by

any warranty within the scope of the applicable laws.
These software components are not
subject to any copyrights or
other third-party rights and are provided in "as is" c.

condition without any warranty, whether express or implied. "Warranty" here includes, but not limited to, an implied warranty for marketability or fitness for specific uses. All risks associated with the quality or performance of these software components are
assumed by the user.

TOSHIBA shall not be liable
whatsoever for any cost of repair or correction or other

incidental expense incurred in connection with a defect found in any of these software components. Unless specified under the applicable laws or in a written agreement, a party who changes or redistributes the software with consent from the copyright holders.

or based on the aforementioned
licenses shall not be held
liable whatsoever for any loss arising from the use of

or inability to use such software components. The same applies
even when the copyright holders
or relevant third parties have

been informed of the possibility of such loss. "Loss" here includes normal, special, incidental and indirect loss (including, but not limited to, the loss of data or its accuracy; loss incurred by the user or any third party; and interface incompatibility with other software). Please read each EULA for details on the use conditions and items.

that must be observed regarding these software components. The table below lists the software components pre-installed in this product, which are subject to EULAs.

The user should read
the applicable EULAs carefully before
using these software components. The EULAs are exhibited in

their original text (English) as exactly written by the respective
parties. License Information on the Software Used in This Product English Project name Linux kernel Busybox U-boot glibc SquashFS
International Components.

for Unicode OpenSSL zlib FreeType Expat CURL Independent JPEG group LIRC Project license GPLv2 GPLv2 GPLv2 LGPLv2.1 GPLv2 ICU License

*OpenSSL.License.
and.SSLey.License zlib license FreeType License Expat license curl license IJG license GPLv*

*..GNU.GENERAL.PUBLIC.LICENSE Version 2, June 1991 Copyright (C) 1989, 1991 Free Software Foundation, Inc., 51 Franklin Street, Fifth Floor,
Boston, MA 02110-1301.USA .Everyone.is.*

*permitted.to.copy.and.distribute.
verbatim.copies.of.this.license.document, but changing it is not.allowed. ..*

.....

.....

.....

*..Preamble The.licenses.for.
most.software.are.designed.to. take. away. your. freedom. to.*

*share. and. change. it. By contrast, the GNU General Public License. is. intended. to. guarantee. your.
freedom. to. share. and. change.*

free. software--to. make.



[You're reading an excerpt. Click here to read official TOSHIBA
BDX-1100-KB user guide
http://yourpdfguides.com/dref/3873130](http://yourpdfguides.com/dref/3873130)

sure.the.
software.is.free.for.all.its.users...This.

General. Public. License. applies. to. most. of. the. Free.Software.
Foundation's.software.and.to.any.
other. program. whose. authors. commit.
to. using.it...(Some.other.Free.Software.Foundation.

software.is.covered.by.the.GNU.Lesser.General. Public.License.
instead.).You.can.
apply.it.to.your. programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the

freedom. to. distribute. copies. of. free. software. (and. charge. for.
this. service. if. you. wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs;
and that.

you.know.you.can.do.
these.things. To protect your rights, we need to make restrictions that forbid anyone to deny you these

rights.or.to.ask.you.to.surrender.the.rights. These.
restrictions. translate. to. certain. responsibilities.
for. you. if. you. distribute.
copies. of. the. software, or if you modify it. For example, if you distribute copies of such a program, whether gratis or for a fee, you must
give.the.recipients.all.the.rights.

that.you.have.. . You must make sure that they, too, receive or can get the source code.
..And.you.must.

show. them.these.terms.so.
they.know.their.rights. . . We. protect. your. rights.

with. two. steps.: (1). copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.
Also, for each author's protection and ours, we

want.to.make.certain.that.
everyone.understands.that.there.is.

no.warranty.for.this.free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the
original, so that any problems introduced

by.others.will. not reflect on the original authors' reputations. Finally, any free program is threatened constantly by software patents...
We.wish.to.avoid. the.

danger.that.redistributors.of.a.
free.program. will individually obtain patent licenses, in effect making the program proprietary.. . To prevent

this, we have made it clear that any patent must be licensed for everyone's free use or not licensed.
at.all. The precise terms and conditions for copying, distribution and modification follow. GNU.GENERAL.
PUBLIC.LICENSE TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION ..
0..This.License.applies.to.any.program.or.other.

work.which.contains.a.notice.placed.by.the. copyright.holder.
saying.it.may.be.distributed.under.
the.terms.of.this.General.

Public.License.. . The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or

any.derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or
translated. into. another. language.. . (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as
"you". Activities other than copying, distribution and modification are not covered by this License; they are outside its

scope...The.act.
of.running. the Program is not restricted, and the output from the Program is covered only if its

contents.constitute.a.work.based.on.the.Program. (independent.of.
having.been.made.by.running.
the.Program)..Whether.that.
is.true.depends.on. what.the.Program.does. ..

1..You.may.copy.and.distribute.verbatim.copies.of.
the.Program's.source.code.as.
you.receive. it, in any medium, provided that you conspicuously. and. appropriately.
publish. on. each. copy. English an appropriate copyright notice and disclaimer.

of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program. You may charge a fee for the physical act of

transferring a copy, and you may at your option offer warranty protection in exchange for a fee. . . 2. You may modify your copy or copies.

of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions: a) You must cause the modified files to carry prominent notices stating that

you changed the files and the date of any change. . . . b) You must cause any work that

you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties

under the terms of this License. c) If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice.

and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how

to view a copy of this License. . . (Exception: if the Program itself is interactive but does not normally print

such an announcement, your work based on the Program is not required to print an announcement.) These requirements apply to the modified work as a whole. . . If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent

and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works.

. . . But when you distribute the same sections as part of a whole which

is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it. Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control

the distribution of derivative or collective works based on the Program. In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of

a storage or distribution medium does not bring the other work under the scope of this License. . . 3.

. You may copy and distribute the Program (or a work based on it, under Section 2) in object code

or executable form under the terms of Sections 1 and 2 above provided that you also do one of the

following: . . . a) Accompany it with the complete

corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium

customarily used. . . . @ @ copy of the corresponding @ @ source code. . . (This alternative is allowed only

for noncommercial distribution and only if @ @ form of the work for making modifications to it @ @ @ @ need not include anything that is @ @ If distribution of executable or object code

is made by offering access to copy from a designated place, then offering equivalent access to

copy the source code from the same place @ @ the source along with the object code. 4. @ @ under this License. .

. Any. attempt. @@@@parties.remain.in.full.compliance. 5. @@@@actions.

are.prohibited.by.law.if.you.do.not.accept.this.License. @@@@.

.6..Each.time.

you.redistribute.the.Program.(or.

@@. You.may.not.impose.any.further.restrictions.on.the.

recipients'. exercise. of. the. rights. granted. herein.



[You're reading an excerpt. Click here to read official TOSHIBA](#)

[BDX-1100-KB user guide](#)

<http://yourpdfguides.com/dref/3873130>

. You are.
not responsible for enforcing compliance
by third parties to this.
License. 7. @ other reason (not limited to patent issues), conditions are imposed on you (whether by @ excuse.

you from the conditions of this License...If
you cannot distribute so as
to satisfy @ of the Program.
by all those who receive @ of any portion of this.

section is held invalid or unenforceable under any particular @ apply
in other circumstances. It is
not the purpose of this
section to induce you to infringe any patents or other

property right claims or to contest validity of any such
@ contributions to the wide range
of @ is up to the
author/donor to decide if he or she is willing to

distribute software through any other system and a licensee cannot
impose that choice. This section
is intended to make thoroughly
@ .8. If the distribution and/or use of

the Program is restricted in certain countries either by @ this.
License may add an explicit
geographical distribution limitation excluding those
@ .9. The Free Software Foundation may publish

@ . Such new versions will be similar in spirit to
the @ Each version is given
a distinguishing version number. @ version
or of any later version published by the Free Software

Foundation... If the Program does @ the Free Software
Foundation. . . 10.

If you wish to incorporate
parts of the Program into other free programs whose distribution conditions are different, write to the author.

to ask for permission... For software which is
copyrighted by the Free Software
Foundation, write to the Free Software Foundation; we sometimes make exceptions for
this... Our decision will be guided by the

two goals of preserving the free status of all derivatives
of our free software and
of promoting the sharing and
reuse of software generally.

.....

.....

NO WARRANTY . . 11.

. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT
PERMITTED BY APPLICABLE LAW.

.. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS.

AND/OR OTHER PARTIES PROVIDE THE PROGRAM

"AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED
WARRANTIES OF MERCHANTABILITY AND FITNESS.

FOR A PARTICULAR PURPOSE... THE ENTIRE RISK AS TO

THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU.

... SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR
CORRECTION. . . 12.

IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED.

TO.IN.WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY.WHO.MAY.MODIFY.AND/OR REDISTRIBUTE.THE.PROGRAM.
AS.PERMITTED. ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL
DAMAGES.ARISING OUT.OF.THE.USE.

OR.INABILITY.TO.USE.THE. PROGRAM.(INCLUDING.BUT.NOT.LIMITED TO.

LOSS.OF.DATA.OR.DATA.BEING.RENDERED. INACCURATE.OR.LOSSES.

SUSTAINED.BY YOU.OR.THIRD.PARTIES.

OR.A.FAILURE.OF.THE.

PROGRAM.TO.OPERATE.WITH.ANY.OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER.PARTY.HAS.BEEN.ADVISED.

OF.THE.POSSIBILITY.OF.SUCH.DAMAGES.

....END.

OF.TERMS.AND.CONDITIONS ..

How.to.Apply.These.Terms.to.Your.New.Programs If you develop a new program, and you want it.to.

be.of.the.greatest.possible.use.to.the.public, the best way to achieve this is to make it free. software.

which. everyone. can. redistribute. and.

change.under.these.terms. To do so, attach the following notices to the program.

..It.is.safest.to.attach.them.to.the.

start. of each source file to most effectively convey the exclusion of warranty; and each file should have.at.least.the."copyright".line.and.a.pointer.

to.where.the.full.notice.

is.found. ...

.<one.line.to.give.the.program's.name.and.a.

brief.idea.of.what.it.does.>

Copyright.(C).<year>..<name.

of.author> This program is free software; you can redistribute. it. and/or. modify.

it. under. the. terms. of.the.GNU.General.Public.License.

as.published. by the Free Software Foundation; either version 2 of the License, or (at your option) any later.version.This.program.

is.distributed.in.the.hope.

that.it. will be useful, but WITHOUT ANY WARRANTY; without. even. the.

implied. warranty. of. MERCHANTABILITY.or.FITNESS.FOR.A.PARTICULAR. PURPOSE.

..See.the.GNU.General.Public.License. for.more.

details.

You.should.have.received.a.

copy.of.the.GNU. General Public License along with this program; if not, write to the Free Software Foundation, Inc.,51 Franklin Street, Fifth Floor, Boston,

MA 02110-1301.USA. English 0 Also.add.information.

on.how.to.contact.you.by. electronic.and.paper.mail.

If the program is interactive, make it output a short.notice.like.this.when.

it.starts.in.an.interactive.

mode: Gnomovision version 69, Copyright (C) year name.of.authorGnomovision.comes.with.ABSOLUTELY.

NO. WARRANTY; for details type `show w'. This is free software, and you are welcome to redistribute it under certain conditions; type `show c' for details.

The hypothetical commands `show w' and `show c' should show the appropriate parts of the General Public License. Of course, the.commands.you.use.may.be

called something other than `show w' and `show c'; they could even be mouse-clicks. or.

menu. items--whatever. suits. your.program.

You.should.also.get.your.

employer.(if.you.work. as a programmer) or your school, if any, to sign a "copyright disclaimer" for the program, if necessary. @@in. the. program.

Gnomovision'. (which.

makes. passes. at. compilers). written. by. James. Hacker. @@@@51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA. .

Everyone. is. permitted. to. copy.

and. distribute. @@@@Library Public License, version 2, hence the version.number.2.

1.J.

.....

....

....

.....Preamble. . .The.

licenses.for.most.software.are.designed.to. take.away.your.

freedom.to.share.and.change.

it. . By contrast, the GNU General Public Licenses. are.

intended. to. guarantee. your. freedom.to.share.and.change. .

*. . . . free.software--to.make.sure.the.software.
is.free.for.all.its.*

*users.. This license, the Lesser General Public License, applies. to.
some. specially. designated. software. packages--typically. libraries--of. the. Free. Software.Foundation.*

and.other.authors.who.decide. to use it. @@@@. . . .

*. . . .
.. @Our General Public.Licenses.are.
designed.to.make.sure.that you. have. the. freedom. to. distribute.*

*copies. of. free.software.(and.charge.for.this.service.if.
you. @@. . . . To protect your rights, we need to make restrictions.
that.forbid.. distributors. to.
deny. you. these.rights.or.to.ask.you.to.surrender.*

*these rights...These.restrictions.translate.to. certain.responsibilities.for.
you.if.you. distribute.copies.
of.the.library.or.if.*

you.modify.it.. For example, if you distribute copies of the library, whether gratis or for a fee, you must give the recipients all the.rights.that.we.gave.

*. you. You must make sure that they, too, receive.or.can.get.the.source. code..
.If.you.link. other code with the library, you must provide 1 English complete object files to the recipients, so that they.
can.relink.them.with.the.
library.after.making. changes. to. the. library. and. recompiling. it.*

*. . . . And.you.must.show.them.these.terms.so.
they. know.their.rights..*

*We.protect.your.rights.with.a.two-step.method: (1) we copyright the library, and (2) we offer you this license, which gives you legal permission to copy,
distribute and/or modify the library.. .*

*. . . . To protect each distributor, we want to make it.very.clear.that.there.is.no.
warranty.for.the. free library. Also, if the library is modified by someone else and passed on, the recipients.
should.know.that.what.they.
have.is. not the original version, so that the original author's.reputation.will.not.be.affected.by. problems.*

that.might.



**[You're reading an excerpt. Click here to read official TOSHIBA
BDX-1100-KB user guide
http://yourpdfguides.com/dref/3873130](http://yourpdfguides.com/dref/3873130)**